

BHARAT HEAVY ELECTRICALS LIMITED

TRANSMISSION PROJECTS ENGINEERING MANAGEMENT



DOCUMENT No.	TB-398-316-003	Rev. No.	00	Prepared	Checked	Approved
TYPE OF DOC.	TECHNICAL SPECIFICATION			NAME	GV	MM
TITLE	245 kV Class Surge Arresters (198kV Surge Arrester)			SIGN	<i>[Signature]</i>	<i>[Signature]</i>
				DATE		
				GROUP	TBEM	W.O. No
CUSTOMER	UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)					
PROJECT	220kV GIS for 2x60 MW VYASI HEP AT VYASI, DISTT. DEHRADUN, UTTARAKHAND					

CONTENTS

COPYRIGHT AND CONFIDENTIALITY
 The information on this document is the property of BHARAT HEAVY ELECTRICALS LTD.
 It must not be used directly or indirectly in anyway detrimental to the interest of the company

S/N	Description	No. of Sheets
1.	SECTION-1: SCOPE, SPECIFIC TECHNICAL REQUIREMENTS	03
	ANNEXURE-I: BILL OF QUANTITIES	01
2.	SECTION-2: EQUIPMENT SPECIFICATION	05
3.	SECTION-3: PROJECT DETAILS & GENERAL SPECIFICATIONS	15
	Annexure-II: CORONA AND RIV TEST/ SEISMIC WITHSTAND TEST PROCEDURE	03
4.	SECTION-4: GUARANTEED TECHNICAL PARTICULARS	01
5.	SECTION-5: CHECK LIST	02
	Annexure-A: Schedule of technical deviation	01
	Annexure-III: Checklist for TE	01

Rev No.	Date	Altered	Checked	Approved	REVISION DETAILS	
Distribution				To	TBMM	OFFICE COPY
				Copies		

SECTION 1

SCOPE, SPECIFIC TECHNICAL REQUIREMENTS

1.0 SCOPE

This technical specification covers the requirements of design, manufacture, testing at works, packing and dispatch of 198kV non-linear metal oxide resistor type Surge arrester complete with all accessories like surge counter, leakage / grading current meter, insulating base, connecting lead, fixing hardware etc.

In case of any conflict between the technical details mentioned in this section and the remaining sections of this document, then Section-1 shall prevail and is to be considered as binding requirement.

Surge arrestors are required for the following Project:

Customer : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Project : 220kV GIS for 2 x 60 MW VYASI HEP AT VYASI, DEHRADUN,
UTTARAKHAND

Refer Section-3 for Project Details and General Specifications.

2.0 BILL OF QUANTITIES – As per Annexure-I

3.0 SPECIFIC TECHNICAL REQUIREMENTS

Equipment shall perform satisfactorily under various other electrical, electromechanical and meteorological conditions of the site of installation.

All equipment shall be able to withstand all external and internal mechanical, thermal and electromechanical forces due to various factors like wind load, temperature variation, ice & snow, (wherever applicable) short circuit etc. for the equipment.

Refer Section-2 for Detailed Technical requirements.

ACCESSORIES REQUIRED

Note-1- Terminal connector shall be suitable for universal take off. The conductor details for terminal connector of Surge arrester shall be provided during Detailed Engineering.

Note-2- Insulated Connecting cable between Lightning Arrester and Surge monitor shall be supplied in single length for all required surge arresters including main and spare items considering individual length of 5 m. Please note that connecting lead, lugs and accessories shall be provided for each Lightning Arrester.

Note-3- Total quantity may vary up to $\pm 30\%$ at contract stage.

Note-4- Other standard fittings and accessories, which are not specifically mentioned but are usually provided with Surge Arrester of type and rating being offered for efficient and trouble free operation. Prices of accessories to be included in the equipment price.

Note-5- Following Hardware required for each surge arrester:

1. For Inter-Unit Connection Within Arrester
2. For Connecting the Arrester to structure (Structure in BHEL-Scope)
3. For Connecting the surge counter /monitor to the structure.
4. Earthing Hardware

3.0 DEVIATIONS:

The bidder shall list all the deviation from the specification separately. Offers without specific deviation will be deemed to be totally in compliance with the specification and NO DEVIATION on any account will be entertained at a later date.

4.0 SPECIAL TOOLS AND TACKLES

Bidder shall supply all special tools and tackle free of cost which are specifically required for the Surge Arrestor and are proprietary in nature. List of such special tools and tackle should be clearly listed along with the technical offer. Any special tool which is not listed in the list but required during the erection/ testing/ commissioning of Surge Arrestor shall also be supplied free of cost by Bidder.

5.0 TYPE TESTING

Bidder shall submit valid type test reports (as per relevant IEC/IS standard) for the tests carried out after 08.05.2007. The reports should have been conducted on identical or similar equipment/components to those offered. In case type test reports are more than 10 years old or if any type report is found to be technically unacceptable, such type test(s) shall be conducted by the bidder free of cost without any cost and delivery implication to BHEL/UJVNL.

6.0 PACKING

6.1 All equipment shall be suitably protected, coated, covered or boxed and crated to prevent damage or deterioration during transit, handling and outdoor storage (for a minimum period of 2 years) at site till the time of erection. While packing all the materials, the limitations from the point of view of availability of transportation facilities in India should be taken into account. The Bidder shall be responsible for any loss or damage during transportation, handling and storage.

6.2 The Bidder shall include and provide for security, protection and packing the equipment so as to avoid loss or damage during transport by any mode.

6.3 All packing shall allow for easy removal and checking at site. Wherever necessary, proper arrangement for attaching slings for lifting shall be provided. All packages shall be clearly marked for with signs showing 'UP' and 'DOWN' side of boxes, and handling and unpacking instructions as considered necessary. Special precautions shall be taken to prevent rusting of steel and iron parts during transit and storage. Gas seals or other methods proposed to be adopted for protection against moisture during transit shall be to the satisfaction of the purchaser.

6.4 The cases containing easily damageable material shall be very carefully packed and marked with appropriate caution symbols i.e. FRAGILE, HANDLE WITH CARE, USE NO HOOKS etc.

6.5 Each package delivered under the contract shall be marked by the Bidder at his expense and such marking must be distinct (all previous irrelevant marking being carefully obliterated). Such marking shall show the description and quantity of contents, the name of consignee and address, the gross and net weights of the package, the name of Bidder with a distinctive number of mark sufficient for purpose of identification. All markings shall be carried out with such materials as to ensure quickness of drying, fastness and legibility.

6.6 Each Package shall contain a note quoting specifically the name of the Bidder, the number and date of contract or order and the name of office placing the contract, nomenclature of the stores and include a schedule of parts for each complete equipment giving the parts number with reference to the General Arrangement/ Assembly drawing and the quantity of each part, drawing number and tag numbers.

6.7 All equipment/ material shall be suitably packed for transport, carriage at site and outdoor storage during transit. The Bidder shall be responsible for any damage to the equipment during transit. The contents of each package shall bear marking that can be readily identified from the package list and packing shall provide complete protection from moisture, termites and mechanical shocks etc.

6.8 Any material found short inside the packing cases shall be supplied by the Bidder without any extra cost.

6.9 Notwithstanding anything stated in this clause the Bidder shall be entirely responsible for any loss, damage or depreciation to the stores.

Project:	220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND	TB-398-316-003 REV.00 ANNEXURE-I	
Bill of quantities for Surge Arresters			
S.No.	DESCRIPTION	Unit	QTY.
A	<u>Main Quantity</u>		
1	198 kV, 25mm/kV Surge arrester (single phase) complete with all accessories like corona ring(if required) terminal pad, surge counter, leakage/grading current meter, insulating base, lugs for connecting cable, fixing hardware etc.	Nos.	6
2	198 kV Surge Arrester terminal connector suitable for single/twin conductor	Nos.	6
3	Insulated connecting cable between Surge Arrester and surge Monitor (Single length)	m	30
B	<u>Mandatory Spares</u>		
1	198 kV, 25mm/kV Surge arrester (single phase) complete with all accessories like corona ring(if required) terminal pad, surge counter, leakage/grading current meter, insulating base, lugs for connecting cable, fixing hardware etc.	Nos.	1
Note:			
1	Quantity Variations: Total quantity may vary upto +/- 30% at contract stage.		

SECTION-2 EQUIPMENT SPECIFICATIONS

1.0 GENERAL:

1.1 The Surge arresters shall conform to IEC: 60099-4 and IEC-60037 WG-4 except to the extent modified in the specification.

1.2 Arresters shall be of hermetically sealed units, self-supporting construction, suitable for mounting on tubular support structures to be supplied by the Contractor.

1.3 The Surge Arrestors shall be designed for use in the geographic and meteorological conditions as given in Specifications.

2.0 DUTY REQUIREMENTS:

a. The surge arresters shall be of heavy duty station class and gapless type without any series or shunt gaps.

b. The surge arresters shall be capable of discharging over-voltages occurring during switching of unloaded transformers, reactors and long lines.

c. 245 kV class arrester shall be capable for discharging energy equivalent to class 3 of IEC for 245 kV system on two successive operations.

d. The surge arresters shall be suitable for withstanding forces as given in specification.

e. The reference current of the arresters shall be high enough to eliminate the influence of grading and stray capacitance on the measured reference voltage.

f. The surge arresters are being provided to protect the following equipment whose insulation levels are indicated in the table given below: -

Equipment to be protected	Lightning impulse(kVp) for 800 kV system	Switching Surge for 800 kV system	Lightning impulse(kVp) for 420 kV system	Switching Surge for 420 kV system	Lightning impulse(kVp) for 245 kV system	Lightning Surge for 145 kV system
Power transformer	±1950	±1550	±1300	±1050	±950	±550
Instrument Transformer	±2100	±1550	±1425	±1050	±1050	±650
Reactor	±1950	±1550	±1300	±1050	--	--
CB/Isolator Phase to ground	±2100	±1550	±1425	±1050	±1050	±650
CB/Isolator Across open contacts	±2100 (-/+457)	±1140 (-/+653)	±1425 (/+240)	±900 (-/+345)	±1050(for CB) ±1200(for iso)	±750

g. The duty cycle of CB installed in 245kV System of the Purchaser shall be O-0.3 sec-CO-3 min-CO. The Surge Arrester shall be suitable for such circuit breaker duties in the system.

3.0 CONSTRUCTIONAL FEATURES:

The features and constructional details of surge arresters shall be in accordance with requirement stipulated hereunder:

- a) The non-linear blocks shall be of sintered metal oxide material. These shall be provided in such a way as to obtain robust construction, with excellent mechanical and electrical properties even after repeated operations.
- b) The surge arresters shall be fitted with pressure relief devices suitable for preventing violent failure of insulator housing and providing path for flow of rated fault currents in the event of arrester failure. Details shall be furnished in the bids along with quality checks.
- c) The arresters shall not fail due to arrester insulation contamination.
- d) Seals shall be provided in such a way that these are always effectively maintained even when discharging rated lightning current.
- e) The outer insulator housing shall be so coordinated that external flashover will not occur due to application of any impulse or switching surge voltage up to the maximum design value for arrester.
- f) The end fittings shall be made of corrosion proof material and preferably be nonmagnetic.
- g) The name plate shall conform to the requirements of IEC incorporating the year of manufacture.
- h) The heat treatment cycle details along with necessary quality checks used for individual blocks alongwith insulation layer formed across each block are to be furnished. Metalizing coating thickness for reduced resistance between adjacent discs is to be furnished with additional information schedule of bid proposal sheets alongwith procedure for checking the same. Details of thermal stability test for uniform distribution of current on individual disc is to be furnished.
- i) The manufacturer will submit Data for rejection rate of ZnO blocks during manufacturing/operation for the past three years.
- j) The sealing arrangement of the Surge Arrester stacks shall be done incorporating grooved flanges with the O-rings/elliptical cross-section gaskets of Neoprene or Butyl rubber.
- k) The Surge arrester with porcelain housing shall have a cantilever strength of not less than ~~500kg, 500 kg, 350 kg and 350 kg~~ for ~~624/390/216/120kV~~ surge arresters respectively. For Surge arrester with polymer housing, the cantilever strength shall not be less than 150kg.

4.0 FITTINGS AND ACCESSORIES:

- a) Arresters shall be complete with insulating base having provision for bolting to flat surface of structure.

b) Self-contained discharge counters, suitably enclosed for outdoor use and requiring no auxiliary or battery supply for operation shall be provided for each single pole unit along with necessary connection. Suitable leakage current meters should also be provided. The reading of milliammeter and counters shall be visible through an inspection glass panel. The terminals shall be robust and of adequate size and shall be so located that incoming and outgoing connections are made with minimum possible bends. The surge counter shall be provided with a potential free contact rated for 220 Volt (DC) which shall close whenever a surge is recorded by the surge monitor. Necessary arrangement shall be provided for extending the contact information to Substation Automation System/RTU.

c) Surge monitor consisting of discharge counters and milliammeters should be suitable to be mounted on support structure of the arrester and should be tested for IP66 degree of protection. The standard supporting structure for surge arrester should be provided with a mounting pad, for fixing the surge monitor. The surge monitor should be suitable for mounting on this standard mounting pad. Also all nuts, bolts, washers etc. required for fixing the surge monitor shall have to be supplied by the Contractor.

The arrangement for Surge Monitor enclosure fixing to the structure shall be at its rear/bottom. Connection between the Surge Arrester base and Surge Monitor shall be through a 5 m (minimum) long insulated copper cable flexible of at least 70 sq.mm cross sectional area. The cable shall be terminated at rear/bottom side of the Surge Monitor. The gaskets of the surge monitors shall be of Neoprene, Butyl or equivalent material.

d) Grading/corona rings shall be provided on each complete arrester unit as required. Suitable terminal connectors shall be supplied by the Contractor.

5.0 TESTS:

5.1 The surge arresters should have been type tested as per IEC/IS and shall be subjected to routine and acceptance tests in accordance with IEC document. The test reports of the type tests as per IEC-60099-4 and the following additional type tests shall also be submitted for the Employer's review.

- i) Radio interference voltage test.
- ii) Seismic withstand test as per Annexure-II
- iii) Accelerated aging test.
- iv) Test to verify the Power frequency versus time characteristics.

Each metal oxide block of surge arresters shall be tested for the guaranteed specific energy capability in addition to the routine/acceptance test as per IEC: 60099-4.

5.2

(a) Acceptance Tests:

1. Measurement of power frequency reference voltage of the arrester units.
2. Lightning Impulse Residual voltage on arrester units. (IEC clause 6.3.2).
3. Internal Ionisation or partial Discharge test.

(b) Special Acceptance Test:

1. Thermal stability test on three sections. (IEC Clause 7.2.2).
2. Aging test for Zinc oxide blocks as an acceptance test is to be carried out on 3 samples for 72 hours at maximum continuous over voltage (MCOV) and at a temperature of 115°C. Acceptance norm being Ir (resistive current)/watt loss shall remain or decrease at the end of 72 hrs from the value taken after 1 hour of start of test.
3. Wattloss test.

(c) Routine Tests:

1. Sealing test: Water dip test at 1.5m depth from top of Surge Arrestor for 30 minutes shall be performed during assembly of Surge Arrester stacks (followed by other routine tests, i.e. P.D. Measurement, Reference Voltage, Residual Voltage & IR measurement).
2. Measurement of reference voltage.
3. Residual voltage test of arrester unit.
4. Internal Ionisation test or partial discharge test.
5. Verticality check on completely assembled Surge arresters as a sample test on each lot.

(d) Routine Test on Surge Monitors:

The Surge monitors shall be connected in series with the test specimens during residual voltage and current impulse withstand tests to verify efficacy of the same. Additional routine/functional tests with one 100A and 10kA current impulse (8/20 micro sec.) shall also be performed on the Surge monitor.

Surge monitors shall be routinely tested for water dip test at 1.5m for 30 minutes. No water vapours shall be visible on the monitor glass.

(e) Test on insulators

All routine tests shall be conducted on the hollow column insulators as per IEC 62155. Polymer housing shall be tested in accordance to IEC-61462.

6.0 SPARE PARTS AND MAINTENANCE EQUIPMENT:

Bidder shall include in his proposal spare parts and maintenance equipment.

7.0 TECHNICAL PARAMETERS:

A. 245 kV CLASS SURGE ARRESTER

- | | |
|---------------------------|--|
| a) Rated arrester voltage | 198 kV |
| b) Rated System voltage | 245kV |
| c) Rated Frequency | 50 Hz |
| d) Nominal discharge | 10 kA of 8/20 microsecond current wave |
| e) System fault rating | 50kA for 1 s |

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND

CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Technical Specification of 245kV Class Surge Arrester

TB-398-316-003 REV.00

f) Minimum discharge capability	5kJ/kV (referred to rated arrester voltage correspond to min. discharge characteristics.
g) Continuous operating voltage at 50 deg.C	168 kV rms
h) Max. switching surge residual voltage (1kA)	455 kVp
i) Max. residual voltage at	
i) 5 kA	-
ii) 10 kA nominal discharge current	550 kVp
j) Max. steep current impulse residual voltage at 10 kA	600 kVp
k) Long duration discharge class	3
l) High current short duration test Value (4/10 micro second wave)	-
m) Current for pressure relief test	50 kA rms
n) Low current long duration test value (2400 micro sec)	As per IEC.
o) Pressure relief class	50 kA
p) Creepage distance	25mm/kV
q) Minimum Creepage distance	6125mm
r) Rated insulation levels	
i. Full wave Impulse withstand voltage (1.2/50 microsec.)	±1050kVpeak
ii. One minute power frequency dry and wet withstand voltage (rms)	460kV rms
s) Partial discharge at 1.05 COV	Not exceeding 10pC
t) Max. Radio Interference Voltage for frequency between 0.5 MHz and 2 MHz	500 micro- Volt (at 156kV rms)
u) Cantilever strength of the surge Arrester	150kg (Min.) (For Polymer insulator) 350kg (Min.) (For Porcelain insulator)
v) System neutral earthing	Effectively Earthed
w) Applicable References	IEC 60099-4

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

SECTION-3

3.0 GENERAL

This section stipulates the General Technical Requirements under the Contract and will form an integral part of the Technical Specification.

The provisions under this section are intended to supplement general requirements for the materials, equipment and services covered under other respective sections and are not exclusive. However in case of conflict between the requirements specified in this section and requirements specified under other sections, the requirements specified under respective sections shall hold good.

3.1 PROJECT INFORMATION AND SYSTEM PARAMETERS

a)	Customer/ Purchaser/ Owner	Uttarakhand Jal Vidhyut Nigam Limited
b)	Project Title	220kV switchyard for 2 X 60MW Vyasi HEP
c)	Location	Village Vyasi, 5.0 Km.d/s of Lakhwar, Dehradun
d)	Elevation above MSL	535 m
e)	Transport Facilities	Airport ,Railways at Dehradun, accessible by Road from National Highway NH-123 at Barawala (3 km from Dakpathar).
f)	Postal Address	To follow
SITE CONDITIONS		
a)	Max. temp.	42.8°C
b)	Min. temp.	0.3°C
c)	Design ambient temp.	40°C
d)	Latitude/Longitude	30° 31' 00" N/ 77° 53' 00" E
e)	Maximum Relative humidity	100 %
f)	Minimum Relative humidity	8%
g)	Pollution Severity	Less Polluted
h)	Seismic acceleration	0.18g
i)	Seismic zone	Zone-IV
I)	Wind Velocity & Zone	47 m/s Zone IV

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

SYSTEM PARAMETERS :

Nominal system voltage	220 kV
Highest system voltage	245 kV
Rated Normal Current at Nominal System Voltage	1600 A
Basic Impulse level	1050 kVP
Power frequency withstand voltage	460 kVrms
Switching Impulse voltage	850 kV -
Maximum Permissible Switching Over Voltage to Earth (kV)	487 kV
Frequency	50 Hz $\pm$ 5%
Rated short time current	50 kA for 1 sec
Creepage distance	25 mm/kV
System Earthing	Solidly Grounded

Note: -

Seismicity: -The project is situated in a seismic zone and falls within Zone IV of the seismic zoning Map of India. Value of peak ground acceleration has been recommended as 0.36g for maximum Credible Earthquake (MCE) and 0.18g for Design Basis Earthquake (DBE).

Wind Load: - The basic wind load as per IS875 (part-3) shall be applied on the vertical projected area, multiplied with the applicable factor for different type of structures.

AUXILIARY POWER SUPPLY

3 phase A.C power supply	415V, 50 Hz, 3-phase 4 wire, solidly earthed with variation in frequency of $\pm$ 5% and variation in voltage $\pm$ 10%.
1 phase A.C power supply	240V, 50 Hz, 1-phase, AC supply with variation in frequency of $\pm$ 5% and variation in voltage $\pm$ 10%.
D.C. power supply	220V (variation under worst condition from 198V to 242V) , 2-wire ungrounded, 50V, 2 wire system (+) earthed , 48V $\pm$ 20%

Transportation Limitations: - For shipments, the Manufacturer shall pack the items to meet size and weight restrictions of the Indian railways and road systems. Shipments from Manufacturer's work (in case of foreign manufacturer) shall travel to the Port of entry in India, from where these will be transported, after necessary port clearances etc., by the Contractor to Dehradun, which shall be the nearest rail head for the Project, and further transported to site. However, in certain cases the Contractor may be required to transport the materials from Point of entry to Dehradun and further to Vyasi HE Project site directly by road transport. However, Indian contractors shall be responsible in all respects for transportation of all materials and equipment up to the project site. Manufacturers shall consult with the concerned authorities of railways and highways to ensure that their packaging will be such as to permit them to transport the plant and equipment within such imposed limits. Manufacturers shall arrange to deliver the maximum size subassemblies consistent with safe and convenient transport. All materials and equipment etc. arrived at

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Dehradun will be unloaded from rail wagons and reloaded on to road transport for shipment to project site by the Contractor. The roads and bridges en-route shall be made suitable for 70R loading capacity.

3.2 GENERAL TECHNICAL REQUIREMENT

3.2.1 TYPE TESTS

For all the items of equipment's, bidder shall furnish copies of Type Tests Certificates for the equipment's of the type and ratings similar to those specified. Type Tests Certificates furnished shall be as per the provisions of relevant standards for such equipment's. In case the contractor is not in position to furnish, such type tests certificates or the type tests certificate furnished by him are not as per the relevant standard for such equipment and, therefore, not acceptable to the Employer, Type Test for such items and equipment's will have to be conducted by the contractor at his cost.

All the switchyard equipment's shall be type and routine tested as per relevant IS / IEC- Publication or Type tests certificate shall be furnished to prove that the equipment fulfils all characteristics defined in Specifications. The contractor is required to carry out all type tests on one apparatus of each type and routine tests on all apparatus and submit the reports to the Employer. If approved by the Employer, type test certificates can be accepted in place of type tests in case of the same have been carried out on same type & similar capacity. All equipment/systems to be supplied shall conform to type tests as per relevant standards and proven type.

The Bidder / Contractor shall furnish the reports of all the type tests carried out after **08.05.2007** as listed in relevant clauses in respective electrical specification and relevant standards for all components / equipment / systems. These reports should be for the tests conducted on identical/similar components/equipment/systems to those offered/proposed to be supplied under this contract.

Type tests done in an independent government laboratory or in the presence of representative of State Electricity Board or other reputed public undertakings, the type test reports of the same shall be submitted for scrutiny /approval. If these are found suitable and technically acceptable, conducting of type tests shall be waived off.

In case Contractor is not able to submit report of type test(s) conducted in last ten years, or in case type test report(s) are not found to be meeting the specification/relevant standard requirements, then all such tests shall be conducted by the Bidder free of cost to Employer/Purchaser, and reports shall be submitted for approval. No charges shall be paid under this contract. All acceptance and routine tests as per relevant standards and specification shall be deemed to be included in the bid price.

3.2.2 CODES AND STANDARDS

All materials and equipment shall generally comply in all respect with the latest edition of relevant international electro-technical commission (IEC) or any other internationally accepted standard which ensure equal or better quality or relevant Indian standard(IS) mentioned against each equipment and this specification.

3.3 MATERIAL/WORKMANSHIP

3.3.1 General Requirement

Where the specification does not contain characteristics with reference to workmanship, equipment, materials and components of the covered Equipment it is understood that the same must be new, of highest grade of the best quality of their kind conforming to best engineering practice and suitable for the purpose for which they are intended. All design calculations, materials, works, manufacturing and testing shall conform to the latest applicable standards.

The design of the Works shall be such that installation, future expansions, replacements and general maintenance may be undertaken with a minimum of time and expenses. Each component shall be designed to be consistent with its duty and suitable factors of safety, subject to mutual agreements and shall be used throughout the design. All joints and fastenings shall be devised, constructed and documented so that the component parts shall be accurately positioned and restrained to fulfill their required function. In general screw threads shall be standard metric threads. The use of other thread forms will only be permitted when prior approval has been obtained from purchaser.

Whenever possible, all similar part of the Works shall be made to gauge and shall also be made interchangeable with similar parts. All spare parts shall be interchangeable with, and shall be made of the same materials and workmanship as the corresponding parts of the Equipment supplied under the Specification. Where feasible, common component units shall be employed in different pieces of equipment in order to minimize spare parts stocking requirements. All equipment of the same type and rating shall be physically and electrically interchangeable.

All materials and equipment shall be installed in strict accordance with the manufacturer's recommendation(s). Only first-class work in accordance with the best modern practices will be accepted. Installation shall be constructed as being the erection of equipment at its permanent location. This, unless otherwise specified, shall include unpacking, cleaning and lifting into position, grouting, leveling, aligning, coupling of or bolting down to previously installed equipment bases/foundations, performing the alignment check and final adjustment prior to initial operation, testing and commissioning in accordance with the manufacturer's tolerances and instructions and the Specification. All factory assembled rotating machinery shall be checked for alignment and adjustments made as necessary to re-establish the manufacture's limits suitable guards shall be provided for the protection of personal on all exposed rotating and / or moving machine parts and shall be designed for easy installation and removal for maintenance purpose. The spare equipment(s) shall be installed at designated locations and tested for healthiness.

The Contractor shall apply oil and grease of the proper specification to suit the machinery, as is necessary for the installation of the equipment. Lubricants used for installation purposes shall be drained out and the system flushed through where necessary for applying the lubricant required for operation. The Contractor shall apply all operational lubricants to the equipment installed by him.

All oil, grease and other consumables used in the Works/ Equipment shall be purchased in India unless the Contractor has any special requirement for the specific application of a type of oil or grease not available in India. In such is the case he shall declare in the proposal, where such oil or grease is available. He shall

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

help purchaser in establishing equivalent Indian make and Indian Contractor. The same shall be applicable to other consumables too.

3.3.2 Provisions For Exposure to Hot and Humid climate

Outdoor equipment supplied under the specification shall be suitable for service and storage under tropical conditions of high temperature, high humidity, heavy rainfall and environment favorable to the growth of fungi and mildew. The indoor equipment located in non-air conditioned areas shall also be of same type.

3.4 COLOUR SCHEME AND CODES FOR PIPE SERVICE

The contractor shall propose a color scheme for those equipment/Items for which the colour scheme has not been specified in the specification for the approval of purchaser. The decision of purchaser shall be final. The scheme shall include:

Finishing colour of Indoor equipment

Finishing colour of Outdoor equipment.

Finish colour of all cubicles.

Finishing colour of various auxiliary system equipment including piping

Finishing colour of various building items.

All steel structures, plates etc shall be painted with non-corrosive paint on a suitable primer. It may be noted that normally all electrical equipment in switchyard are painted with shade RAL 7032. All The indoor cubicles shall be of same colour scheme and for other miscellaneous items, colour scheme will be approved by the purchaser.

3.5 PROTECTION

All coated surfaces shall be protected against abrasion, impact, discoloration and any other damages. All exposed threaded portions shall be suitably protected with either a metallic or a non-metallic protecting device. All ends of all valves, pipings and conduit equipment connections shall be properly sealed with suitable devices to protect them from damage.

All equipment accessories and wiring shall have fungus protection, involving special treatment of insulation and metal against fungus, insects and corrosion. The parts which are likely to get rusted, due to exposure to weather should also be properly treated and protected in a suitable manner. Screens of corrosion resistant material shall be furnished on all ventilating louvers to prevent entry of insects.

3.6 FUNGISTATIC VARNISH

Besides the space heaters, special moisture and fungus resistant varnish shall be applied on the parts, which may be subjected or predisposed to the formation of fungi due to the presence or deposit of

nutrient substances. The varnish shall not be applied to any surface of part where the treatment will interface with the operation or performance of the equipment. Such surfaces or parts shall be protected against the application to the varnish.

3.7 SURFACE FINISH

All surfaces that are so indicated on the drawings or those that require machining for their intended function, or those that are usually machined according to good workshop practice shall be machined. Surface finish qualities shall be adequate for the intended use and shall be indicated on the Contractor's Drawings. Suitable measuring device such as scatter meter or other acceptable measuring device will be used to determine compliance with specified surface finish.

All interiors and exteriors of tanks, control cubicles and other metal parts shall be thoroughly cleaned to remove all rust, scales, corrosion, greases or other adhering foreign matter. All steel surfaces in contact with insulating oil as far as accessible, shall be painted with not less than two coats of heat resistant, oil insoluble, insulating paints.

All metal surfaces exposed to atmosphere shall be given two primer coats of zinc chromate and two coats of epoxy paint with epoxy base thinner. All metal parts not accessible for painting shall be made of corrosion resisting material. All machine finished or bright surfaces shall be coated with a suitable preventive compound and suitably wrapped or otherwise protected. All paints shall be carefully selected to withstand tropical heat and extremes of weather within the limit specified. The paint shall not scale off or wrinkle or be removed by abrasion due to normal handling. All external painting shall be as per RAL 7032.

Before delivery, all exposed, unfinished metal surfaces shall be cleaned and shop painted. Cleaning and Preparation of steel surfaces shall be in accordance with relevant standards and they shall be given at least one prime coat the same day. Paint shall be in accordance with applicable portions of relevant Indian and International standards. The colours of the paint will be selected at the Employer's option. All interior surfaces of the crane those are accessible for maintenance inspections shall also be completely painted. All other interior surfaces shall be painted with only the 1 coat of primer. The inside of all gear housings shall be painted with 2 coats of oil resisting enamel as recommended by the gear housing manufacturer. A quantity and type of paint equal to 15% of the paint used for the second and third coats shall be provided for field touchup work. Monorail hoists shall be painted with the manufacturer's standard finish. The colour of the paint will be subject to approval of the Employer/Customer.

3.8 GALVANIZING

All structural steel including ladders, platforms, hand rails and the like and all exterior and interior steel surfaces of outdoor Works, as well as bolts and nuts associated with galvanized parts shall be hot-dip galvanized, electrolytic galvanized or serialized, as may be appropriate to the particular case. Galvanizing shall be performed in accordance with VDE Standard 0210 (Verband Deutscher Elektrotechniker) or IS 4795:1996. For galvanizing, only original blast furnace raw zinc shall be applied, which shall have a purity of 98.5%. The thickness of the zinc coat shall be for bolts and nuts, approx. 60 micrometer.

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Conforming to latest version of IS:2629 or any other equivalent authoritative standard. However, hardware less than M12 size shall be electro-galvanized. Minimum weight of zinc coating shall be **610 gms. per square meter** and minimum thickness of coating shall be 85microns for all items thicker than 6mm. For items lower than 6 mm thickness, requirement of coating shall be as per relevant ASTM.

3.9 PACKING

The following details are to be clearly indicated in the material forwarding documents:

- a) Name and address of the consignee.
- b) Purchase order number.
- c) Name of supplier/s.
- d) Description of equipment / material.
- e) Net weight.
- f) Gross weight.

All the equipment's shall be suitably protected, coated, covered or boxed and crated to prevent damage or deterioration during transit, handling and storage at Site till the time of erection. On request of the purchaser, the Contractor shall also submit packing details/associated drawing for any equipment material under his scope of supply, to facilitate the purchaser to repack any equipment/ material at a later date, in case the need arises. Any material found short inside the packing cases shall be supplied by the supplier without any extra cost.

The cases containing easily damageable material shall be very carefully packed and marked with appropriate caution symbol i.e. fragile, handle with care, use no Hooks etc. All electrical parts shall be carefully protected from damage by sand, moisture, heat or humid atmospheric conditions by packing them in high-pressure polyethylene foil.

All the cable shall be supplied on nonreturnable wooden drums with adequate barrel diameter so as to avoid any damage to the cables and to withstand rough handling during transportation and storage. A layer of waterproof paper shall be applied to the surface of the drums and over the outer cable layer.

A circular space of at least 40mm shall be left between the cable and the lagging. Each drum shall carry the name of the manufacturer, the name of the Employer, his address, order number, item number, type, size length of cable, net and gross weight duly stenciled thereon.

3.10 HANDLING, STORING AND INSTALLATION

Contractor may engage manufacturer's Engineers to supervise if required for unloading, transportation to site, storing, testing and commissioning of the various equipment being procured by them separately. In case of any doubt/misunderstanding as to the correct interpretation of manufacturer's drawings or instructions, necessary clarifications shall be obtained from the purchaser. Contractor shall be held responsible for any damage to the equipment consequent to not following manufacturer's drawings/instructions correctly.

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Where assemblies are supplied in more than one section, contractor shall make all necessary mechanical and electrical connections between sections including the connection between buses. Contractor shall also do necessary adjustments/alignments necessary for proper operation of circuit breakers, isolators and their operating mechanisms. All components shall be protected against damage during unloading, transportation, storage, installation, testing and commissioning.

Contractor shall be responsible for examining all the shipment immediately of any damage, shortage, discrepancy etc. for the purpose of Purchaser's information only. Any demurrage, pilferage and other such charges claimed by the transporters, railways etc. shall be to the account of the Contractor. The Contractor shall be fully responsible, for the equipment/material until the same is handed over to the purchaser in an operating condition after commissioning.

The minimum phase to earth, phase to phase and section clearance along-with other technical parameters for the various switchyard voltage levels to be maintained shall be strictly as per the approved drawings.

The design and workmanship shall be in accordance with the best engineering practices to ensure satisfactory performance throughout the service life. If at any stage during the execution of the Contract, it is observed that the erected equipment(s) do not meet the above minimum clearances, the Contractor shall immediately proceed to correct the discrepancy at his risks and costs.

3.11 DEGREE OF PROTECTION

The supplier shall propose following Degree of protection for those equipment/Items for which the degree of protection has not been specified in the specification for the approval of BHEL/UJVNL. The decision of BHEL/UJVNL shall be final. The enclosures of the Control Cabinet, Junction boxes and Marshalling boxes panels etc. to be installed shall be provided with degree of protection as detailed here under:

- a) Installed outdoor: IP-55
- b) Installed indoor in air conditioned area: IP-42
- c) Installed in covered area IP:52
- d) For LT switchgear (AC & DC distribution Boards): IP-54

The degree of protection shall be in accordance with IS:13947, (Part-1)/IEC-947(Part-1). Type test report/or degree of protection test on each type of the box shall be submitted for approval. If necessary, the cubicles shall be equipped with automatically controlled heating elements for protection against internal condensation and moisture. All panels/cubicles shall have approximately 20% space for mounting of future devices. Door operated interior illuminating lamps, power socket for 240V 5 /15A and communication socket shall be provided in all panels.

3.12 RATING PLATES, NAME PLATES AND LABELS

The switchyard equipment shall have a rating plate with the information required by relevant IEC i.e. at least the following:

- Manufacturer's name
- Type number

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

- Serial number
- Rated Voltage
- Rated impulse withstand voltage
- Rated power frequency withstand voltage
- Rated frequency
- Rated current
- Rated short circuit breaking current
- Rated short time current (r.m.s), & duration Each instrument transformer must have its own rating plate with the information as required in IEC 600441 and IEC 60186.

3.13 EARTHING

The operating mechanism housing, control cabinets, support structure etc. shall be provided with two separate earthing terminals suitable for bolted connection to 50x6mm mild steel flat to be provided for connection to station earth mat.

Circuit breakers, LA, Isolator, CVT, CT, BPI shall be provided with two grounding pads suitable for connection to galvanized steel flat of Size 75X12 mm. Control panels, Relay panel, outdoor marshalling boxes, Junction boxes, lighting panels and distribution board shall be provided with two grounding pads, for connection to galvanized steel flat. The two pads shall be provided, one each at the middle of the two opposite sides of the bottom frame of the equipment. Earthing of hinged door shall be done by using a separate earth wire.

The Contractor shall connect all equipment included in the scope of delivery to the grounding system. In addition to the grounding through cable screens, all equipment such as cubicles, motors, etc. shall be connected directly to the grounding system using copper wire of area not less than 50 mm sq. at two different points. In general, all iron parts such as supports, covers, railing, etc. shall be connected to the grounding system. Each conductor shall have its own separate connection point. Pressed on closed shoes shall be used for connections to bars.

3.14 TERMINAL BLOCKS AND WIRING

Wiring within cubicles and equipment enclosures shall conform to requirements of this section unless otherwise specified. Control wiring shall be stranded copper and shall be not smaller than 1.5 mm sq. except as otherwise agreed by the Engineer.

Larger size wiring shall be used where needed for the current carrying capacity requirements. Cables shall have at least 1000 V grade PVC insulation except for 110V DC and telemetering or communication system equipment for which 650V and 300 V ratings respectively may be acceptable.

For current and potential transformer secondary circuits the minimum cross section of the conductors

shall not be less than 2.5mm sq. Wiring shall terminate at terminal blocks at one side only. Where tap connections are required, they shall be made on terminal blocks. Wiring shall be neatly arranged and laid in plastic conduits accessible from the front door. The conduits shall not be filled more than 70 %.

Each cubicle shall be provided with an earthing bar (PE) of sufficient cross section carrying any possible fault current without undue heating. All metallic parts of the cubicle not forming part of the live circuits, all instrument transformer terminals to be earthed and other earthing terminals as well as all cable screens and PE-wires shall be connected to the earthing bar.

The terminal blocks shall be located to allow a neat and easy connection work and shall be safely accessible while the equipment is in service. Control circuits and power circuits shall be completely separated by use of divided or separate terminal blocks. Power terminal blocks shall be rated in accordance with applicable standards and shall be provided with covers. Control wiring terminal shall be equipped with facilities for opening the circuit. It shall be possible to interchange a single terminal block for a new one without dismantling a whole row. Current transformer terminal blocks shall have provisions for short-circuiting and disconnecting. Not more than two wires shall be connected to any one terminal. Terminal blocks using screws acting directly on the wire will not be accepted. At least **20%** spare terminals shall be provided. Terminals shall be marked with printed labels.

Terminal blocks shall be 1100 V grade and have continuous rating to carry the maximum expected current on the terminals. Those shall be of moulded piece complete with insulated barriers stud type terminals, washers nuts and lock nuts. Screw clamp, overall insulated, insertion type, rail mounted terminals can be used in place of stud type terminals. But preferably the terminal blocks shall be non-disconnecting stud type equivalent to Elmex type CATM4, Phoenix cage clamp type of Wedge or equivalent. The Insulating material of terminal block shall be nylon 6.6 which shall be free of halogens, fluorocarbons etc.

Terminal block for current transformer and voltage transformer secondary leads shall be provided with test links and isolating facilities. The current transformer secondary leads shall also be provided with short circuiting and earthing facilities.

The terminal shall be that maximum contact area is achieved when a cable is terminated. The terminal shall have a locking characteristic to prevent cable from escaping from the terminal clamp unless it is done intentionally. The conducting part in contact with cable shall preferably be tinned or silver plated however Nickel plated copper or zinc plated steel shall also be acceptable. The terminal blocks shall be of extensible design. The terminal blocks shall have locking arrangement to prevent its escape from the mounting rails.

The terminal blocks shall be fully enclosed with removable covers of transparent, non-deteriorating type plastic material. Insulating barriers shall be provided between the terminal blocks. These barriers shall not hinder the operator from carrying out the wiring without removing the barriers.

The arrangements shall be in such a manner so that it is possible to safely connect or disconnect terminals on live circuits and replace fuse links when the cabinet is live. At least 20 % spare terminals shall be provided on each panel/cubicle/box and these spare terminals shall be uniformly distributed on all terminals rows.

There shall be a minimum clearance of 250mm between the first bottom row of terminal block and the

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

associated cable gland plate. Also the clearance between two rows of terminal blocks shall be a minimum of 150 mm. The Supplier shall furnish all wire, conduits and terminals for the necessary inter-phase electrical connection (where applicable) as well as between phases and common terminal boxes or control cabinets.

All input and output terminals of each control cubicle shall be tested for surge withstand capability in accordance with the relevant IEC Publications, in both longitudinal and transverse modes. The supplier shall also provide all necessary filtering, surge protection, interface relays and any other measures necessary to achieve an impulse withstand level at the cable interfaces of the equipment.

3.15 CONTROL CABINETS, JUNCTION BOXES, TERMINALS BOXES AND MARSHALLING BOXES FOR OUTDOOR EQUIPMENTS

All types of boxes, cabinets etc. shall generally conform to and be tested in accordance with IS-5039, IS-8623 or IEC-439, as applicable and the clause given below.

Control cabinet, Junction boxes, marshalling boxes & Terminal boxes shall be made of sheet steel or aluminium and shall be dust, water and vermin proof. Sheet used shall be least 2.0 mm cold rolled or 2.5mm hot rolled. The box shall be properly braced to prevent wobbling. There shall be sufficient reinforcement to provide level surfaces, resistance to vibrations and rigidity during transportation and installation. In case of aluminium enclosed box the thickness of aluminium shall be such that it provides adequate rigidity and long life as comparable with sheet of specified thickness. Cabinet/boxes shall be free standing floor mounting type, wall mounting type or pedestal mounting type as per requirements.

Removable plates with gaskets shall be fitted at the top and bottom of the box to provide the entry for conduit or cable. The door shall be provided with suitable gasket and fitted with a lock type handle. The door shall be hung on hinges having brass bodies and stainless steel pins. Each cable junction box shall be provided with terminals of adequate rating on the terminal strip of suitable thickness. Disconnecting (sliding) type terminal blocks shall be provided, to facilitate testing & maintenance without disconnecting the cables.

Multi block terminal board of 15 A, 500 V rating shall be provided to form in assembly of number of terminal block. Assembly may be secured with only two screws on the surface. There shall be provision on the strips to add more terminal in case of further requirement.

Cabinet /boxes shall be provided with double hinged doors with padlocking arrangements. The distance between two hinges shall be adequate to ensure uniform sealing pressure against atmosphere. The quality of gaskets shall be such that it does not get damaged/cracked during the operation of the equipment.

All door, removable covers and plates shall be gasketed all around with suitably profiled EPDM gaskets. The gasket shall be tested in accordance with approved quality plan. The quality of gasket shall be such that it does not get damaged /cracked during the years of the equipment or its major overhaul whichever is earlier. All gasketed surfaces shall be smooth, straight and reinforced if necessary to minimize distortion and to make a tight seal. Ventilating Louvers, if provided, shall have screen and filters. The screen shall be fine wire mesh made of brass.

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

All boxes/cabinets shall be designed for the entry of cables from bottom by means of weather proof and dust-proof connections. Boxes and cabinets shall be designed with generous clearances to avoid interference between the wiring entering from below and any terminal blocks or accessories mounted within the box or cabinet. Suitable cable gland plate projecting atleast 150 mm above from the base of the Marshalling Kiosk/box shall be provided for this purpose along with the proper blanking plates. Necessary number of cable glands shall be supplied and fitted on this gland. The gland shall project at least 25mm above gland plate to prevent entry of moisture in cable crutch. Gland plate shall have provision for some future glands to be provided later, if required.

3.16 SPACE HEATERS

The space heaters shall be suitable for single phase 50 Hz AC supply from an independent source, which should automatically switch off before starting of unit. However, once the dehumidification unit is switched ON, it shall be controlled automatically with a thermostat. The dehumidification unit shall be designed to avoid hot spot. The heater shall be suitable for continuous operation at 240 V AC supply voltage and shall be provided with on – off switch and fuse shall be provided for heater.

One or more adequately rated, thermostatically connected heaters shall be supplied to prevent condensation in any compartment. The heater shall be installed in the lower portion of the compartment and electrical connections shall be made from below the heater to minimize deterioration of supply wire insulation. The heaters shall be suitable to maintain the compartment temperature to prevent condensation.

The heaters shall be suitably designed to prevent any contact between the heater wire and air and shall consist of coiled resistance wire centered in metal sheath and completely encased in a highly compacted powder of Magnesium Oxide or other material having equal heat conduction and electrical insulation properties, or they shall consist of a resistance wire wound on a ceramic and completely covered with a ceramic material to prevent any contact between the wire and air. Alternatively, they shall consist of resistance wire mounted into a tubular ceramic body built into an envelope of stainless steel or the resistance wire is wound on a tubular ceramic body and embedded in glaze the surface temperature of the heaters shall be restricted to a value which will not shorten the life of the heater sheaths or that of insulated wire or other component in the compartments

3.17 QUALITY

BHEL quality plan to be followed subject to TBEM / customer's approval.

3.18 GUARANTEE:

The supplier shall guarantee that the goods under the Contract are new, unused of the most recent or current models and incorporated all recent improvements in design and materials unless provided otherwise in the Contract. The supplier shall further guarantee that the goods supplied under this Contract shall have no defects arising from design, materials or workmanship, installation and erection, if that may develop under normal use of the supplied goods. The supplier shall also guarantee the performance of the works executed by him including the performance of all the materials/goods supplied by him.

BHEL shall promptly notify supplier in writing of any claims arising under guarantee in respect of goods. Upon receipt of such notice, the supplier shall, with all reasonable speed, repair or replace the defective works or parts thereof, free of cost at site. All the expenses towards transportation of defective parts to supplier's works and of repaired/replaced parts to site shall be borne by the Supplier.

If the Supplier, having been notified, fails to remedy the defects within 14 days, the BHEL will proceed to take such remedial action as may be necessary, at the supplier's risk and expenses. All expenses in this regard will be recovered from Supplier.

3.19 DOCUMENTATION

3.19.1 LIST OF DOCUMENTS

The bidder shall submit a detailed list of drawings / documents along with the bid proposal which he intends to submit to the Employer after award of the contract.

The supplier shall necessarily submit all the drawings / documents unless anything is waived.

All engineering data submitted by the Contractor after final process including review and approval by the Employer shall form part of the Contract Document and the entire works performed under this specification shall be performed in strict conformity, unless otherwise expressly requested by the Employer in Writing.

3.19.2 DRAWINGS

All drawings submitted by the Contractor including those submitted at the time of bid shall be in sufficient detail to indicate the type, size, arrangement, material description, Bill of Materials, weight of each component, break-up for packing and shipment, the external connections, fixing arrangement required, the dimensions required for installation and interconnections with other equipment's and materials, clearances and spaces required for installation and interconnection between various portions of equipment's and any other information specifically requested in the specifications.

Each drawing submitted by the Contractor shall be clearly marked with the name of the Employer, name of consultant, the unit designation, contract no., and the name of the Project. If standard catalogue pages are submitted, the applicable items shall be indicated therein. All titles, noting, markings and writings on the drawing shall be in English. All the dimensions should be in metric units.

Further work by the Contractor shall be in strict accordance with these drawings and no deviation shall be permitted without the written approval of the Employer if so required.

All manufacturing and fabrication work in connection with the equipment prior to the approval of the drawing shall be at the Contractor's risk. The Contractor may make any changes in the design which are necessary to make the equipment conform to the provisions and intent of the Contract and such changes

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

will again be subject to approval by the Employer. Approval of Contractor's drawing or work by the Employer shall not relieve the contractor of any of his responsibilities and liabilities under the Contract.

3.19.3 APPROVAL PROCEDURE

The scheduled dates for the submission of these as well as for, any data/information to be furnished by the Employer would be discussed and finalized at the time of award. The supplier shall also submit required no. of copies as mentioned in this specification of all drawings/design documents/test reports for approval by the Employer. The following schedule shall be followed generally for approval.

i.	Approval/comments/by employer on Initial submission	Within 2 weeks of receipt
ii.	Resubmission	Within 2 (two) weeks (whenever from date of comments required) Including both ways postal time.
iii.	Approval or comments	Within 2 weeks of receipt of resubmission
iv.	Furnishing of distribution copies	2 weeks from the date of last approval.

Note: The contractor may please note that all resubmissions must incorporate, all comments given in the submission by the Employer failing which the submission of documents is likely to be returned. Every revision shall be a revision number, date and subject, in a revision block provided in the drawing, clearly marking the changes incorporated.

The title block of drawings shall contain the following information incorporated in all contract drawings.

3.19.4 DOCUMENTS TO BE SUBMITTED ALONGWITH OFFER

- 1) Drawings
- 2) Guaranteed Technical Particulars
- 3) Type Test Reports
- 4) Manufacturing Quality Plan

3.20 DOCUMENTATION SCHEDULE

S. No.	DESCRIPTION	TENDER STAGE	CONTRACT STAGE FOR APPROVAL	FINAL DOCUMENTATION	
			Prints	Prints	CDs
1	Drawings and Data Sheets	1	10	13	-
2	Drawings "As Built "	-	-	13	05
3	Type Test Reports	1	05	13	-
4	Erection Manuals	-	11	13	-
5	Operation and Maintenance Manuals	-	11	13	-
6	Manufacturing Quality Plan	1	11	13	-

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND
CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

7	Field Quality Plan	1	11	13	-
8	Inspection Test Reports	-	-	13	-

Drawings will also be submitted in mini cartridges in AUTOCAD Release -14 package or any other CAD package along with conversion files for all major items.

Final Documentation shall be submitted in bound volumes with Customer & Project etc. written on top.

ANNEXURE-II

CORONA AND RADIO INTERFERENCE VOLTAGE (RIV) TEST

1. General

Unless otherwise stipulated, all equipment together with its associated connectors, where applicable, shall be tested for external corona (for 400kV & above) both by observing the voltage level for the extinction of visible corona under falling power frequency voltage and by measurement of radio interference voltage (RIV) for 132kV and above.

2. Test Levels:

The test voltage levels for measurement of external RIV and for corona extinction voltage are listed under the relevant clauses of the specification.

3. Test Methods for RIV:

3.1 RIV tests shall be made according to measuring circuit as per International Special-Committee on Radio Interference (CISPR) Publication 16-1(1993) Part -1. The measuring circuit shall preferably be tuned to frequency with 10% of 0.5 Mhz but other frequencies in the range of 0.5 MHz to 2 MHz may be used, the measuring frequency being recorded. The results shall be in microvolts.

3.2 Alternatively, RIV tests shall be carried out in accordance with relevant IEC of respective equipment or NEMA standard Publication No. 107-1964.

3.3 In measurement of, RIV, temporary additional external corona shielding may be provided. In measurements of RIV only standard fittings of identical type supplied with the equipment and a simulation of the connections as used in the actual installation will be permitted in the vicinity within 3.5 meters of terminals.

3.4 Ambient noise shall be measured before and after each series of tests to ensure that there is no variation in ambient noise level. If variation is present, the lowest ambient noise level will form basis for the measurements. RIV levels shall be measured at increasing and decreasing voltages of 85%, 100%, and 110% of the specified RIV test voltage for all equipment unless otherwise specified. The specified RIV test voltage for 765kV, 400 kV, 220 KV is listed in the detailed specification together with maximum permissible RIV level in microvolts.

3.5 The metering instruments shall be as per CISPR recommendation or equivalent device so long as it has been used by other testing authorities.

3.6 The RIV measurement may be made with a noise meter. A calibration procedure of the frequency to which noise meter shall be tuned shall establish the ratio of voltage at the high voltage terminal to voltage read by noise meter.

4. Test Methods for Visible Corona

The purpose of this test is to determine the corona extinction voltage of apparatus, connectors etc. The test shall be carried out in the same manner as RIV test described above with the exception that RIV measurements are not required during test and a search technique shall be used near the onset and extinction voltage, when the test voltage is raised and lowered to determine their precise values. The test voltage shall be raised to 110% of specified corona extinction voltage and maintained there for five minutes. In case corona inception does not take place at 110%, test shall be stopped, otherwise test shall be continued and the voltage will then be decreased slowly until all visible corona disappears. The procedure shall be

repeated at least 4 times with corona inception and extinction voltage recorded each time. The corona extinction voltage for purposes of determining compliance with the specification shall be the lowest of the four values at which visible corona (negative or positive polarity) disappears. Photographs with laboratory in complete darkness shall be taken under test conditions, at all voltage steps i.e. 85%, 100%, and 110%. Additional photographs shall be taken at corona inception and extinction voltages. At least two views shall be photographed in each case using Panchromatic film with an ASA daylight rating of 400 with an exposure of two minutes at a lens aperture of f/5.6 or equivalent. The photographic process shall be such that prints are available for inspection and comparison with conditions as determined from direct observation. Photographs shall be taken from above and below the level of connector so as to show corona on bushing, insulators and all parts of energised connectors. The photographs shall be framed such that test object essentially, fills the frame with no cut-off.

For recording purpose, modern devices utilizing UV recording methods such as image intensifier may also be used.

4.1 The test shall be recorded on each photograph. Additional photograph shall be taken from each camera position with lights on to show the relative position of test object to facilitate precise corona location from the photographic evidence.

4.2 In addition to photographs of the test object preferably four photographs shall be taken of the complete test assembly showing relative positions of all the test equipment and test objects. These four photographs shall be taken from four points equally spaced around the test arrangement to show its features from all sides. Drawings of the laboratory and test set up locations shall be provided to indicate camera positions and angles. The precise location of camera shall be approved by Purchaser's inspector, after determining the best camera locations by trial energisation of test object at a voltage which results in corona.

4.3 The test to determine the visible corona extinction voltage need not be carried out simultaneously with test to determine RIV levels.

4.4 However, both test shall be carried out with the same test set up and as little time duration between tests as possible. No modification on treatment of the sample between tests will be allowed. Simultaneous RIV and visible corona extinction voltage testing may be permitted at the discretion of Purchaser's inspector if, in his opinion, it will not prejudice other test.

5. Test Records:

In addition to the information previously mentioned and the requirements specified as per CISPR or NEMA 107-1964 the following data shall be included in test report:

- a) Background noise before and after test.
- b) Detailed procedure of application of test voltage.
- c) Measurements of RIV levels expressed in micro volts at each level.
- d) Results and observations with regard to location and type of interference sources detected at each step.
- e) Test voltage shall be recorded when measured RIV passes through 100 microvolts in each direction.
- f) Onset and extinction of visual corona for each of the four tests required shall be recorded.

SEISMIC WITHSTAND TEST PROCEDURE

The seismic withstanding test on the complete equipment (for 132kV and above) shall be carried out along with supporting structure.

The Bidder shall arrange to transport the structure from his Contractor's premises/UJVNL sites for the purpose of seismic withstand test only.

The seismic level specified shall be applied at the base of the structure. The accelerometers shall be provided at the Terminal Pad of the equipment and any other point as agreed by the Purchaser. The seismic test shall be carried out in all possible combinations of the equipment. The seismic test procedure shall be furnished for approval of the Purchaser.

SECTION 4

SCHEDULE OF GUARANTEED TECHNICAL PARTICULARS

1. Name and address of Manufacturer
2. Manufacturer's type designation
3. Applicable standards
4. Arrester class and type
5. Rated arrester voltage (kV)
6. Rated system voltage (kV)
7. Maximum continuous operating voltage (COV) at 50 deg.C ambient temperature (kV)
8. Nominal discharge current (8/20 micro sec.wave) (kA)
9. Minimum discharge capability (kJ / kV)
10. a) Maximum residual voltage at nominal discharge current (kVpeak)
b) Minimum residual voltage at nominal discharge current (kVpeak)
11. a) Maximum residual voltage at 50 % nominal discharge current (kVpeak)
b) Maximum residual voltage at 200% nominal discharge current (kVpeak)
12. Steep fronted wave residual voltage at 1 KA (kVpeak)
13. Long duration discharge class
14. Impulse current withstand
a) High current short duration (4/10 micro-sec wave) in kVpeak
b) Low current long duration (2000 microsec.)
15. Current for pressure relief test (kA)
16. Pressure relief class (as per IEC 99)

SECTION 5

TECHNICAL CHECK LIST FOR SURGE ARRESTOR

(INFORMATION TO BE FURNISHED WITH OFFER)

BIDDERS ARE INSTRUCTED TO
WRITE 'YES' UNDER CLOUMN '3', IF THE INFORMATION / SCHEDULE IS
FURNISHED / ENCLOSED WITH THE OFFER, **OR**
WRITE 'NO' UNDER CLOUMN '3', IF THE INFORMATION / SCHEDULE IS NOT
FURNISHED / ENCLOSED WITH THE OFFER, **OR**
WRITE '**NOT APPLICABLE (NA)**' UNDER CLOUMN '3', IF THE INFORMATION /
QUERY / SCHEDULE IS NOT RELEVANT TO THEM, **AND**
RETURN THIS CHECKLIST AS THE PART OF THE OFFER DULY SIGNED

	Parameters	2	3	4
S.No.		Specified Requirement (198kV)	Confirmed Yes/No	Comments, if Col. 3 is No
1.	Confirm that all items in BOQ have been quoted.	Yes		
2.	Type	Gapless , Zinc Oxide		
3.	Installation	Outdoor		
4.	Nominal System Voltage	220kV		
5.	Highest system Voltage	245kV		
6.	Rated Arrester Voltage(kV)	198kV		
7.	System fault rating	50kA for 1s		
8.	Type of Insulator housing	Porcelain		
9.	Standard applicable for Surge arrester	IEC:60099-4		
10.	Nominal discharge current	10kA of 8/20 microsecond wave		
11.	Continuous Operating Voltage at 50 deg C	168kV (rms)		
12.	Min. discharge capability	5kJ/kV		
13.	Rated frequency (Hz)	50		
14.	Current for Pressure relief test	50 kA rms		
15.	Long duration discharge class	Class 3		

PROJECT : 220kV GIS for 2x60 MW VYASI HEP AT VYASI, DEHRADUN, UTTARAKHAND

CUSTOMER : UTTARAKHAND JAL VIDYUT NIGAM LIMITED (UJVNL)

Technical Specification of 245kV Class Surge Arrester

TB-398-316-003

REV.00

	Parameters	2	3	4
S.No.		Specified Requirement (198kV)	Confirmed Yes/No	Comments, if Col. 3 is No
16.	Min. creepage distance	6125mm		
17.	Length of connecting lead between Surge arrestor to counter	5 meter		
18.	Degree of Protection for Surge counter	IP66		
19.	Accessories & Earthing Connection leads between the bottom of the Arrester & Surge counter	included		
20.	Hardware required for inter-unit connection and to connect the Lightning arrester to structure included	Yes		
21.	Terminal connectors provided	Yes		
22.	Type test Reports conducted after 08.05.2007 available	Yes		
23.	Type tests will be conducted free of cost if reports not acceptable/invalid	Free		
24.	GA drawing, GTP & VI characteristics graphs	Enclosed		
25.	System neutral earthing	Effectively earthed		
26.	Cantilever strength For Polymer For Porcelain	150kg (min.) 350kg (min.)		

Date:

Place:

Phone:

Fax:

E-mail:

Mobile:

Website:

ANNEXURE - A

SCHEDULE OF TECHNICAL DEVIATIONS

Bidder shall list below all technical deviation clause wise w.r.t. tender specifications:

S.No.	Page No.	Clause No.	Deviation	Reason / Justification
-------	----------	------------	-----------	------------------------

Any deviation not specifically brought out in this section shall not be admissible for any commercial implication at later stage. Except to the technical deviations listed in this schedule, bidder's offer shall be considered in full compliance to the tender specifications irrespective of any such deviation indicated / taken elsewhere in the submitted offer.

Date:

Tenderer's Stamp & Signature

CHECKLIST FOR TECHNICAL EVALUATION

Along with the Technical Bids of the offers, the Bidder should submit this checklist confirming the inclusion of the enclosures as listed below. (Shall tick as ✓)

Sr No	Documents to be enclosed	Bidder to check & confirm
1	Copy of Unpriced BOQ as enclosed in the Technical Specification to confirm that bidder has quoted in the same format (Annexure-1)	
2.	Schedule of Technical Deviation format duly signed. (Annexure-A)	
3.	Checklist of Technical parameters as per Section-5 duly filled and signed.	

NOTE:- If the Bidder fails to submit any of the documents as asked in the above check list, their bid is likely to be rejected / not evaluated.

The above checklist is verified for:-

NIT Ref No. :

Name of Equipment :

Name of Project :

Name of Bidder :

Signed with Seal of Bidder.

Date