

**Bharat Heavy Electricals Limited**  
**Ramachandrapuram : : Hyderabad – 502032**  
**M&S – DIVISION**  
**ANNEXURE-A**

**Tender No.:** M&S/P&S/2021/39, Dt.: 13.09.2021

**Name of Work:** Maintenance of HT LT Switchgear, Electrical Maintenance of Administrative Building and Maintenance of Roof Lighting, Street Lighting.

1. Works related to Preventive maintenance, breakdown maintenance and scheduled maintenance of HT and LT breakers, Capacitor banks (HT and LT), Battery banks and Substation maintenance inside BHEL and outside BHEL in TSTRANSCO premises. One quantity is works done by the 4 SSW under the supervision of BHEL Supervisor. The estimated period of one work is approximately 7 – 8 hours. The works includes at least one of the following.
  - a. Preventive / Schedule / Breakdown maintenance of all HT 11/6.6KV HT Switchgear panels (all BHEL Bhopal make) and LT Switcher gear L.T incoming and outgoing ACB panels of L&T, Marine and JG stator makes of various capacities such as 3200A,2000A,1600A,1250A,1000A and 800Amps and other low capacities as per following works to be carried out. Opening of all doors, side covers, drawl of breaker from the unit and cleaning & dusting of the equipment with cora cloth and vaccum cleaner. Contractor shall provide all cleaning agents and equipment's for the above activity. Checking and tightening of the contacts and contact assembly for any pitting, hot spots or any abnormal conditions and replacing damaged contacts with new spares.
    - i. Cleaning the operation mechanism including spring mechanizing/motor operation, limit switches etc., of the Breaker. Checking and correction of the internal wiring of the unit, testing of the wiring by simulation and submission of the report basing on the status. Oiling of the moving mechanision and check for proper operation.
    - ii. Checking and replacing the magnetic coils used for the closing and tripping operations.
    - iii. Checking the total interlocking by simulation.
    - iv. Checking, cleaning including replacement of the damaged bushings/Insulators/Spouts.
    - v. Checking the healthiness of the CTs & PTs and replacing the defective items.
    - vi. Checking the internal wiring of the unit includes metering, indication lamps, switches and replacing the defective items.
    - vii. Checking the wiring of the protective relays, simulation of condition and testing of relays for its healthiness.
    - viii. Checking and cleaning the vaccum interrupters and replacement of defective units.
    - ix. Checking the condition of the insulating oil if required removal of the old oil and filling of the filtered oil.

- x. (Drawl and shifting of new oil and filtering the same and shifting the old/removed oil to stores is in the scope of the contractor.
- xi. Checking and tightening of all busbars of switchgear CTs, PTs terminal blocks and checking for any hotspots.
- xii. Checking of total earth continuity for non-conducting items of the switchgear panels.
- xiii. Replacement of damaged gaskets for prevention of dust and entry of insects. Cleaning and closing of any openings at the bottom/side for prevention of entry of rats.
- xiv. Checking the alignment of panels and if required correcting the same.
- xv. Checking and connecting the external earth flat to meet safety and statutory norms.(concerned earth pit values are to be recorded)
- xvi. Record and submission of IR values of each panel and combination of the panels.
- b. HT Capacitor Banks (outdoor)
  - (i) 2016 KVAR --2 sets (each set consists of 24 Nos 84/168 KVAR units)
  - (ii) 1008 KVAR --2 sets (each set consists of 12 Nos 84/168 KVAR units)
    - i. Cleaning & checking of all fixed and movable parts including applying CTC/Grease.
    - ii. Checking of limit switch operations for entry and closing door.
    - iii. Cleaning and tightening MS and Brass fasteneres including strenthening the same.
    - iv. Checking and operation of outdoor AB switches and if requires rectification of same.
    - v. Checking and replacing the HT fuse wires wherever required.
    - vi. Checking the IR values of Residual Voltage
    - vii. Transformers and capacitor units of 84/168 KVAR and record.
  - viii. Checking and replacement of faulty capacitor units for item III(i&ii)
  - ix. Checking and testing of IR values & earth continuity for the entire equipment before and after switching ON & OFF and record the same.
  - x. Periodical cleaning of the floor area and equipment with cora cloth/vaccum cleaner and water.
  - xi. Replacement of defective RVTs if required for the availabe four sets.
  - xii. Lugging and crimping with solderless copper lugs for interconnection of capacitor units, RVTs, earth and neutral points wherever required.
- c. LT Capacitor banks (Indoor):-
  - (i) LT capacitor banks of 50 KVAR
  - (ii) LTTSC Banks of 200 KVAR (BHEL, BHOPAL & BANGALORE make)
    - i. Cleaning and checking of the capacitor units for proper operation.
    - ii. Dismantelling and shifting of 50KVAR capacitor units, which are faulty from existing location to stores.
    - iii. Replacement of faulty LT control gear with damaged contactors etc, and fixing new control gears for 50 KVAR units.
    - iv. Cleaning and checking of 200 Amps CFS units for 50 KVAR units.
    - v. Replacement of defective 200Amps CFS units for 50 KVAR units.
    - vi. Checking and meggering of LT cables from 50KVAR units to control gear and LT ACB panels.

- vii. Replacement of damaged LT cable of 3 1/2 x 95/70 sqmm Al. PVC Insulated with new cable and making its end terminations at both side (Approx length 5 mtrs per 50 KVAR units)
- viii. Routine checking, cleaning and functioning LTTSC units.
  - ix. Checking of IR values and earth continuity from ACB panel to LTTSC unit.
- d. DC Tripping units and its chargers
  - i) 30V, 40AH MF batteries and 30V, 4A chargers
  - ii) 30V, 160AH MF batteries and 30V, 20A chargers
    - i. Checking and cleaning of batteries and chargers and apply battery terminal coating wherever required. Checking the condition of cells and chargers Replacement of damaged MF batteries, PCBs and other defective items with new ones. Recording the charging and discharging currents of batteries and submission of same.
- e. Dusting and cleaning of HT&LT Sub-stations consisting of a total of 100 Nos HT Breaker panels, 150 Nos LT Breaker Panels, 4 sets HT Capacitor Banks, 36 Nos LT Capacitor Banks, 30 Sets Battery Chargers & Tripping units, 30 Nos Transformers located at various Sub-stations inside the plant regularly. The scope of the work includes the following activities.
  - i) Lifting the rolling shutters, opening the collapsable doors and dusting the various equipments in the sub-station regularly. The shutter/doors shall be closed after cleaning the Sub-station.
  - ii) Cleaning the cobwebs inside the control room and transformer room.