

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

104

**SOLAR ROOF TOP SYSTEM ON THE ROOFS OF HP PETROL PUMP
(MALWA- KUNDL-SONIPAT), HP PETROL PUMP (BALAJI-BARI-
SONEPAT), HP PETROL PUMP (KAUSHALYA-SAMALKHA), HP PETROL
PUMP (COCO- RAMGHAR-KURUKSHETRA)**

GENERAL & TECHNICAL SPECIFICATIONS

**FOR
SOLAR SYSTEM**

IMPORTANT NOTE

**"BIDDER IS REQUESTED TO VISIT ALL THE SITES IN PERSON AND
THEN SUBMIT THEIR BEST OFFER. ANY TYPE OF DENIAL
/OBJECTION WILL NOT BE ENTERTAINED AFTER FINALIZATION OF
ORDER."**



	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

107

GENERAL SPECIFICATIONS



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

1. BRIEF ABOUT THE PROJECT:

List of Identified rooftops indicating potential for proposed installation capacity i.e.

Sl.No.	Site Name	Proposed Capacity (KWp)	No. of Roof	No. of Module	Remarks
1	HP PETROL PUMP (MALWA- KUNDL-SONIPAT)	04	01	38	
2	HP PETROL PUMP (BALAJI-BARI-SONEPAT)	04	01	14	
3	HP PETROL PUMP (KAUSHALYA-SAMALKHA)	03	01	14	
4	HP PETROL PUMP (COCO- RAMGHAR-KURUKSHETRA)	11	01	11	
Total		22		77	

Notes:

- 1. Bidder to note that these site are under approval. Same shall be intimated after approval. Based on approval work (Part scope/full scope) shall be done at site.**
- 2. Bidder to note that Isolation transformer/CDB shall be connected to grid as well as Generator.**
- 3. Bidder to install the MCCB at solar end connecting to customer LT Panel.**
- 4. Bidder to install the MCCB at Isolation transformer/CDB end connecting from customer LT Panel.**

 Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05
		Rev no	00

1.1 SCOPE OF WORK & TECHNICAL SPECIFICATIONS

SUPPLYING of BALANCE OF MATERIALS, INSTALLATION, TESTING AND COMMISSIONING OF 22KWp ROOF TOP SOLAR POWER PROJECT AT above said buildings.

Note: Module of 300 Wp or above (approx. 77 Nos) shall be supplied by BHEL. Remaining all BoS supply shall be in bidder scope. **Bidder to note that storage, safe keeping, transportation, loading and unloading (including lifting and shifting) of BHEL supplied items (Modules, Isolation Transformer & Charger Distribution Box) at site shall be in bidder scope.**

DEFINITION

A Grid Tied Solar Rooftop Photo Voltaic (SPV) power plant consists of SPV array, Module Mounting Structure, array Junction Boxes, String Monitoring system, PCU or Central / String Inverter consisting of Maximum Power Point Tracker (MPPT) with Remote Monitoring System, DC & AC cables, AC Distribution Board with MFM, switches and Controls & Protections with earthing and lightening protections. PV Array is mounted on a suitable structure. Grid tied SPV system is without battery and should be designed with necessary features to supplement the grid power during day time. Components and parts used in the SPV power plants including the PV modules, metallic structures, cables, junction box, switches, Central / String Inverter etc., should conform to the BIS or IEC or international specifications, wherever such specifications are available and applicable.

Solar PV system shall consist of following equipment/components.

- Solar PV modules consisting of required number of Crystalline PV modules.
- Grid interactive Power Conditioning Unit with Remote Monitoring System.
- Mounting structures.
- Junction Boxes.
- Earthing and lightening protections.
- IR/UV protected PVC Cables, pipes and accessories

Note: Bidder to note that BHEL can add new roof/space for increase the plant capacity.

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

Part A : General Scope

1. Services Related to supplies made by BHEL (Sl.No. 1 of BoQ)

Upon award of work for a particular site - Vendor has to identify central area within the CUSTOMER/user premises for unloading and storing of BHEL supplied items. Subsequent arrangement for unloading, safekeeping, shifting to site for installation shall be part of services to be offered by the Bidder associated with BHEL supplied items.

1.1. Unloading, safe storage and movement of supplied items received at site:

- a)** Vendor shall organize all necessary resources such as labour, machinery and tools, cranes, hydra, forklifts, transportation trucks/ trolleys, lifting accessories etc. for unloading the BHEL supplied items from the transport vehicle reaching identified location at site and subsequent movement to storage yards/sheds.
- b)** Similar arrangements shall also be made by vendor for movement of the stored items from storage yards/sheds to the exact construction locations within the project site.
- c)** Vendor shall maintain proper registers/ files/ records of invoices, LRs, delivery challans, material receipt certificates etc. Also, proper records shall be maintained to keep track of material entry (for storage) and material issue (for construction).
- d)** All such documents shall be suitably preserved for further handing over to BHEL.
- e)** Safety of items shall be in vendor scope. Accordingly, vendor will make all requisite arrangements for safe storage and preservation of BHEL supplied material.
- f)** All the equipment shall be handled very carefully to prevent any damage or loss. No untested wire ropes / slings etc. shall be used for unloading / handling. The equipment shall be properly protected to prevent damage either to the equipment or to the floor where they are stored. The equipment from the stores shall be moved to the actual location at the appropriate time so as to avoid damage of such equipment at site.
- g)** The material received shall be properly inspected for any damage caused during transit and the Goods Receipt Document of the Transporter shall be acknowledged after verifying the condition of goods received. Any damage shall be immediately reported to BHEL. In cases when such information is not given to BHEL in time – it will be presumed that material was received in good condition by contractor and damage may have taken place at a later stage. Such damage or loss shall be attributable to the contractor.
- h)** Contractor shall ensure that while lifting slings shall be put over the points indicated on the equipment or as indicated in the manufacturer's drawings. Slings / shackles of proper size shall be used for all lifting and rigging purposes. All care shall be taken to safe guard the equipment against any damage.
- i)** Contractor shall be responsible for examining all the plant and materials issued to him and notify the Engineer immediately of any damage, shortage, discrepancy etc. before they are moved out of the stores / storage area. The contractor shall be solely responsible for any shortages or damages in transit, handling, storage and erection of the equipment once received by him.



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

- j) The contractor shall maintain an accurate and exhaustive record-detailing out the list of all equipment received by him for the purpose of erection and keep such record open for the inspection of the engineer at any time.
- k) All the material in the custody of contractor and stored in the open or dusty locations must be covered with suitable weather proof covering material wherever applicable and shall be blocked up on raised level above ground.
- l) The contractor shall hand over all parts / materials supplied by BHEL and remaining extra over the normal requirement with proper identification tags and measurements to BHEL before site closure. Such intimation will be given in writing to BHEL well in time.
- m) It shall be the responsibility of the contractor to keep the work / storage areas in neat, tidy and working conditions. All surplus/unusable packing and other materials shall be removed and deposited at location(s) as identified within the project premises.
- n) All suitable lifting arrangement and local transport arrangement within premises for material handling at stores/yard/siding of BHEL/Customer/Vendor are included in scope.

1.2. Preservation of components

- a) After taking delivery from BHEL / customer's stores, plant materials storage shall be subjected to the following protection besides other provisions indicated in these specifications elsewhere.
- b) Items stored outdoors shall be stacked up at least six inches (6") off the ground. Items should not be stored in a low lying area where water logging is a possibility.
- c) Electrical items shall be stored indoors or otherwise protected against getting wet/damaged, using suitable measures and should be protected from direct rain.

1.3. "Security & safekeeping of BHEL supplied material.

For all system capacities and in all situations – it is the prime responsibility of the contractor to ensure security and safekeeping of the BHEL supplied material till handing over of complete system in working condition to customer. The contractor will make their own assessment based on prevailing condition at site and will make all arrangements for security and safekeeping of BHEL supplied material. The contractor shall also indemnify BHEL towards any loss incurred towards loss of damage to BHEL supplied material.

2. Installation of BHEL Supplied items (Sl. No. 2 of BoQ)

2.1. SPV Modules:

Vendor Shall do the erection of the SPV module as per approved layout design of BHEL. After placing the purchase order on vendor, BHEL will provide layout drawings that will describe the exact way in which the series/parallel strings are formed. Vendor shall implement the interconnection as per these drawings. Required number of nuts and bolts for the erection of Modules shall be supplied by vendors. These will be **made of SS 304 material - NUTS, BOLTS AND PLAIN WASHERS.**

Installation activity shall include Placing on base, bolting, clamping with Structure material, Ferrule Marking near String. Other fasteners like Clamp, brackets, M6 Screws shall also be supplied as required additionally.

Series interconnection of SPV modules to form strings

Vendor shall interconnect the SPV modules as follows:

- a) Each module is fitted integrally with a junction box having positive and negative polarity cables (4 sq-mm).

98

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

- b) Positive cable of one module shall be connected to the negative cable of adjacent module. The cables have MC4 type of connectors to be supplied by contractor. One polarity cable has male type connector, while the other has female type connector.
- c) This way, Min 17 Modules shall be connected in series. Each set of connections is called as a series string. Series formation may change as per approved layout and design.

Interconnection of SPV module strings to string inverters

- a) Vendor shall connect each series string of 17-20 SPV modules to the DCDB/string inverter using 1Cx 4 cable, copper, XLPO, unarmored as per TUV 2pfg 1169/08.2007.
- b) MC4 connectors shall have rating of 1000VDC (IEC), rated current of 30A, Type approved by TUV Rhineland for product safety. MC4 connector shall be supplied by Contractor.
- c) Min. Two sets of tool kits (with box enclosure) shall be supplied. This shall include crimping plier MC4, open end spanner set MC4, stripping plier MC4, socket wrench insert to tighten, socket wrench insert to secure etc.

Required number of MC-4 Connectors each set having a pair of male and female parts, to join both the cables shall be supplied by Vendor.

2.2. Installation of string inverters

Supply of string inverters is in vendor scope. Approximate weight of inverter 50 Kg.

a) Installation of string Inverter on Roof:

- On roof tops, the Inverter shall be mounted on MS stand that shall be attached by welding to the Roof top MMS.
- Minimum ground clearance shall be 500mm.
- In case of outdoor installation - Structure shall have canopy (as rain shade) made of GI sheet of minimum 2mm thick. Canopy shall be supplied and installed by Vendor.

b) Installation of String Inverter on Wall:

- On wall, Inverter shall be mounted on mounting plate.
- Minimum wall clearance shall be 50mm.
- All structure items including hardware shall be in vendor scope of supply.

2.3. Installation of AC combiner boxes (ACCB/ACDB)

Supply of AC Combiner boxes(ACCB/ACDB) is in vendor scope.

a) Installation of ACCB/ACDB on Roof:

- On roof tops, ACCB/ACDB shall be mounted on MS stand that shall be attached by welding to the Roof top MMS.
- Minimum ground clearance shall be 500mm.
- In case of outdoor installation - Structure shall have canopy (as rain shade) made of GI sheet of minimum 2mm thick. Canopy shall be supplied and installed by Vendor.
- All galvanizing shall be minimum 80 microns and as per IS: 4759, IS: 2629, IS: 2633
- Vendor shall submit GA of the mounting structure along with stability calculations (STAAD.pro etc) for BHEL/CUSTOMER approval during detailed engineering.
- All structure/pedestal items including hardware shall be in vendor scope of supply.

b) Installation of ACCB/ACDB on Wall:

- On wall, Inverter shall be mounted on mounting plate.

 BHEL	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

- Minimum wall clearance shall be 50mm.
- All galvanizing shall be minimum 80 microns and as per IS: 4759, IS: 2629, IS: 2633
- All structure items including hardware shall be in vendor scope of supply.

2.4. Installation of DC distribution boxes (DCDB)

Supply of DC Distribution boxes(DCDB) is in vendor scope.

c) Installation of DCDB on Roof:

- On roof tops, DCDB shall be mounted on MS stand that shall be attached by welding to the Roof top MMS.
- Minimum ground clearance shall be 500mm.
- Structure shall have canopy (as rain shade) made of GI sheet of minimum 2mm thick.
- All galvanizing shall be minimum 80 microns and as per IS: 4759, IS: 2629, IS: 2633
- Vendor shall submit GA of the mounting structure along with stability calculations (STAAD.pro etc) for BHEL/CUSTOMER approval during detailed engineering.
- All structure/pedestal items including hardware shall be in vendor scope of supply.

d) Installation of DCDB on Wall:

- On wall, Inverter shall be mounted on mounting plate.
- Minimum wall clearance shall be 50mm.
- All galvanizing shall be minimum 80 microns and as per IS: 4759, IS: 2629, IS: 2633
- All structure items including hardware shall be in vendor scope of supply.

Note : Price of installation of ACDB and DCDB included in installation cost of Inverter

3. Installation of Structure for Module Mounting on rooftop/Tin Shed (Sl.No.3 of BoQ)

Design, supply & erection Supply of MMS on roof top/Tin string inverters is in vendor scope. Vendor to submit the Design along with the **CHARTED ENGINEER APPROVED STAAD**.

Wherever, welding is carried out, vendor shall arrange for proper grinding and cleaning of the weld surfaces, followed by application of Metal primer and Metallic aluminum paint. Pre-Galvanized parts shall be sprayed with Zinc spray after work.

Required number of nuts and bolts for the erection of MMS shall be supplied by vendors.

Note: NUTS, BOLTS AND PLAIN WASHERS shall be made of SS 304.

4. Civil Pedestal (Sl.No.4 of BoQ)

Basic specification calls for Cement Concrete **1:2:4** (1 cement, 2 coarse sand & 4 graded stone aggregate 20mm nominal size). These will be mixed to get a compressive strength of 20 N/mm² (M20 Concrete Grade).

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

Cement shall be good ISI Portland cement of reputed make. Cement bags shall bear ISI certification mark and date of manufacture. The sand shall be of river sand, clean & free from organic impurities. C.C. (1:2:4) concrete shall be mixed well in watertight platform in proportion as specified. All ingredients in required proportion shall be mixed, first dry & then required quantity of water shall be added. Mixing shall be turned over twice or thrice, so that surface of the coarse aggregate coated with cement & concrete shall be used within half an hour of mixing. Any quantity remaining unused after an hour of mixing will not be allowed to use. The casted pedestals shall be cured minimum for ten days after completion of work. It shall keep well-watered & shall be protected from direct heat of sunlight by means of wet gunny bags.

Cement shall be procured by Vendor conforming to BIS: 8112 and / or BIS: 1489 Specification latest edition or higher Grade. The cement shall be procured directly from the reputed manufacturers/ stockiest as per approved list of BHEL/Customer. Relevant vouchers and test certificates will be produced as and when required. The cement shall be stored by the Vendor in such suitable covered and lockable stores, well protected from climate and atmospheric effects. The cement go-down shall be constructed by the Vendor as per the drawing in CPWD specifications at his own cost. The cement will remain under double lock, one from NBCC and other from Vendor. The cement in bags shall be stored in go-downs in easy countable position. Cement bags shall be used on first in first out basis. Cement stored for beyond 90 days will be required to be tested at Vendors cost, before use in works. Concrete shall consist of cement, sand & graded stone in required proportion. Coarse aggregate for all concrete shall be graded crushed hard granite, trap or basalt stone and shall conform to the requirements. All materials shall be carefully & accurately measured in measuring box. Cement shall either be weighed or used in full bags. The required quantity of water shall be added by measuring in water cans. Concrete shall be mixed by mixer machine. Before any concrete is placed in position, all loose pieces of Timber, Stones, saw dust etc. shall be removed from the work. No concrete mixed 30 minutes' prior of placing in form shall be accepted. Proper water cement ratio shall be observed. Mechanical mixing method shall be adopted for mixing of concrete. The mechanical needle vibrator or other approved methods shall be adopted for compaction of the mix. The concrete consolidation shall be through & no honeycomb work (rough, pitted surface or voids in concrete) shall be allowed. All the formwork shall be provided by the Vendor at his cost & shall be thoroughly wetted before the concrete is placed in position. Formwork shall be of approved quality. Where timber is used, the face in contact with concrete shall be plain & made smooth. All the joints in formwork shall be perfectly close to prevent the loss of cement slurry from concrete. After the form works are complete, the Vendor shall get it checked for strength, suitability & levels. For this advance intimation shall be given for inspection.

Sufficient number of framework/shuttering shall be maintained by the contractor at site to match the pace of the work required at site. Estimated number of shuttering is as specified below :

For capacity upto 100KW : (150 Nos.)

~~For capacity > 100 KW and upto 500KW : (400 Nos.)~~

~~For capacity >500 KW and upto 1500KW : (500 Nos.)~~

J-Bolts –Supply & fixing:

The anchor bolts (J bolt) shall be sunk into the wet concrete by hand immediately after the concrete slab is poured. The anchor shall be standing straight and projecting, as the concrete hardens. 4 Nos. of J-bolt of straight length shall be used general of 200mm in addition to bent portion at unthreaded end as per standard and may change as per MMS design. These bolts are threaded at the top, for about two inches, and the rest of the bolt is smooth. Diameter of J bolt shall be 10mm and TWO nos. nuts each and suitable washers shall be supplied with each bolt. Arrangement shall be as per Drawing.



PURCHASE SPECIFICATION		Doc. No:-	REG1920-20190428
Rudrapur		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

It is essential that a template or a plastic sleeve is used to hold the bolts in place until the concrete sets up enough to support the weight of the bolt. Using a template will help keep the bolts straight, plumb and the correct distance from each other.

Note: Bolt & Nuts shall be made of Galvanized steel and 02 NUTS AND 02 PLAIN WASHERS shall be used.

SAMPLING, INSPECTION & TESTING

Sampling and testing of concrete shall be carried out by drawing random sample during various stages of inspection. Guiding standard shall be IS: 516. Cube Test on selected sample after 7 days curing & 28 days curing shall be conducted for compression strength. Sampling plan as below:

Concrete in m ³ /day work	No of samples
01-05	1
06-15	2
16-30	3
31-50	4
51 and above additional	4 plus one sample for additional 50 cum or part thereof.

Pull Out Test

Pull out test of casted pedestals on roof shall be arranged by the contractor free of cost. Necessary arrangement to show that the pedestal is able to withstand the toppling load due to its dead weight and application of Nitto Bond. BHEL will specify the testing criteria based on roof condition and local site conditions and based on its own design of civil pedestals. The selected locations where pull out test shall be conducted shall be based on decision taken by BHEL site engineer and based on any specific customer requirement.

Lifting

Cost of Lifting of pedestals or raw material of pedestals upto the roof level is included in the contractor's scope. For buildings of height upto 4th floor and for Tin Sheds of height upto 5 Mtrs. – no additional charges shall be payable for lifting. For lifting above these levels – additional amount over the basic rates has been considered elsewhere in the BoQ .

Preparation of Roof

Marking on the roof for the placement of pedestal shall be done by the vendor as per the approved layout.

Pedestal shall be placed after placement of the NITTO BOND on the roof. For particular type of surfaces like waterproofed roof etc. – NITTO BOND may not be required. In such cases – vendor will give prior intimation in writing to BHEL that NITTO BOND is NOT being applied by them. Unless such intimation is given – the vendor will be presumed to have used NITTO BOND in all cases and this will be part of site inspection by BHEL team.

Marked surface to be prepared cleaning the roof by wire brush after that NITTO BOND shall be applied on prepared roof.

Supply of NITOBOND is in scope of Contractor.



Rudrapur

PURCHASE SPECIFICATION

GROUP : REG (RENEWABLE ENERGY GROUP)

Doc. No:-

REG1920-20190428

Part

03/05

Rev no

00

94

5. Monitoring of System Performance (Sl.No.5 of BoQ)

Vendor has to provide data logger device as per the approved make. This is required to enable data exchange between inverter & cloud server to get information on logging screen.

Login details shall be provided by the Bidder to access the parameters as listed below.

The following parameters shall be accessible via the operating interface display in real time separately for solar power plant:

- AC Voltage.
- AC Output current.
- Output Power.
- Power factor.
- DC Input Voltage.
- DC Input Current.
- Time Active.
- Time disabled.
- Time Idle.
- Power produced
- Protective function limits (Viz. AC Over voltage, AC Under voltage, over frequency, under frequency ground fault, PV starting voltage, PV stopping voltage).
- All major parameters available on the digital bus and logging facility for energy auditing through the internal microprocessor and read on the digital front panel at any time) and logging facility (the current values, previous values for up to a month and the average values) should be made available for energy auditing through the internal microprocessor and should be read on the digital front panel.
- vii. PV array energy production: Digital Energy Meters to log the actual value of AC/ DC voltage, Current & Energy generated by the PV system provided
- Computerized DC String/Array monitoring and AC output monitoring shall be provided as part of the inverter and/or string/array combiner box. Computerized AC energy monitoring shall be in addition to the digital AC energy meter. It shall be taken care of by the Inverter itself and shall be available over data logger.
- String and array DC Voltage, Current and Power, Inverter AC output voltage and current (All 3 phases and lines), AC power (Active, Reactive and Apparent), Power Factor and AC energy (All 3 phases and cumulative) and frequency shall be monitored.
- Computerized AC energy monitoring shall be made available in Login screen.
- Software shall be provided for USB download and analysis of DC and AC parametric data for individual plant.
- Provision for instantaneous Internet monitoring and download of historical data shall be also incorporated.
- Remote Server access and Software for centralized Internet monitoring system shall be also provided for download and analysis of cumulative data of all the plants and the data of the solar radiation and temperature monitoring system.
- Remote Monitoring and data acquisition through Remote Monitoring System software at the owner with latest software/hardware configuration and service connectivity for online / real time data monitoring / control complete to be supplied and operation and maintenance / control to be ensured by the bidder.
- The bidders shall be obligated to push real time plant monitoring data on a specified interval (say 15 minute) through open protocol at receiver location (cloud server) in XML/JSON format, preferably. Suitable provision in this regard will be intimated to the bidders.

Web based Remote Monitoring system must be compatible with data logger. The system shall be provided with required accessories and required SIM card for wireless communication inside the



PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
	Part	03/05
GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

premises. The rental and other costs of the SIM cards, IP address, Server charge (storage, access charge and other charges if any), and Rental charge of data communication for remote monitoring system for a period of Five (05) years shall be in Vendor's scope.

Items required during installation like control cable, nuts/bolts etc shall be arranged by Vendor.

6. Cable Laying (Sl.No.6 of BoQ)

All the DC cables of required size as per approved SLD shall be supplied by BHEL.

Supply of AC cable in scope of Vendor.

Cable laying is in scope of Vendor laying details as follows:

All accessories for cable laying, including clamps, hooks, ties, double compression cable glands, cable lugs, SS304 bolts/ nuts/ plain and spring washers, anchoring arrangement shall be in vendor scope of supply. Cutting the wall/surface and making good the same as required is also included in the scope of the contractor. The Cable lengths supplied to site will NOT be in cut to size condition. Contractor has to arrange for cutting of the cables and jointing by using suitable cable jointing kits. All arrangement, tools & tackles in this regard will be in Contractor's scope.

Generally, jointing of cables in the run between two ends is not allowed. Hence, utmost care has to be taken while cutting required length of cables. The joints, as required otherwise due to any particular reason - shall be made only after getting prior consent from BHEL.

Vendor will submit scheme for cable laying within 15 days of site mobilisation. This scheme will include following details:

- (A) Approximate length of various sizes of cables based on routing agreed with customer/user during joint assessment at site. (Cable sizes shall be based on BHEL's Electrical Single Line Diagram).
- (B) Approximate requirement of laying through Conduits, Treys, Excavation etc.
- (C) Contractor to purchase the quantity of conduits, treys etc. after getting written acceptance from BHEL.

Method of measurement of length of cable laying

For the laying of 4 sq mm. DC cable (1 positive + 1 negative connection between different Modules) for formation of string – no additional charges shall be payable. This is covered in Module installation rate.

After the point where cables from different routes are bundled together – these will be routed through cable treys. For routing of cable in Bundles upto 5 parallel lengths on Treys/conduits – no additional charges shall be payable on account of laying of cable. Rates of conduits/treys have been considered elsewhere.

For laying of DC cables in bundles of 6 parallel or more – rates as applicable for maximum sizes of different slots shall be applied. For example – if 6 cables of 4 sq mm are grouped together for routing upto DCDB/AJB – the applicable rates for $6 \times 4 = 24$ sq mm (upto 35 sq mm) shall be followed.

The cables shall be routed in such a way that the length of cables used is minimum and at the same time any specific requirement by customer/user is also complied with. The cables shall be grouped together to the maximum extent possible, while laying on treys/conduits. In case, BHEL observes during inspection that cable length has been taken on a higher side due to no particular such requirement and other better alternatives for cable routing are available – then BHEL will be free to ask for re-routing of the cable by the contractor without any additional charge.

 BHEL	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

Length of Excavation, Treys, Conduits shall be calculated in measured length basis. These will be counted as one length only, for all cases in which clubbing of cables shall be done.

6.1. Routing of 1Cx4 cable below the SPV modules

- a) 1Cx4 cables connecting the SPV module strings to DCDB/inverters shall be suitably routed below the SPV modules and along the horizontal purlin member of MMS structure. Also, the cables shall be fastened to the purlin using UV resistant cable ties that shall be in vendor scope of supply.
- b) Spacing between two adjacent cable ties shall be so chosen as to ensure that there is no loose hanging of cables.
- c) Cable ties, nylon polyamide 6.6 UV stabilized black, UL94 flammability rating V2, operating temperature up to 85 deg C, shall be used to arrest any possibility of movement or sagging. Width of the cable ties shall be minimum 4.5 mm. Length shall be so chosen as to ensure that the bunched cables are held firmly to the MMS structure. During detailed engineering, BHEL/CUSTOMER approval shall be obtained for the selected brand and sizes of cable tie.

6.2. Routing of 1Cx4 cable in GI cable trays

Where 1Cx4 cables run between two adjacent rows of structure and also where the cables run on the roof-floor up to DCDB/string inverters, routing shall be on GI cable trays Wx Hx t = 100x50x 2 mm, perforated type, with GI cover of minimum 2mm thick, coupler plates, GI hardware as per relevant IS standard. Suitable flexible PVC conduit shall be used wherever required for covering cable at entry into GI cable tray.

6.3. Termination of 1Cx4 (DC side), 3.5/4C AC cables at string inverters & ACCB/ACDB boxes

- a) 1Cx4 cables of positive and negative polarities originating from SPV module strings shall be terminated at the DC input side of string inverters using MC4 connectors that are in vendor scope of supply for both ends.
- b) For AC side connection at string inverters and ACCB/ACDB boxes, cable as per SLD, 1.1kV, Copper, XLPE, armored as per IS: 7098 part-1, together with nickel plated brass double compression cable glands, cable lugs, SS304 bolts/ nuts/ plain and spring washers shall be in vendor scope of supply. Termination shall be carried out using appropriate tools and torque setting as per BHEL/CUSTOMER approval.

6.4. Ferruling for 1Cx4 cable

- a) For 1Cx4 DC solar array cable, vendor shall provide UV resistant ferrules printed with source/destination identification of cable connection. Printing details shall be submitted for BHEL/CUSTOMER approval during detailed engineering. Printing shall be of appropriate size to ensure readability.
- b) Ferrules shall be provided on both the termination ends: module end, inverter end.
- c) Supply of ferrule shall be in vendor scope. Make shall be reputed brand. Approval for make/ type/ color/ dimension etc shall be obtained from BHEL/CUSTOMER prior to procurement.

6.5. Underground cable trenches and laying of cables from buildings to building if required.

Routing of cables from buildings to buildings is not envisaged. However, if required due to specific conditions, such power, control, communication cables routed from one building to another building through underground cable trench (direct burying) as per IS: 1255.

 Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05

Typical trench details/dimensions are below only for tender purpose. During detailed engineering, cable trench layouts and cross section drawings as per IS: 1255 shall be submitted for BHEL/CUSTOMER approval.

- i. Total trench depth = 750 mm minimum
- ii. Trench width = As per number of cables/ DWC pipes
- iii. Trench shall have layers one over the other as below (from bottom to top):
 - a) Bottom layer shall be sand of IS: 383 with 75mm minimum thick.
 - b) 3C power cables shall be laid over the sand layer.
 - c) Another layer of sand of 75 mm minimum thick.
 - d) Single layer of brick as protective cover
 - e) Layer of sand of IS:383 with 75mm minimum thick
 - f) All communication cables shall be laid within DWC pipe
 - g) Layer of sand of IS:383 with 75mm minimum thick
 - h) Single layer of brick as protective cover
 - i) Trench shall, then, be filled with refill soil and compacted

Communication cables shall be routed through DWC pipe. Communication cables and DWC pipe shall be in vendor scope of supply. Vendor shall submit GTP/ make/ part number of the DWC pipe, accessories and tools for BHEL/CUSTOMER approval during detailed engineering. Bending radii for cables shall be as per IS: 1255.

At pathway/road/drain/trench crossings, cables shall be routed through GI pipe of appropriate size that shall be in vendor scope of supply and technical details / brand etc shall be submitted for BHEL/CUSTOMER approval. It shall be ensured that a maximum of 60% of inner space of GI pipe shall be occupied by cables.

Vendor shall take utmost care in laying the cables in order to prevent damages on outer sheath and inner insulation. In case cables found to be damaged/ cut after the laying in trenches, vendor shall remove the damaged portion and join the cut pieces using appropriate cable jointing kits that shall be in vendor scope of supply.

6.6. Laying and termination of RS485 cables

Vendor shall supply and install RS485 cable, copper, 2Px0.5, twisted pair, screened, armoured in daisy chain loops (a) from data loggers to string inverters and (b) from MFM meters of LT Panels to data loggers, (c) from weather monitoring system to data loggers. All cable accessories such as glands, lugs, ties, ferrules, tags, trays etc shall be in vendor scope of supply.

6.7. Identification marking of cables using cable tags

- Cable tags shall be provided at both ends of the cables: at SPV modules, string Inverters, data loggers, ACCB boxes, LTPDB panels and so on.
- Cable tag shall be of rectangular shape.
- Cable tag shall be of 2mm thick aluminum with number punched (embossed) on it and securely attached to the cable by not less than two turns of 20 SWG GI wire conforming to IS:280.
- Reference shall be made to “**Cable installation methodology**” of this specification. Vendor shall submit the technical details of cable tags, ID numbering scheme for BHEL/ CUSTOMER approval during detailed engineering.

6.8. Cable route markers

Cable route markers and joint markers for underground cables shall be provided along the route of the cables as per section “**Cable installation methodology**” of this specification.

90

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

7. Supply and installation of Conduits (Sl.No.7 of BoQ)

Contractor shall supply along with all accessories for laying of cable through it and install **Double Wall Corrugated (DWC pipe)** ISI mark IIS 1930 part 2 & latest IS 16205- part-24) double wall corrugated pipes along with accessories in surface/recess including cutting the wall and making good the same in case of recessed conduit as required. Conduits pipes shall be lay as per the approved drawing/make list/ Instruction provided by BHEL/Customer.

DWC pipe (for out door purpose) confirming to IS 14390. It shall be ensured that a max of 60% of inner space shall be occupied by the cables.

Method of measurement shall be as detailed against Sl. No. 6 above. The Scheme for laying of cable treys, conduits shall be submitted by contractor for approval of BHEL. After getting clearance from BHEL only – contractor shall make procurement of required quantity of cable treys, conduits etc.

8. Supply and installation of Cable tray (Sl.No.8 of BoQ)

Contractor shall supply along with all accessories for laying of cable through cable tray and install suitable size of Cable tray along with accessories in surface/recess including cutting the wall and making good the same in case of recessed tray as required. Cable Trey shall be lay as per the approved drawing/make list/ Instruction provided by BHEL/Customer. The Cable Trey shall be of GI material.

All couplers, fixing screws , 45/90 degree bends , intersections, dividers are included in scope.

For cable routing through exposed surfaces to rain – Cable Trey lid and Standoff brackets (for suitably raising the tray above surface for rain protection by minimum 50 mm) shall be used. Also, for important indoor locations Cable Trey lid shall be used for best aesthetic purpose.

Method of measurement shall be as detailed against Sl. No. 6 above. The Scheme for laying of cable treys, conduits shall be submitted by contractor for approval of BHEL. After getting clearance from BHEL only – contractor shall make procurement of required quantity, particular size of cable treys.

Vendor has to supply and installed cable tray with accessories.

Cable Trey shall be lay as per the approved drawing/Instruction provided by BHEL/Customer.

9. Supply and installation of Earthing strip with all accessories (Sl.No.9 of BoQ)

Vendor has to supply and install earthing strip (of Galvanised steel material) of following size:

- a) 25x5 mm OR
- b) 25x3 mm

The Scheme for laying of Earthing strips shall be submitted by contractor for approval of BHEL. After getting clearance from BHEL only – contractor shall make procurement of earthing strip material in required quantity, particular size.

10. Supply and installation of Lighting Arrestor with all accessories (Sl.No.10 of BoQ)

Vendor shall supply, install and commission Copper Globe Type lightning arrestors at the rooftops alongwith GI 25x5 down conductors as base and suitable mounting arrangement for LA on PCC block as part of this scope. The GA drawing of LA, number and location of installation and support arrangement shall be submitted to BHEL for approval before making procurement of this item. All



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

87

items in vendor scope of supply and installation. LA shall be supplied as per Indian Standard. The main aim in this protection shall be to reduce the over voltage to a tolerable value before it reaches the PV or other sub system components. The source of over voltage can be lightning, atmosphere disturbances etc. The entire space occupying the SPV array shall be suitably protected against Lightning by deploying required number of Lightning Arrestors.

Necessary foundation / anchoring for holding the lightning conductor in position to be made after giving due consideration to shadow on PV array, maximum wind speed and maintenance requirement at site in future. The lightning conductor shall be earthed through flats and connected to the earth mats as per applicable Indian Standards with earth pits (rates of earth pits, GI strips covered elsewhere in scope).

11. Supply of Earthing Material and Installation after making of Suitable Pit as per standard (Sl.No.11 of BoQ)

Solar array MMS structures, string inverters, data loggers, ACCB/ACDB boxes, LTPDB and lightning arrestors etc shall be provided with appropriate earthing for protection against faults as guided by **IEC 60364/IS:3043-1987**.

Earthing system shall be designed with consideration of the soil resistivity of the project site. Unless otherwise specified, earthing system shall be in accordance with IS: 3043 and IEEE 80, Indian Electricity Rules, Codes of practice and regulations existing in the location where the system is being installed. Vendor shall submit design calculations for earth grids/ system for roof-top equipment's and lightning arrestors for BHEL/CUSTOMER approval during detailed engineering. Chemical earthing electrodes of 3m minimum long, 50 mm minimum diameter, perforated GI pipe, chemical compound filled, double walled shall be installed at the ground level outside the buildings. For each electrode, earth chamber shall be constructed using brick masonry.

Vendor to ensure that earthing resistance shall be minimum **05 Ohm**.

Electrodes shall be supplied as per approved make of BHEL/CUSTOMER or during detailed engineering.

GI flat earthing terminal points and sizes :

- (a) 25x5 mm for MMS structures:
 - (1) structure to structure,
 - (2) interconnection of structures of all rows,
 - (3) from top of buildings to the chemical electrodes at ground level.
- (b) 25x5 mm/Equivalent cross section for string inverters, data loggers, ACCB box, lightning arrestors at roof-top

The Earth chamber shall have features as follows:

- (a) Square sized with 300mm x 300mm minimum inner opening. Exact size shall be chosen to ensure ease of maintenance operation using spanners etc.
- (b) Brick wall thickness all around = 115 mm minimum
- (c) Depth of chamber = 500 mm minimum below FGL.
- (d) Projection of chamber above FGL = 150mm minimum
- (e) Top of electrode shall have minimum clearance of 100 mm below cover plate.
- (f) Cover plate, cast iron of 5mm minimum thickness, square shaped to fit the opening of chamber, painted with red oxide and two coatings of black paint both sides.
- (g) Cover plate shall have suitable lifting hooks and padlocking arrangement.
- (h) Both the outer and inner walls of the brick wall shall be plastered and painted as per relevant clauses of "General civil works" of this specification.
- (i) Supply and installation of all materials shall be in vendor scope.



	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Part	03/05
		Rev no	00

General points:

- i. All items related to earthing viz electrodes, GI flats, hardware etc are in vendor scope of supply.
- ii. GI bolts, nuts, plain washers shall be used. Spring washers shall be zinc/epoxy coated.
- iii. Wherever applicable, welding for GI flats shall be carried out using electric arc welding. Both the flats shall be overlapped for the full width where they are in perpendicular direction in same plane. Where the connection is along same line, both flats shall be overlapped for a minimum of 50mm. L-bend with weld length of 50mm minimum shall be adopted wherever overlap length to be ensured.
- iv. Resistance of welded joint shall not be more than that of GI flat.
- v. Welds shall be treated with red oxide for rust protection and then coated with bitumen compound for corrosion protection.
- vi. While laying earthing electrodes, adding/mixing of chemical compound and water around the electrode in the dug hole shall be as per instructions of OEM. Vendor shall ensure visit of OEM engineer to site at the time of installation for proper guidance/ supervision.
- vii. Other applicable standards:
 - IS: 2629: Recommended practice for hot dip galvanizing of iron and steel - IS: 2633: Method for testing uniformity of coating on zinc coated articles
 - IS: 6745: Methods for determination of mass of zinc coating on zinc coated iron and steel articles.
 - IS: 513: Cold rolled low carbon steel sheets and strips
 - IS: 3063: Fasteners single coil rectangular section spring washers

In compliance to Rule 11 and 61 of Indian Electricity Rules, 1956 (as amended up to date), all non-current carrying metal parts shall be earthed with two separate and distinct earth continuity conductors to an efficient earth electrode.

12. Testing (SI.No.12 of BoQ)

Testing includes all the following activities. The payments against particular testing items as listed in the BoQ shall be admissible only after completion of all the Pre-commissioning inspections/checks/tests as per description given below:

Vendor shall organize all necessary tools/ measuring instruments required to operate the various electrical equipment at the time of commissioning: Digital megger 5KV with PI feature, Earth resistance tester, Phase sequence meter, Clamp meters etc, discharge rods, etc.

12.1. Pre-commissioning inspections / checks / tests on DC side

Vendor shall carry out following minimum pre-commissioning checks:

- a. Verification of firmness of SPV module interconnections (MC4)
- b. Verification of firmness of DC cable terminations at string inverters using torque wrench (for the specified torque values)
- c. Verification of firmness of RS485 cable terminations
- d. Verification of firmness of all earthing connections
- e. Cable megger/ continuity check for all DC power cables
- f. Measurement of open circuit voltage of individual strings
- g. Measurement of earth resistance at individual earth pits of solar array: (a) as disconnected from earth mat grid and also, (b) as connected to earth mat grid
- h. Submission of test reports to BHEL for acceptance.



 Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05

12.2. Pre-commissioning inspections/checks/tests on AC side.

12.2.1. Basic checks

12.2.1.1. Tightness checks:

- Terminations of AC power cables at string inverters, data loggers, ACCB box, LTPDB panels.
- Terminations of Control/ Instrumentation/ Data/ Communication cables wherever applicable.
- Terminations of earthing at all electrical equipments/ panels.
- Terminations of earth chambers of vendor scope

12.2.1.2. Electrical continuity checks

12.2.1.3. Megger (1kV) checks for all 1.1kV grade cables

12.2.1.4. AC/DC supply checks at TBs of all electrical panels/ DBs.

12.2.2. Pre-commissioning electrical tests:

12.2.2.1. String inverters

- DC side open circuit voltage
- Vendor to provide technician support to service engineer of string inverters for all other pre-commissioning tests as per OEM checklist

12.2.2.2. Earth resistance measurements for all chambers of vendor scope

- With electrode connected to grid
- Without connecting electrode to grid

13. Termination of Solar power output for evacuation on existing distribution board of customer (Sl.No.13 of BoQ)

13.1. Laying and termination of cables from ACCB box to existing LTPDB box of customer.

- a) Exact measurement of Cables as per SLD, 1.1kV, Copper/Aluminum, XLPE, armoured as per IS: 7098 part 1 shall be submitted by Contractor to BHEL. These will be supplied by BHEL but installation and laying between ACCB to LTPDB is in vendor scope. Required cable shall be cut out from longer lengths as supplied by BHEL. Necessary cutting arrangement/crimping arrangement and Cable jointing arrangement and all associated supplies will be in the scope of the Contractor.
- b) Nickel plated brass double compression cable glands, cable lugs, SS304 bolts/ nuts/ plain and spring washers shall be in vendor scope of supply. Termination shall be carried out using appropriate tools and torque setting as per specification.

13.2. Laying and termination of cables from BHEL's LTPDB to Customer LT point evacuation.

- a) Exact measurement of Cables as per SLD, 1.1kV, Copper/Aluminum, XLPE, armoured as per IS: 7098 part 1 shall be submitted by Contractor to BHEL. These will be supplied by BHEL but installation and laying between ACCB to LTPDB is in vendor scope. Required cable shall be cut out from longer lengths as supplied by BHEL. Necessary cutting arrangement/crimping arrangement and Cable jointing arrangement and all associated supplies will be in the scope of the Contractor.
- b) Nickel plated brass double compression cable glands, cable lugs, SS304 bolts/ nuts/ plain and spring washers for above cable terminations shall be in vendor scope of



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

~~supply. Termination shall be carried out using appropriate tools and torque setting as per BHEL/CUSTOMER approval.~~

~~c) Wherever spares breakers are available at Customer LT evacuation panel, termination shall be carried. However, few sites where spare breakers not available, LT busbar extension is required from customer LT panel to solar LTPDB and cable shall be terminated.~~

14. Supply and fixing of Name Plate (Sl.No.14 of BoQ)

The quantity mentioned in the BoQ shall be only to meet specific requirements of the Customer specification/Signage for Name plate. These will be generally of size 250x200 mm of steel material and of thickness 2 mm.

In addition to this, Vendor shall use danger boards, wherever required, to ensure safety of the persons during the work at site. For all other places where it is required to fix danger plates as per Good Engineering practice and as per Latest Electricity Act stipulations – the same shall be complied with.

15. Additional Safety Arrangement for compliance of HSE/OHSAS requirement (Sl.No.15 of BoQ)

~~This line item shall be applicable when working on RCC roofs above 4th floor (G+4 and above buildings) or on Tin Sheds above 5 Mtr. Height is required. All necessary items required for compliance of safety norms as per SCC Chapter VII of this Tender document (Part 3) will be arranged and deployed by the contractor at the erection site. The scope includes items such as Insulating mats, working platform for Tin shed/Tilted slopes, Barricading on roof, safety nets, special PPEs, and all other items as required as per Chapter VII (Part 3).~~

~~It is also underlined here that for RCC roofs/Tin Sheds below the heights as mentioned above – all safety compliances as noted under SCC Chapter VII has to be mandatorily complied with. However, cost on this account is already built up within major heads of the BoQ.~~



 Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No.:	REG1920-20190428
		:Part	03/05
		Rev no	00

Part B Special Scope

1. Installation of Supplied items (Special Scope/Part B – Sl.1)

1.1. Installation of Isolation Transformer:

Installation of Isolation transformer is in Vendor scope.

Scope of Installation of Isolation Transformer includes making of suitable foundation, making all terminal connections on incomming and outgoing side. Supply of all accessories like lugs, cage for housing of transformer, nuts and bolts, etc. are in the scope of contractor.

1.2. Installation of Step up Transformer:

Supply of Step Up transformer is in BHEL scope.

Scope of Installation of Step Up Transformer includes making of suitable foundation, making all terminal connections on incomming and outgoing side. Mounting of this BHEL supplied item at suitable location after joint assessment by BHEL, Customer/User is also in Contractor's scope. Supply of all accessories like lugs, nuts and bolts, etc. are in the scope of contractor.

1.3. Installation of Ring Main Unit for connection with HT Line side:

Supply of Ring Main System / Switchgear is in BHEL scope.

Scope of Installation of Ring Main System/Switchgear includes making of suitable foundation, making all terminal connections on incomming and outgoing side. Mounting of this BHEL supplied item at suitable location after joint assessment by BHEL, Customer/User is also in Contractor's scope. Supply of all accessories like lugs, nuts and bolts, etc. are in the scope of contractor.

1.4 Installation of LT Panel (CDB)

Installation of Isolation transformer is in Vendor scope

This scope of Installation includes all required material (copper/Aluminium busbar connection, hardwares, lugs, isolating insulators, danger marks etc.). Requirement of Rigid interconnection through Busbar (other than flexible Cables) shall be complied by making all requisite supply and fixing. Mounting of this BHEL supplied item at suitable location after joint assessment by BHEL, Customer/User is also in Contractor's scope.

2. Supply & Installation of Steel Member for Elevated Superstructure etc. (Special Scope/Part B – Sl.2)

This is a special requirement arising in case installation of Solar PV system is not feasible without making of Superstructure (Elevated type) at site. In such case – prior approval (along with the charted engineer approved Staad reports) shall be taken by contractor from BHEL before initiating any activity in this regard. Supply, fabrication and installation of elevated structure is in vendor scope.

Apart from supply and installation of the elevated Superstructure – Scope would also include, activities like making of drawing, getting the same reviewed and vetted by chartered structure engineer and submitting the same for approval to BHEL. In this regard BHEL will make all attempts to optimize the support structure weight. The same shall be considered by contractor and accordingly, different combinations will be tried by the contractor in the design submitted



	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Part	03/05
		Rev no	00

for approval. In all cases – complete responsibility for suitability, strength and safety as per technical specification of the project will lie wholly with the contractor. All support structure material shall be Steel Sections as per standard and of reputed make. The structure shall be Hot dip galvanized with 80 micron thickness.

3. Supply & Installation of Internet connection with datalogger. (Special Scope/Part B – Sl.3)

This is required for local communication inside the premises of Solar Plant Installation. This is required against specific requirement of customer where the Inverter output is NOT to be fed on the cloud but only on the local network. Following items are covered in the scope of supply, laying, installation, testing and trial run :

- (a) Desktop computer as per BHEL specification.
- (b) Modems
- (c) Switches
- (d) Control Cables.
- (e) All other accessories not listed here.

4. Module Level Monitoring (Optimiser) – (Special Scope/Part B – Sl.4)

Supply of required equipment for Module level monitoring is BHEL scope. All required accessories, control cable and interconnection shall be contractor's scope.

5. String Level Monitoring – (Special Scope/Part B – Sl.5)

For string level monitoring, a string combiner box with facility of monitoring string voltage, current shall be supplied by the contractor. The output parameters of Voltage & Current shall be made available on the data logger/ remote monitoring system.

6. Integration with existing DG (Special Scope/Part B – Sl.6)

The output power from SPV would be fed to the inverters which converts DC produced by SPV array to AC and feeds it into the main electricity grid after synchronization. In case of grid failure, or low or high voltage, solar PV system shall be out of synchronization and shall be disconnected from the grid. Once the DG set comes into service, PV system shall again be synchronized with DG supply and load requirement would be met to the extent of availability of power. 4 pole isolation of inverter output with respect to the grid/ DG power connection need to be provided

This type of integration should adhere to voltage level regulations as per local DISCOM and as per latest commercial circulars.

7. Waterproofing Work (Special Scope/Part B – Sl.7)

This work includes preparatory work before waterproofing work also.

The roofs at buildings may be old. The existing cemented/other tiles may have gaps in between. There may be minor unevenness in the roof which may be levelled by locally applying cement sand mixture on small areas. Such small activities before waterproofing shall also be included.

The waterproofing process which is to be carried out is as below-

Cleaning/scrubbing the whole roof and removing dust and other loose items available at roof.



Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05

Surface preparation or replacing damaged tiles(if required).

Applying approved waterproofing bituminous primer on whole surface and filling the gaps between the tiles.

Waterproofing work shall be done as below:-

Supply and laying of APP modified polymeric membrane having 3 mm thick APP (Atactic polypropylene polymer) modified per fabricated five layer, weight not less than 3.6kg/sqm water proofing membrane, black finished reinforced with non woven polyester matt @ 170Gsm laid over bituminous primed surface @ 0.4 ltr/sqm by torching method with 100mm side and end lap on other layer, membrane shall be laid using butane torch and sealing all joints etc completed in all respect.

8. Bird Spikes (Special Scope/Part B – Sl.8)

Supply, Installation, Fixing of Bird Spikes is in the scope of the contractor. These will be as per approved make and specification of BHEL. The Bird spikes shall be fitted on top edge of the PV Module. This is fitted to prevent perching of birds on modules.

9. Water washing system for SPV modules (Module cleaning system) PROVISION OF WATER PUMP & REQUIRED PIPELINES – (Special Scope/Part B – Sl.9)

Bidder must provide at least one water pump along with required pipelines on each shed structure/building on which solar system is to be set up for making the provision of water availability at the roof top for the periodic cleaning of the Solar Panels. The provision of the pipeline and tap points should be sufficient to ensure that all the Solar Panels can be covered from those points. Module cleaning to be done weekly once to get maximum output from the Solar panels as per rated capacity of Solar Power Plant during warranty period/defect liability period/period of maintenance of 05 (five) years from DOC.

- (a) Vendor shall supply, install and commission permanent arrangement for module washing at the roof top taking into account site conditions.
- (b) Water source for cleaning at site.
- (c) The system shall essentially include the following minimum components:
 - i. Surface pump of appropriate size/ rating with starter shall be installed at respective buildings so as to pump water to roof tops. Suitable RCC civil pedestal and Canopy with frame shall be constructed for this arrangement. Arrangement shall have necessary door/lock provision, steel sections/ steel sheets to withstand wind load etc, corrosion protection painting, fasteners etc. Vendor shall submit drawings for BHEL/CUSTOMER approval during detailed engineering.
 - ii. Vendor shall employ armoured electrical cables of suitable size/rating for all electrical connections. Cables with cable accessories (glands/ lugs/ termination hardware etc) shall be in vendor scope of supply and installation. Cabling to the pumps shall be from ACCB. Cables shall be laid/routed through GI cable trays. All cable terminations including the ones at ACCB panels shall be in vendor scope.
 - iii. UPVC pipes as per relevant IS standards, heavy duty, 6 Kg/sqcm: pump suction/ header pipes (40NB minimum), Feeder pipes (25NB minimum).



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

iv. UPVC elbows, Tees, bends, couplers as applicable, as per relevant IS standards, for jointing and leak proof pressurized pipe fittings.

v. UPVC raiser pipes with ball valves (25NB minimum, metal body, IS marked) and reducer nozzles for fitting hose pipes, at every delivery point. Every raiser pipe shall be fixed on the roof using concrete (PCC) pedestal construction.

vi. Delivery points shall be made available as per solar array layout and space provisions at roof top. Accordingly, number of delivery points shall be provided for cleaning of the entire solar array.

vii. Air release valve fittings (metal body, IS marked) for header pipes at suitable locations.

viii. Air release valve fittings (metal body, IS marked) for feeder pipes at suitable locations.

ix. Control gate valve for header pipes; for maintenance (IS marked) at suitable locations.

x. Control gate valve for feeder pipes; for maintenance (IS marked) at suitable locations.

xi. Non returnable valves (NRV) shall be provided wherever applicable.

xii. Hose pipes, heavy duty 15NB minimum

xiii. All necessary hardware items such as GI clamps/ screws/ bolts/ nuts/ plain washers/ spring washers etc wherever applicable.

(d) Any other items as required to complete the technical/ operational requirements of module washing system.

(e) Vendor shall design and submit the piping and instrumentation diagram (P&ID) of water washing arrangement including the physical sequence of branches, reducers, valves, pressure gauge, delivery points and location of pumps and water storage tanks for BHEL/CUSTOMER approval during detailed engineering. The diagram shall show locations of water source, pipelines, valves, delivery points etc as superimposed on the solar array layout, Bill of materials (item wise description, type / rating, make, model number / part number, quantity) of water washing arrangement with necessary calculations of water flow / pressure / discharge etc for BHEL/CUSTOMER approval during detailed engineering.

(f) All necessary labour, machinery, tools, instruments shall be in vendor scope.

10. Providing services for Loading and unloading during local shifting of material from central storage location to multiple sites as required. (Special Scope/Part B - Sl. 10)

Contract shall provide service for loading and unloading, local shifting of materials from central storage location to the site during the installation.

In this case, vehicle for shifting shall be arranged by BHEL. However, Contract has to arrange proper arrangement for loading by Hydra etc. at the loading location and subsequently for Unloading by Hydra etc. at the Unloading location. Placing of Unloaded goods at the identified place of storage in a proper manner is also in the Contractor's scope.

Ref unit of "lot" taken for 1 event of loading and 1 event of unloading. This line items is applicable when two different walled premises are involved.

81

 Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05

11. Daily & Periodic Maintenance of Solar RTS (Special Scope/Part B – Sl. 11)

Rates against this activity has been invited on per month or per visit basis based on various requirements of maintenance of Solar Rooftop system.

Decision regarding particular line item to be chosen will lie with BHEL.

11.1. Typical Scope of Daily & Periodic maintenance

11.1.1. O&M operations – daily basis

- a) Water cleaning of SPV modules with one cycle of cleaning of all the modules of the power plant not exceeding 7 days. In order to fulfil this requirement, vendor shall organize all necessary resources such as
 - (a) manpower (number of persons for the cleaning work),
 - (b) number of simultaneously operating teams,
 - (c) machinery/ materials/ accessories such as pressurised water pumps, hose pipes, nozzles etc.
 Whenever the integral module washing system of the plant is not operational due to reasons of any kind, vendor shall make alternate arrangements such as water tankers, water delivery mechanisms (pumps, hoses, nozzles and other fittings), operating personnel etc required to fulfil the above specified cleaning of max 7 days/cycle.
- b) Logging of DC, AC, and grid parameters (current, voltage, power, energy etc) at string inverters/ LTPDB/ metering panels, equipment tripping/ breakdown, grid outage etc as per BHEL formats.

11.1.2. O&M activities – monthly basis

- a) Inspection of fire extinguishers (weight, pressure indication, physical status etc) followed by refilling actions, if necessary, based on indications. Report to be submitted as per BHEL approved recording formats.
- b) Earthing resistance measurements for solar array structures, various equipment and lightning arrestors: measured values shall be recorded in registers and reported to BHEL as per BHEL approved recording formats.
- c) Submission of values / status of plant parameters and events for the corresponding month, as below, as per BHEL approved formats:
 - Daily values of solar array at string inverters, ACCB, LTPDB panel levels
 - Daily values of weather parameters (solar energy, wind speed, ambient temperature)
 - Events (with date, time) of faults / tripping / breakdown of equipment
 - Events (with date, time) of grid outage
 - Events (with date, time) of equipment damages, accidents and thefts
 - Activities of module cleaning
- d) (Monthly reports shall be submitted to BHEL for all the above data.

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

e) ~~(Energy generation / meter reading report to be prepared and submitted to the concerned state/central department. Signatures from BHEL/CUSTOMER representatives shall be obtained wherever required.~~

11.1.3. O&M activities – quarterly basis

- a) ~~Cleaning of string inverters, ACCB, LTPDB panels etc to remove accumulated dust.~~
- b) ~~Monitoring and status review, followed by rectification/ calibration/ replenishment/replacement actions as necessary and applicable for following:~~
 - Spare items of all electrical equipment
 - First aid box items – medicines and accessories
 - Safety gadgets
 - Tool kits and measuring instruments
 - Pumps, starters
- c) ~~Submission of quarterly report on above activities to BHEL.~~

11.1.4. O&M activities – yearly basis

- a) ~~Painting of earthing chambers if required based on conditions of rusting.~~
- b) ~~Checking tightness of hardware in MMS structures and tightening wherever required.~~
- c) ~~Checking tightness of power cable terminations in SPV modules (MC4), string inverters, ACCB, LTPDB.~~

11.1.5. O&M activities – as and when required (contractual basis)

- a) ~~Monitoring and operation of plant electrical equipment as and when required:~~
 - ACB and MCCB on/off operations on LT side
 - String inverter operations: review/selection of settings, monitoring the DC/AC/ event/ fault status parameters
 - Maintaining SCADA/Data logger system
 - Water pumping operations
- b) ~~Removal of garbage from solar array field, logging in registers with signatures of operating persons and in charge.~~
- c) ~~Coordinating and liaisoning, on behalf of BHEL, and obtaining renewal of statutory licenses, clearances and approvals from state departments such as electricity boards, CEA/CEIG etc.~~
- d) ~~Repair and replacement of vendor supplied items, by vendor, with urgent action plans and implementation, when the items are found non-working / damaged. The same shall be reported to BHEL within 12 hours from time of observation.~~
- e) ~~Reporting, on an immediate basis (within max 2 hours) of functional problems / damages in BHEL supplied items to facilitate repair / replacement by BHEL. Further, vendor shall correspond / coordinate with respective equipment vendors / service centers, on behalf of BHEL, for getting the service engineers to the site. Later, coordinating with the service engineers during their visit to site, and assisting them in the trouble shooting process until the problem is~~



Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No:-	REG1920-20190428
		Part	03/05

resolved. Vendor shall report to BHEL (within max 2 hours) immediately after the problem is resolved.

- f) Vendor shall keep updating the spares inventory at the site every time there is consumption of spare items towards replacement. In case of shortage of spares, the same shall be reported on an urgent basis (with max 2 hours) to BHEL.
- g) Coordinating with sub-station upon grid failures, line problems etc and implementing the needful steps to restore the plant to normal operation.
- h) Theft incidents: immediate reporting to BHEL, filing FIRs with police stations on behalf of BHEL, coordination for site inspection by insurance companies and clearance of insurance claims, logging of events (date, time) and maintaining records.
- i) Accidents: immediate reporting to BHEL, coordinating with hospitals, logging of events (date, time) and maintaining records.

11.2. Vendor shall deploy personnel as per following description

Technical / administrative / office personnel

- One experienced technical cum administrative in-charge having diploma in electrical/ electronic engineering and experience with overall responsibility for complete plant operations. The in-charge shall have competence to deftly handle technical and operational / crisis problems.
- Working level staff with ITI / diploma level qualifications in engineering with competence for operating electrical/ electronic/ mechanical equipment, taking measurements, data logging / maintaining registers, preparation of reports in computer.
- In addition to the above, separate set of persons shall be deployed for water cleaning of SPV modules on daily basis. Number of persons shall be decided considering maximum 7 days per cleaning cycle.

11.2.1. Vendor shall provide uniforms for the O&M staff.

11.2.2. Similarly, O&M personnel shall be provided with raincoats, toolsets, earthing rods, safety gloves, safety harness, safety goggles, gumboots, helmets and all other personal protective equipment (PPE) that will be relevant to ensure human safety.

11.2.3. Names, qualification, work responsibility of personnel shall be listed on a display board at an appropriate location as suggested by the end customer.

11.2.4. Attendance registers shall be maintained for all the staff, workmen.

11.2.5. Vendor shall ensure statutory requirements such as ESI, PF, labour license, BOCW etc as applicable for their O&M personnel posted at site.

11.2.6. BHEL/CUSTOMER shall have right to disallow any O&M employee, if found unfit to perform. BHEL instructions issued in writing shall be binding on vendor who shall replace the person.

11.2.7. O&M personnel at site shall conform to general regulations in force at site and to any special instructions from BHEL/CUSTOMER administration.

11.2.8. O&M personnel at site shall be deemed to be aware of damages and risks incidental to conditions of rooftop place & works from time to time and

78

	PURCHASE SPECIFICATION	Doc. No:- REG1920-20190428
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Part 03/05
		Rev no 00

~~BHEL/CUSTOMER shall not be responsible for any injury to personnel arising there from.~~

11.3. Training to O&M personnel

~~It is the absolute responsibility of vendor to ensure imparting of necessary training to their O&M personnel to get them acquainted with the operations of various electrical and mechanical equipment of the power plant. For this purpose, vendor shall identify the O&M personnel well in advance and involve them during installation and commissioning stages so that they become well versed with various functional aspects of the power plant.~~

~~Availability of O&M personnel at power plant~~

- ~~Vendor shall ensure that operating staff are present in the power plant during 6:30 AM – 6:30 PM every day. (staggered shift to cover duty time)~~
- ~~Vendor shall ensure that certain minimum operating staff are present at the power plant even on festivals, public holidays and any other unique occasions so that the plant is run under competent supervision on all days.~~

~~O&M personnel shall, strictly, not use any part of the power plant for their personal /residential purposes. Their presence at the plant shall, strictly, be meant only for the purpose of operation and maintenance of plant.~~

12. Grid Integration & start of Net Metering of Solar PV System after getting all approvals, calibration through state department (Special Scope/Part B – Sl. 12)

This line item pertains to liaison part with DISCOM. Activity will start from co-ordination with customer and submission of application form to DISCOM for installation of bidirectional meter. Subsequently (a) arranging issue of net meter (either from local DISCOM or through approved supplier) (b) Calibration of meter through recognized lab of local DISCOM (c) Arranging Testing of new meter (d) Getting replacement order from DISCOM office after inspection of Old/existing energy Meter (e) Getting estimates done for issue of Solar Meter (f) Arranging order from DISCOM for installation of Bidirectional Meter.

Cost of Bidirectional Meter, Solar Meter, Government receipts for calibration etc. shall be borne by BHEL. In case, such items are to be arranged through the contractor – the cost of supply & installation has been covered elsewhere. Minor accessories required during installation of bidirectional meter (to the extent of maximum cost Rs.500/-) shall be in the scope of the contractor. The contractor has to co-ordinate with the agency for installation of net meter at site and the contractor will provide required manpower assistance during installation of the Net Meter.

13. Supply of Bidirectional Meter and Installation (Special Scope/Part B – Sl. 13)

A Bi-directional electronic energy meter shall be supplied, installed and commissioned by the vendor at appropriate place at MRS (main receiving station) of CUSTOMER. The vendor shall take NOC/approval for the connectivity, technical feasibility and synchronization of the Solar

77

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

plant with distribution network and submit to CUSTOMER through BHEL before commissioning of the plant. The Bi directional meter shall be of 0.5 S class of type and make as approved by DISCOM and shall be installed for measurement of Import and export of energy.

The utility meter (Net-meter) has to be bi-directional meter to register both import grid electricity amount as well as export solar electricity amount.

The utility meter (Net-meter) has to be bi-directional meter to register both import grid electricity amount as well as export solar electricity amount. Bidirectional energy meter with CTs and PT, if required, having the feature of recording both the import and export of energy, besides other parameters shall be as per CEA metering regulations or State Grid code as applicable and of the make & specifications as approved by the DISCOM. This shall be installed at the point where interconnection is made between Consumer system and DISCOM system.

If required by the DISCOM or CEA, Reverse power relay arrangement shall be provided at appropriate location/s.

14. Supply and Installation of Solar Meter (Special Scope/Part B – Sl. 14)

Solar Meter (or Solar Energy Meter) is used to record the output of String Inverters. This is required to be installed as per requirement of DISCOM.

The Solar Meter shall be supplied, installed and commissioned by the Contract at appropriate place of CUSTOMER. The vendor shall take NOC/approval for the connectivity, technical feasibility and synchronization of the Solar plant with distribution network and submit to CUSTOMER through BHEL before commissioning of the plant. While required cable shall be supplied by BHEL – all other minor accessories shall be in Contractor's scope.

15. Charger distribution Box supply and Installation (Special Scope/Part B – Sl. 15)

- a) Charger distribution Box (Double door type), shall be in vendor scope of supply and installation.
- b) Charger distribution Box having 1 in and 4 Out
- c) Following rating of MCCB shall be used
 - a. 200 Amps, 01 No
 - b. 63 Amps, 02 Nos
 - c. 32 Amps, 02 No
- d) AC Combiner box must have one earth fault relay and SPD
- e) The AC Combiner box shall have MCCBs for connecting to load point at CUSTOMER building according to the evacuation plan. These shall be L&T/ABB/Schneider reputed make.
- f) MCB: L&T/ C&S/ ABB/ Siemens/ Schneider or reputed equivalent subject to BHEL approval
- g) Indicator lamps shall be L&T/ C&S or reputed equivalent subject to BHEL approval
- h) IS/IEC standards and other general features shall be as per "LT switchgear panel" section of this specification.
- i) Termination of output cable from LTPDB to customer evacuation point along with required terminal cable lugs, bolts and conduit etc

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

~~j) Charger distribution Box should have proper space for connection of 04 nos charger cable & incomer cables. Non metal Gland shall be required for charger cable. Sizes of cable gland shall be decided during detailing.~~

16. FIRE EXTINGUISHERS: (Special Scope/Part B – Sl. 16)

The firefighting system for the proposed power plant for fire protection shall be consisting of: Portable fire extinguishers

- a) The installation of Fire Extinguishers should confirm to TAC regulations and BIS standards.

Vendor shall provide fire extinguishers as follows for fighting fire electrical wiring, live machinery fires and flammable liquid/ gas as per recommendation by relevant fire safety

authority and as per relevant standards IS: 2171 and IS: 10658 marked. Make shall be Safex/ Ceasefire/ Vintex/ Unicare fire safety or any other reputed equivalent subject to BHEL/CUSTOMER approval.

- DCP type (ABC) 9Kg designed/tested IS 15683/ IS: 13849 with safety release valve, NRV and CE approved valve. Dry powder IS 14609 with standard accessories.
- CO2 type Hand 9 Kg with wheel. Designed/tested IS 2878 complete with hose, screw valve, CO2 gas IS 1522, cylinder IS 7285, valve IS 3224. Tested at 250 Kgf/cm2.

Quantity shall be as per vendor scope of supply (deliverables) in this specification.

17. Trial/ Reliability Run/Plant efficiency test for duration of min. 15 days or more. (Special Scope/Part B – Sl. 17)

~~In some cases – BHEL's contract with end user calls for trial/reliability run/plant efficiency test for specified duration. System output data is compiled for the duration on daily basis. In this duration – all performance parameter checks by customer/BHEL is also facilitated. Adequate manpower including experienced engineer, electrician and helpers are to be kept posted at site for continuous monitoring of system performance, data gathering, troubleshooting of any defect, shortcoming and responding to inspection team by closing the Punch Points.~~

18. Arrangement of Inspection by statutory authority like CEA, DISCOM/MNRE/ agency other than customer (example PMC) – as applicable as part of contract requirement (Special Scope/Part B – Sl. 18)

- a) ~~Liaison responsibility for getting the above approvals rests with contractor.~~
- b) ~~Following are the areas of approval, as applicable, for the SPV side portions including solar array and up to 1.1kV side connection point.~~
 - ~~Schemes/ layouts/ calculations such as solar array layout, lighting arrestor layout, module cleaning system, cable trench layout, fire alarm system etc.~~
 - ~~GTP/ datasheets/ GA drawings/ Bill of materials, MQP etc of supply items.~~
 - ~~Factory test reports of supply items including BHEL supplied items.~~
 - ~~Interaction with supervising/ inspection agency such as MRT departments, Transco, CEIG, CEA etc, as applicable, for applying to them/ inviting them for supervision/ inspection at site.~~



26

 BHEL Rudrapur	PURCHASE SPECIFICATION GROUP : REG (RENEWABLE ENERGY GROUP)	Doc. No.:	REG1920-20190428
		Part	03/05

- Interaction/ coordination with customer (CUSTOMER) in the above process as and when required.
- All necessary testing kits/ instruments shall be arranged as per the requirements of inspection agency. Basic instruments such as digital multimeter, 5kV digital megger with PI feature, earth resistance meter, clamp meters etc shall be organized at site at the time of inspection.
- Competent electrical technician shall also be made available at the site.
- Subsequent to site inspection by the concerned agency, vendor shall support the upstream 1.1kV evacuation line/ Vendor in following up with them to obtain their clearance for line charging/ grid synchronization.
- Vendor shall implement all the observations of CEIG related to SPV side portion including solar array and up to 1.1kV connection point to metering panel at plant end.

~~liaison activities with state / central departments / DISCOM/ CEIG etc for necessary approvals / clearances for commissioning, synchronization with grid and post commissioning operation of the plant. (Clearances shall include obtaining prior approvals for all applicable drawings/ documents etc from concerned state / central departments / DISCOM/ CEIG etc.)~~

19. Lighting arrester special type (NFC series-European standard)

~~(Special Scope/Part B – Sl. 19)~~

~~This item is to be supplied against specific requirements arising out as part of the contract specification. Detailed specification, make shall be as per BHEL approved. The Technical Data Sheet, Quality Plan and make shall be got approved by contractor from BHEL.~~

20. Liaison charges for expediting, Bill verification for facilitating BHEL payments based on specific written request from BHEL (Special Scope/Part B – Sl. 20)

~~Apart from basic scope of Solar Rooftop System Installation – BHEL may request the contractor to do liaison with customer for Bill verification, for expediting payment. Such a case shall be counted after the event of system commissioning and handover. Separate Order for this scope may be issued by BHEL for estimated number of such events. Payment shall be processed based on proof of written request for visit from BHEL and proof of visit by contractor and report of visit. Such a work order shall be awarded with mutual consent. Contractor's response in this regard will also form part of the Overall Performance evaluation of the contractor.~~

21. Site survey and generation of site survey report generation in BHEL format.

~~(Special Scope/Part B – Sl. 21)~~

~~Applicable only when site survey has been done by party on BHEL written request – BEFORE release of work order to same party or other.~~

~~Apart from basic scope of Solar Rooftop System Installation – BHEL may request the contractor to do site survey before award of work. Such a case shall be counted before the event of ordering on the contractor. Separate Order for this scope may be issued by BHEL for estimated number of such events. Payment shall be processed based on proof of written request for visit from BHEL and proof of visit by contractor and report of site survey.~~

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

Such a work order shall be awarded with mutual consent. Contractor's response in this regard from time to time will also form part of the Overall Performance evaluation of the contractor.

Whereas preference will be given for ordering to the party who has done site survey. It is possible that in some cases BHEL may have to arrange execution of the work by an agency other than the one who has done site survey.

22. Additional Charges applicable for lifting of material on roof above floor IV or tin shed above 5 Mtrs (Lifting of Material like PCC, Modules, Structure considered) (Special Scope/Part B - Sl. 22)

For high rise buildings and difficult heights of Tin shed roof - additional lifting charges shall be allowed. Additional charges have been considered by estimating that 02 Mandays per Roof per addl. 4 floors is considered for lifting all material typical for system capacity upto 50KW. Quantity shall be finalized in the work order based on actual number of such roofs.

23. Temporary, closed and lockable Storage for BHEL supplied items after unloading till Installation of the BHEL supplied items, floor area for upto 500 KWp (Special Scope/Part B - Sl. 23)

Following area has been considered for such a shed:

For System Capacity 10 KW to Upto 100KW : NIL (material to be immediately installed)

For System Capacity >100KW to upto 500 KW: 1000 Sq.ft floor area.

For System Capacity >500KW to upto 1500 KW: 2100 Sq.ft floor area.

For system capacity upto 100KW - it has been presumed that all supplied items shall be shifted to the place of installation in short span of time. Therefore, requirement of separate storage shed has not been envisaged.

For system capacity more than 100 KW - it has been presumed that generally, the BHEL supplied items shall either be received by customer/user themselves and these will be stored in walled premises of customer/user where security may be available. In such case - creation of temporary shed has NOT been envisaged.

However, for systems of capacity more than 100 KW and for such cases - where BHEL supplied material is NOT received by the customer/user - separate temporary shed has to be constructed by the Contractor.

Contractor shall, at a suitable location at site, as decided based on discussions with BHEL site engineer, construct closed sheds for safe storage of items such as String inverters ACDB, LTPDB boxes, cables etc and other miscellaneous items such as tools, measuring instruments, cable glands/ lugs/ markers, safety gadgets, sign boards etc. Record of such items is to be maintained after necessary Gate entries in CUSTOMER Security records and with Gate pass and Register which shall be carefully preserved and handed over to BHEL.

27

 BHEL	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

~~Responsibility for safety, safekeeping and preservation of material in such storage space as created shall lie wholly with the contractor.~~

- ~~a) These sheds shall have suitable water proof roof and side walls so to ensure that there are no pin holes or joints through which rain water entry is possible. Also, these sheds shall be designed to withstand heavy wind loads. Lockable door shall be provided to ensure safety of these items.~~
- ~~b) Similarly, open yards shall be provided with suitable fencing for safekeeping of solar PV modules, MMS structure items, stone aggregate, sand, bricks, steel materials.~~
- ~~c) Area of all storage yards/sheds shall be selected based on sizes of items. Vendor shall, at the time of starting their activities at site, submit drawings/ sketches/ dimensions etc to obtain approval from BHEL/CUSTOMER.~~
- ~~d) Wherever applicable, suitable raised platforms / arrangements shall be provided to ensure that the items are not affected by water at the ground level during rain, storm, flood etc.~~
- ~~e) Safety of all the contractor supplied items and BHEL Supplied items shall be within vendor scope. Accordingly, vendor shall ensure lock and security for these items.~~



Rudrapur	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

Part C: scope not cover in part A & B

1. AC & DC Cables: (Part C – Sl. 1,3&8)

a. The Specification of wiring material of PV Power plant shall include but not limited to the following:

Sl. No	Item	Description
1.0	DC Cable	From PV module to inverter
1.1	Type	1.1kV grade heavy duty PVC insulated, Double sheathed, UV protected XLPO stranded copper cables as per IS: 7098 (Part I & II) – 1976 or IS 1554 or IS9537/IEC60227/IS694 or Solar DC Cable as per BS EN 50618
1.2	Size	1 core 4 sq. mm Unarmored
1.3	Laying	The cable must be laid through PVC conduit /GI pipe/ cable tray on roof and indoor. In case of using metallic pipe as conduit proper grounding of the conduit must be done.
2.0	AC Cable	From inverter to ACDB and ACDB to distribution panel/LT panel
2.1	Type	1.1kV grade heavy duty PVC insulated galvanized strip/wire armored XLPE stranded Cu conductor cables as per IS: 7098 (Part I & II) – 1976 or IS 1554 or IS9537/IEC60227/IS694.
2.2	Size	As per site requirement
2.3	Laying	The cable must be laid through PVC conduit /GI pipe/ cable tray on roof and indoor. In case of using metallic pipe as conduit proper grounding of the conduit must be done.

b. Procedure of cable laying:

- Cable terminations shall be made with suitable cable lugs & sockets etc, crimped properly and cables shall be provided with dry type compression glands wherever they enter junction boxes/ panels/ enclosures at the entry & exit point of the cubicles. The panels bottoms should be properly sealed to prevent entry of snakes/lizard etc. inside the panel. All cables shall be adequately supported. Outside of the terminals / panels / enclosures, shall be protected by conduits. Cables and wire connections shall be soldered, crimp-on type or thimble or bottle type.
- Only terminal cable joints shall be accepted. Cable joint to join two cable ends shall not be accepted
- All cable/wires/control cable shall be marked with good quality letter and number ferrules of proper sizes so that the cables can be identified easily.
- All fasteners will be made of Stainless steel or Aluminum or UV Protected PVC.
- All DC wire upto DCDB & Inverter shall be covered in CPVC (suitable size) heavy duty (SDR 11) as per IS 15778:2007 & ASTMD 2846.
- All AC cable shall be routed in covered perforated metal cable tray.
- All AC/DC cable shall be properly tied by plastic ties.
- DC wires shall be routed through proper marking/naming by ferrules.
- Earthing by greens wires only, if required.

BHEL	PURCHASE SPECIFICATION	Doc. No.:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

2. String Inverter (Part B – Sl. 2)

As SPV array produce direct current electricity, it is necessary to convert this direct current into alternating current and adjust the voltage levels to match the grid voltage. Conversion shall be achieved using an electronic Inverter and the associated control and protection devices. All these components of the system are termed the "Power Conditioning Unit (PCU)" or Central/String Inverter. In addition, the PCU/Central/String Inverter shall also house multiple MPPT (Maximum Power Point Tracker) (Minimum two), an interface between Solar PV array & the Inverter, to the power conditioning unit/inverter should also be DG set interactive. If necessary, Inverter output should be compatible with the grid frequency.

Sl. No	Technical parameter	Specification
1.	Type	Grid Connected String Inverter (transformer less).
2.	Make	As per approved make list enclosed.
3.0	Standards	
3.1	Efficiency Measurement	IEC 61683/ Equivalent BIS Std.
3.2	Environmental testing	IEC 60068-2 (1,2,14,30) / Equivalent BIS Std.
3.3	EMC	IEC 61000/Equivalent BIS Std.
3.4	Islanding Prevention Measurement	Bidder to specify
3.5	MPPT	Bidder to specify
3.6	Type Test certificate issuing authority (for Sl. No. 3.1,3.2,3.3,3.4 and 3.5)	NABL/ IEC Accredited Testing Laboratories or MNRE approved test centers.
4.0	Input DC	
4.1	Voltage range	Min 200-1000 V
4.2	MPP voltage range	Min 200-1000 V
4.3	Power Control	MPPT (Multiple)
5.0	Output AC	
5.1	Output voltage and phase	415V, 3Phase, 50Hz (In case single phase inverters are offered, suitable arrangement for balancing the phases must be made.)
5.2	Reactive power	0.9 lagging to 0.9 leading
5.3	Total Harmonic Distortion (THD)	< 3 % at rated power
5.4	Power factor at rated current	0.98-1.00
5.5	Grid frequency tolerance range	± 3% Hz
5.6	Grid voltage tolerance	±10%
5.7	No-load losses	Less than 1% of rated power



Rudrapur

PURCHASE SPECIFICATION

Doc. No:- REG1920-20190428

Part 03/05

Rev no 00

5.8	Self-power consumption	Standby power consumption of Inverter shall not exceed 1 Watt
6.0	Efficiency	>93% (in case of 10kw or above with in-built galvanic isolation) >97% (in case of 10kw or above without in-built galvanic isolation) >90% (in case of less than 10kw)
7.0	Protection	
7.1	DC Side	Disconnection device Reverse polarity protection Reverse polarity protection. Over voltage protection. Surge protection
7.2	AC Side	Short circuit protection Over voltage/current limitation Anti-Islanding protection AC surge protection
7.3	Protection over and under Grid frequency protection.	Bidder to specify
7.4	Ground fault / Grid Monitoring	Bidder to specify
7.5	Over Temperature protection	Bidder to specify
8.0	Display	
8.1	Display type	LCD/LED
8.2	Display parameter	Bidder to specify
9.0	Communication	
9.1	Communication port	Bidder to specify
10.0	General	
10.1	Operating Temperature	-20 Deg. C to + 50 De. C
10.2	Humidity	95% non-condensing.
10.3	Dimensions	Shall be provided by the Bidder.
10.4	Weight	Shall be provided by the Bidder.
10.5	Cooling	Cooling arrangement (if any) details shall be furnished by the Bidder.
10.6	Ingress protection (IP)	IP 65 or better (Out Door Installation)
10.7	Maximum altitude	Bidder to mention up to what altitude above sea level inverters will work without de-rating.
10.8	Noise level	<68 dB
10.9	Switching Devices	IGBT/MOSFET



PURCHASE SPECIFICATION		Doc. No:-	REG1920-20190428
Rudrapur		Part	03/05
	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

10.10	Control	Microprocessor/DSP
-------	---------	--------------------

Other important Technical Requirements :

- a) The String Inverter must have the feature to work in tandem with other similar PCU's and be able to be successively switched "ON" and "OFF" automatically based on solar radiation variations during the day. Inverters must operate in synergy and intelligently to optimize the generation at all times with minimum losses.
- b) The String Inverter must have minimum of DC input capacity .The PCU shall be capable of controlling power factor dynamically.
- c) String inverter shall be capable of complete automatic operation including wake-up, synchronization & shutdown.
- d) The output of power factor of String inverter is suitable for all voltage ranges or sink of reactive power, inverter should have internal protection arrangement against any sustainable fault in feeder line and against the lightning on feeder.
- e) Built-in meter and data logger shall be provided to monitor plant performance through external computer.
- f) Anti-islanding (Protection against Islanding of grid): The Central/String shall have anti islanding protection in conformity to IEEE 1547/UL 1741/ IEC 62116 or equivalent BIS standard.
- g) The String inverter generated harmonics, flicker, DC injection limits, Voltage Range, Frequency Range and Anti-Islanding measures at the point of connection to the utility services should follow the latest CEA (Technical Standards for Connectivity Distribution Generation Resources) Guidelines.
- h) String Inverters should comply with applicable IEC/ equivalent BIS standard for efficiency measurements and environmental tests as per standard codes IEC 61683/IS 61683 and IEC 60068-2 (1,2,14,30)/ Equivalent BIS Std.
- i) The MPPT units environmental testing should qualify IEC 60068-2 (1, 2, 14, 30)/ Equivalent BIS std. The junction boxes/ enclosures should be IP 65 or better and as per IEC 529 specifications.
- j) The PCU or Central/String inverters should be tested from the MNRE approved test centres/ NABL/ BIS/ IEC accredited testing- calibration laboratories. In case of imported power conditioning units, these should be approved by international test houses. Test report shall be submitted before supply.

3. DCDB (Part B – Sl. 4)

DCDB is to be provided in the PV yard for connecting cables from solar string to string inverter. DCDB shall be dustproof, vermin and weatherproof and shall be made of GRP/FRP/Powder coated Aluminium/cast aluminium alloy. The material used for boxes shall be made with UV resistant material to avoid degradation during module life and the sealing shall comply IP65 degree of protection.

DCDB shall have suitable cable entry points fitted with cable glands of appropriate sizes for both incoming and outgoing cables. All wires/cables must be terminated through cable lugs.

Terminals shall be connected to copper bus bar arrangement of proper sizes. Suitable markings shall be provided on Bus bar for easy identification and cable ferrules shall be fitted at the cable termination points for identification.

The junction box shall have hinged door with EPDM rubber gasket to prevent water entry and shall have provision for earthing.

DCDB must comprise of following:

	PURCHASE SPECIFICATION	Doc. No:-	REG1920-20190428
		Part	03/05
Rudrapur	GROUP : REG (RENEWABLE ENERGY GROUP)	Rev no	00

- Arrangement for group array isolation.
- Test point for subgroup fault location.
- Shall have suitable capacity MCBs/MCCB, DC breaker, surge (Type II SPD, MOV), fuse protection device and suitable reverse blocking diode or bypass diodes to prevent hot spots in case of cell mismatch or shading.
- It Shall have DC disconnect switch and proper earthing arrangements.
- All fuses shall have DIN rail mountable fuse holders and shall be housed in thermoplastic IP65 enclosure with transparent covers.
- All internal wiring shall be carried out with 1100V grade stranded Cu wires.
- String fuses shall be provided in both positive and negative legs of the string cabling. String fuses shall be of PV category and dedicated to solar applications and conform to IEC 60269-6 or UL-2579 standards.

The design and components of DCDB must be approved by BHEL prior to Manufcaturing/ordering.

4. ACDB (Part B – Sl. 5)

- AC Distribution Panel Board (DPB) shall control the AC power from PCU/ inverter, and should have necessary surge protection devices, MCB/MCCBs & AC circuit breaker with phase indication of R,Y,B. Interconnection from ACDB to mains at LT Bus bar while in grid tied mode.
- All switches and the circuit breakers, connectors should conform to IEC 60947, part I, II and III/ IS60947 part I, II and III.
- The changeover switches, cabling work should be undertaken by the bidder as part of the project.
- All the Panel's shall be metal clad, totally enclosed, rigid, floor mounted, air -insulated, cubical type suitable for operation on three phase / single phase, 415 or 230 volts, 50 Hz
- The panels shall be designed for minimum expected ambient temperature of 45 degree Celsius, 80 percent humidity and dusty weather.
- All panels will have protection of IP65 or better.
- It Shall have AC disconnect switch and proper earthing arrangements
- Should conform to Indian Electricity Act and rules (till last amendment).
- All the 415 AC or 230 volts devices / equipment like bus support insulators, circuit breakers, SPDs, VTs etc., mounted inside the switchgear shall be suitable for continuous operation and satisfactory performance under the following supply conditions

Variation in supply voltage	+/- 10%
Variation in supply frequency	+/- 3 Hz

- Ac combiner box (3 in 1 out) with proper MCCB & safty device at each input and output shall be supplied & installed by bidder (sr 5(c)). All the 415 AC or 230 volts devices / equipment like bus support insulators, circuit breakers, SPDs, VTs etc., mounted inside the switchgear shall be suitable for continuous operation and satisfactory performance under the following supply conditions.

5. Support Structure:

Hot dip galvanizes 80 Micron module mounting structure shall be supplied by the bidder. Structure shall be design to withstand the wind velocity of that zone.



Rudrapur

PURCHASE SPECIFICATION

GROUP : REG (RENEWABLE ENERGY GROUP)

Doc. No:-	REG1920-20190428
Part	03/05
Rev no	00

LIST OF ENCLOSURES:

Following enclosure makes the part of REG1920-20190330

- a) SPV Module drawing
- b) SPV Module Data Sheet
- c) SCC
- d) GCC