

## Contents

|                                                                                                |                                     |
|------------------------------------------------------------------------------------------------|-------------------------------------|
| SECTION 3:.....                                                                                | 3                                   |
| PROJECT DETAILS & GENERAL TECHNICAL REQUIREMENTS (FOR ALL EQUIPMENT UNDER PROJECT).....        | 3                                   |
| 1. General .....                                                                               | 3                                   |
| 2. Project Details .....                                                                       | 3                                   |
| 3. Meteorological Data .....                                                                   | 3                                   |
| 4. Instruction to Bidders .....                                                                | 4                                   |
| 5. Standards.....                                                                              | 5                                   |
| 6. Services to be Performed by the Equipment being furnished.....                              | 6                                   |
| 7. Engineering Data .....                                                                      | 6                                   |
| 8. Colour Scheme and Codes .....                                                               | 8                                   |
| 9. Material/ Workmanship.....                                                                  | 9                                   |
| 10. Rating Plates, Name Plates and Labels.....                                                 | 12                                  |
| 11. First Fill of Consumable, Oil and Lubricant.....                                           | <b>Error! Bookmark not defined.</b> |
| 12. Design Improvements.....                                                                   | 12                                  |
| 13. Quality Assurance Programme .....                                                          | 12                                  |
| 14. Inspection, Testing and Inspection Certificate .....                                       | 14                                  |
| 15. Tests .....                                                                                | 15                                  |
| 16. Packing and Shipping .....                                                                 | 16                                  |
| 17. Protection .....                                                                           | 16                                  |
| 18. Painting and Finishing of Metal Surfaces .....                                             | 16                                  |
| 19. Handling, Storing and Installation.....                                                    | 17                                  |
| 20. Protective Guard .....                                                                     | 19                                  |
| 21. Design Co-ordination .....                                                                 | 19                                  |
| 22. Design Co-Ordination Meeting.....                                                          | 19                                  |
| 23. Tools and Tackles.....                                                                     | 19                                  |
| 24. Equipment Bases .....                                                                      | 19                                  |
| 25. Support Structure.....                                                                     | <b>Error! Bookmark not defined.</b> |
| 26. Clamps and Connectors including Terminal Connectors.....                                   | <b>Error! Bookmark not defined.</b> |
| 27. Control Cabinets, Junction Boxes, Terminal Boxes & Marshalling Boxes for Outdoor Equipment |                                     |
| 20                                                                                             |                                     |

|                                                                                                           |                                                                                                                               |                                     |
|-----------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------|-------------------------------------|
| 28.                                                                                                       | Auxiliary Switches .....                                                                                                      | 21                                  |
| 29.                                                                                                       | Terminal Blocks and Wiring.....                                                                                               | 21                                  |
| 30.                                                                                                       | Lamps and Sockets .....                                                                                                       | 22                                  |
| 31.                                                                                                       | Bushings, Hollow Column Insulators, Support Insulators.....                                                                   | <b>Error! Bookmark not defined.</b> |
| 32.                                                                                                       | Motors .....                                                                                                                  | <b>Error! Bookmark not defined.</b> |
| 33.                                                                                                       | Rating Plates, Name Plates and Labels.....                                                                                    | 23                                  |
| 34.                                                                                                       | Radio Interference Voltage (RIV) Test.....                                                                                    | <b>Error! Bookmark not defined.</b> |
| Annexure-A: ....._List of Standards and Specifications/ General Standards/ Indian Electricity Rules ..... |                                                                                                                               | 24                                  |
| 1.                                                                                                        | Circuit Breakers .....                                                                                                        | <b>Error! Bookmark not defined.</b> |
| 2.                                                                                                        | Current Transformers, Voltage Transformers and Coupling Capacitor Voltage Transformers... <b>Error! Bookmark not defined.</b> |                                     |
| 3.                                                                                                        | Bushing Insulators .....                                                                                                      | <b>Error! Bookmark not defined.</b> |
| 4.                                                                                                        | Surge Arresters.....                                                                                                          | 24                                  |
| 5.                                                                                                        | Cubicles and Panels & Other related Equipment .....                                                                           | 25                                  |
| 6.                                                                                                        | Lt Switchgear.....                                                                                                            | <b>Error! Bookmark not defined.</b> |
| 7.                                                                                                        | Disconnecting Switches .....                                                                                                  | <b>Error! Bookmark not defined.</b> |
| 8.                                                                                                        | Protection and Control Equipment.....                                                                                         | <b>Error! Bookmark not defined.</b> |
| 9.                                                                                                        | Motors .....                                                                                                                  | <b>Error! Bookmark not defined.</b> |
| 10.                                                                                                       | Material and Workmanship Standards .....                                                                                      | 25                                  |
| 11.                                                                                                       | Clamps and Connectors .....                                                                                                   | <b>Error! Bookmark not defined.</b> |
| 12.                                                                                                       | Strain and Rigid Bus-Conductor.....                                                                                           | <b>Error! Bookmark not defined.</b> |
| 13.                                                                                                       | Battery Chargers.....                                                                                                         | <b>Error! Bookmark not defined.</b> |
| 14.                                                                                                       | Battery .....                                                                                                                 | <b>Error! Bookmark not defined.</b> |
| 15.                                                                                                       | Wire and Cables .....                                                                                                         | 25                                  |
| 16.                                                                                                       | Galvanizing.....                                                                                                              | 26                                  |
| 17.                                                                                                       | Fire Protection.....                                                                                                          | <b>Error! Bookmark not defined.</b> |
| 18.                                                                                                       | Steel Structures .....                                                                                                        | <b>Error! Bookmark not defined.</b> |
| 19.                                                                                                       | Other Civil Works Standards .....                                                                                             | <b>Error! Bookmark not defined.</b> |

**SECTION 3****PROJECT DETAILS & GENERAL TECHNICAL REQUIREMENTS****1. General**

1. This section stipulates the general technical requirements under the contract and will form integral part of the technical specification.
2. The provisions under this specification are intended to supplement requirement for the materials, equipment and services covered under this specification and is not exclusive. However, in case of conflict between requirements specified in this section and requirements specified in other sections the requirements specified under respective sections shall hold good.

**2. Project Details**

Panipat Refinery is a PSU Refinery and is having capacity of 15 MMTPA, catering the customers of northern India and is strategically important as per national interest. The refinery is located at Panipat, Haryana and was commissioned in the year 1998.

Presently 132KV supply to Panipat Refinery is provided from 2 sections of grid (one from PTPS and one from Munak) and point of supply is at Panipat Refinery 132KV switchyard. Panipat Refinery complex is consisting of Refinery (will be marked as PR here onwards) and Naphtha cracker complex (will be marked as PNCP here onwards). As a strategic initiative, Panipat Refinery is planning for Bulk power import from HVPNL (Haryana Vidyut Prasaran Nigam Limited) at 220 KV level of 70 MW.

In view of this, Indian Oil Corporation Ltd. (IOCL) - Panipat Refinery is in the process of developing infrastructure to import 70 MW power from grid at 220 KV. Infrastructure development for grid power import at 220KV jobs consists of Inside Battery Limit (ISBL) jobs, Outside Battery Limit (OSBL) jobs.

| Sl. No. | Description          | Particulars                                                                                                              |
|---------|----------------------|--------------------------------------------------------------------------------------------------------------------------|
| 1       | Customer             | Indian Oil Corporation Ltd.                                                                                              |
| 2       | Consultant           | TATA Consulting Engineers Ltd.                                                                                           |
| 3       | Project              | LSTK job for ISBL work of 220KV Grid Power Import at IOCL, Panipat Refinery                                              |
| 4       | Project location     | Panipat (City): 16 Km (approx.)<br>Chandigarh Highway: 11 Km (approx.)<br>Noida (Advant)/ Delhi: 150 Km/ 80 Km (approx.) |
| 5       | Transport facilities | Well connected by road, rail & air with other parts of the country.                                                      |

**3. Meteorological Data**

Equipment to be supplied against this specification shall be suitable for satisfactory continuous operation under the following tropical conditions,

| Sl. No. | Technical Parameters                    | Unit                    | Particulars |
|---------|-----------------------------------------|-------------------------|-------------|
| 1       | Location                                | Panipat, Haryana, India |             |
| 1.1     | Maximum ambient temperature             | °C                      | 50          |
| 1.2     | Minimum ambient temperature             | °C                      | -5          |
| 1.3     | Average ambient temperature             | °C                      | 35          |
| 1.4     | Design ambient temperature              | °C                      | 45          |
| 2       | Average no. of thunder storm days       | Days                    | 45          |
| 3.1     | Maximum Relative humidity               | %                       | 95          |
| 3.2     | Maximum Relative humidity               | %                       | 26          |
| 4       | Average Annual Rain Fall                | Mm                      | 900         |
| 5       | Maximum Wind Pressure                   | Kg/ sqm                 | 195         |
| 6       | Maximum Altitude above Mean Sea Level   | M                       | 1000        |
| 7       | Isoceraunic Level                       | Days/ Year              | 45          |
| 8       | Seismic Level (Horizontal Acceleration) | Zone                    | 4           |
| 9       | Average no. of rainy day per Year       | Days/ Year              | 120         |

NOTE: Moderately hot and humid tropical climate conducive to rust and fungus growth. The climate conditions are also prone to wide variations in ambient condition. Smoke is also present in the atmosphere. Heavy lightening also occurs during June to October. Switchyard is inside the refinery premise which is also prone to other corrosive gases like sulphur, H<sub>2</sub>S, Chlorine etc.

#### 4. Instruction to Bidders

1. The bidders shall submit the technical requirements, data and information as per the technical specifications provided in the bid documents.
2. The bidders shall furnish catalogues, engineering data, technical information, design document, drawings etc fully in conformity with the technical specification.
3. It is recognised that the Manufacturer may have standardised on the use of certain components, materials, processes or procedures different than those specified herein. Alternate proposals offering similar equipment based on the manufacturer's standard practice will also be considered provided such proposals meet the specified designs, standard and performance requirements and are acceptable to the owner. Unless brought out clearly, the Bidder shall be deemed to conform to this specification scrupulously; All deviations from the specification shall be clearly brought out in the respective schedule of deviations. Any discrepancy between the specification and the catalogues or the bid, if not clearly brought out in the schedule, will not be considered as valid deviation.

4. Equipment furnished shall be complete in every respect with all mountings, fittings, fixtures and standard accessories normally provided with such equipment and/or needed for erection, completion and safe operation of the equipment as required by applicable codes though they may not have been specifically detailed in the technical specifications unless include in the list of exclusions. Materials and components not specifically stated in the specification but which are necessary for commissioning and satisfactory operation of the switchyard shall be deemed to be included in the scope of the specification. All similar standard components/parts of similar standard equipment provided, shall be interchangeable with one another.
5. Unless brought out clearly in the respective schedule of deviations, it will be considered that, the bid proposal scrupulously confirms compliance to the specification. The bidder must bring out all the deviations in the bid proposal.
6. In case there is a discrepancy between the data offered equipment and catalogue furnished, and unless the deviations are brought out clearly in the Technical Deviation Schedule, the equipment will be deemed to conform compliance to the specification scrupulously.
5. **Standards**
  1. The works covered by the specification shall be designed, engineered, manufactured, built tested and commissioned in accordance with the Acts, Rules, Laws and Regulations of India.
  2. The equipment to be furnished under this specification shall conform to latest issue with all amendments of standard specified of this section as well as under respective Sections/Chapters of the specification.
  3. In addition to meeting the specific requirement called for in the respective sections of the Technical Specification, the equipment shall also conform to the general requirement of the relevant standards and shall form an internal part of the specification.
  4. The Bidder shall note that standards mentioned in the specification are not mutually exclusive or complete in themselves, but intend to complement each other.
  5. The Manufacturer shall also note that list of standards presented in this specification is not complete. Wherever necessary the list of standards shall of the specification shall take precedence.
  6. When the specific requirements stipulated in the specification exceed or differ than those required by the applicable standards, the stipulation of the specification shall take precedence.
  7. Other internationally accepted standards which ensure equivalent or better performance than that specified in the standards referred shall also be accepted.
  8. In case governing standards for the equipment is different from IS or IEC, the salient points of difference shall be clearly brought out in deviation sheets along with English language version of standard or relevant shall be subject to Owner's approval.

9. Indicative List of Standards and Specifications General Standards Indian Electricity Rules shall be as per Annexure- A.
6. Services to be performed by the Equipment being furnished
  1. The 220/33 kV system is being designed to limit the switching surge over voltage and the power frequency over voltage within limits of IEC. The equipment furnished under this specification shall perform all its functions and operate satisfactorily without showing undue strain, re-strike etc. under such over voltage conditions and in system where line lengths would extend up to 200 km.
  2. All equipment shall also perform satisfactorily under various Electro-mechanical and meteorological conditions of the site of installation.
  3. All the Equipment shall be able to withstand all external and internal mechanical, thermal and electromechanical forces due to various factors like wind load, temperature variation, short circuit etc. for the equipment.
  4. The bidder shall design the various forces for terminal connectors of the equipment are required to withstand.
  5. The equipment shall also comply to the following:
    - All outdoor EHV equipment shall be suitable for hot line washing.
    - To facilitate erection of equipment, all items to be assembled as site shall be "match marked". All piping, if any between equipment control cabinet operating mechanism to marshalling box of the equipment shall bear proper identification to facilitate the connection at site.
7. Engineering Data
  1. The furnishing of engineering data by the Manufacturer shall be in accordance with the schedule for each set of equipment as specified in the technical specifications.
  2. The review of these data by the owner will cover only general conformance of the data to the specifications and documents, interfaces with the equipment provided under the specifications, external connections and of the dimensions which might affect substation layout. This review by the owner may not indicate a thorough review of all dimensions, quantities and accuracy of the information submitted. This review and/or approval by the owner shall not be considered by the Manufacturer, as limiting any of his responsibilities and liabilities for mistakes and deviation from the requirements, specified under these specifications and documents.
  3. All engineering data submitted by the Manufacturer after final process including review and approval by the owner shall form part of the Contract Document and the entire works performed under these specifications shall be performed in strict conformity, unless otherwise expressly requested by the owner in Writing.
  4. LIST OF DOCUMENTS
    - 4.1 The bidder must furnish a detailed list of drawings/documents along with the bid proposal which he intends to submit to the owner after awarded of the contract.

4.2 The supplier shall necessarily submit all the drawings/ documents unless anything is waived. The supplier shall submit required sets of drawings/design documents/test reports as may be required for the approval of the owner.

4.3 All engineering data submitted by the Manufacturer after final process including review and approval by the Owner shall form part of the Contract Document and the entire works performed under these specifications shall be performed in strict conformity, unless otherwise expressly requested by the owner in Writing.

## **5. DRAWINGS**

5.1 All drawing submitted by the Manufacturer including those submitted at the time of bid shall be in sufficient detail to indicate the type, size, arrangement, material description, Bill of Materials, weight of each component, break-up for packing and shipment, the external connections, fixing arrangement required, the dimensions required for installation and interconnections with other equipment and materials, clearances and spaces required for installation and interconnection between various portions of equipment and any other information specifically requested in the specifications.

5.2 Each drawing submitted by the Manufacturer shall be clearly marked with the name of the Owner, the unit designation, the specifications title, the specification number and the name of the Project. If standard catalogue pages are submitted, the applicable items shall be indicated therein. All titles, noting, markings and writings on the drawing shall be in English. All the dimensions should be in metric units.

5.3 Further work by the Manufacturer shall be in strict accordance with these drawing and no deviation shall be permitted without the written approval of the Owner if so required.

5.4 All manufacturing and fabrication work in connection with the equipment prior to the approval of the drawing shall be at the Manufacturer's risk. The Manufacturer may make any changes in the design which are necessary to make the equipment conform to the provisions and intent of the Contract and such changes will again be subject to approval by the Owner. Approval of Manufacturer's drawing or work by the Owner shall not relieve the Manufacturer of any of his responsibilities and liabilities under the Contract.

## **5.5 APPROVAL PROCEDURE**

The scheduled dates for the submission of these as well as for, any data/information to be furnished by the Owner would be discussed and finalised at the time of award. The supplier shall also submit six (6) copies of all drawings/design documents/test report for approval of the Owner. The following tentative schedule shall be followed in general for approval. However final schedule shall be prepared with approval of Engineer in-charge post award of approval.

|   |                                                                       |                           |
|---|-----------------------------------------------------------------------|---------------------------|
| 1 | Submission, comments, by resubmission and approval recommended agency | Within 4 weeks of receipt |
|---|-----------------------------------------------------------------------|---------------------------|

|   |                                                    |                                                                                                   |
|---|----------------------------------------------------|---------------------------------------------------------------------------------------------------|
| 2 | Approval/ comments/ by Owner on initial submission | Within 4 weeks of receipt.                                                                        |
| 3 | Resubmission                                       | Within 3 (three) weeks (whenever from date of comments required) including both ways postal time. |
| 4 | Approval or comments                               | Within 3 weeks of receipt of commented drawing/ documents.                                        |
| 5 | Furnishing of distribution copies                  | 1 weeks from the date of last approval.                                                           |

NOTE: The Manufacturer may please note that all resubmission must incorporate all comments given in the submission by the Owner failing which the submission of documents is likely to be returned.

5.6 The drawing which are required to be referred frequently during execution should be submitted on cloth lined paper.

#### 5.7 OTHER REQUIREMENTS OF DOCUMENTATION

5.7.1 One set of soft copy of all drawings, manual, catalogues to be submitted along with 6 sets of hardcopies during submission of as built documents.

5.7.2 6 copies of instruction/operation manuals for complete project shall also be furnished. The instruction Manuals shall contain full details of drawing of all equipment being supplied under this contract, their exploded diagrams with complete instruction for storage, handing, erection, commissioning, testing, operation, trouble shooting, servicing and overhauling procedures.

5.7.3 If after the commissioning and initial operation of the substation, the instruction manuals require any modifications/additions/changes, the same shall be incorporated and the updated final instruction manual in the form of one (1) reproducible original and twelve (12) copies shall be submitted by the Manufacturer to the Owner.

The Manufacturer shall furnish to the Owners, twelve (12) sets of spare part catalogue.

#### 5.8 TITLE BLOCK

Title block for project shall be as follows,

|                    |                                                                             |
|--------------------|-----------------------------------------------------------------------------|
| Customer:          | Indian Oil Corporation Ltd.                                                 |
| Consultant:        | TATA Consulting Engineers Ltd.                                              |
| LSTK Manufacturer: | Bharat Heavy Electricals Ltd.                                               |
| Project:           | LSTK job for ISBL work of 220KV Grid Power Import at IOCL, Panipat Refinery |

### 8. Colour Scheme and Codes

- The Manufacturer shall propose parts a colour scheme for those equipment/ Items for which the colour scheme has not been specified in the specification, for the approval of Owner. The decision of Owner shall be final. The scheme shall include,
  - Finishing colour of Indoor equipment.

- Finishing colour of Outdoor equipment.
- Finishing colour of all cubicles.
- Finishing colour of various auxiliary system equipment including piping.
- Finishing colour of various building items.

2. All steel structures, plates etc. shall be hot dip galvanised or painted with noncorrosive paint on a suitable primer as per the provisions of the respective Section. It may be noted that normally all Owner's electrical equipment in Owner's switchyard are painted with shade 631 of IS-5 and Owner will prefer to follow the same for this project also. All the indoor cubicles shall be of same colour scheme and for other miscellaneous items colour scheme will be approved by the Owner.

## **9. Material/ Workmanship**

### **1. GENERAL REQUIREMENTS**

- 1.1 Where the specification does not contain characteristics with reference to workmanship, equipment, materials and component of the covered Equipment, it is understood that the same must be new, of highest, grade of the best quality of their kind, conforming to the best engineering practice and suitable for the purpose for which they are intended.
- 1.2 The equipment must be new, of highest grade, the best quality of their kind, to best engineering practice and latest state of art in accordance with purpose for which they are intended and to ensure satisfactory performance throughout the service life.
- 1.3 In case where the equipment, material or components are indicated in the specification as "similar" to any special standard, the Owner shall decide upon the question of similarity. When required by the specification or required by the Owner the supplier shall submit, for approval, all the information concerning the material or components supplied, installed or used without such approval shall run the risk of subsequent rejection, it being understood that the cost as well as the time delay associated with the rejection shall be borne by the Supplier.
- 1.4 The design of the work shall be such that installation, future expansions, replacement and general maintenance may be undertaken with a minimum of time and expenses. Each component shall be designed to be consistent with its duty and suitable factors of safety, subject to mutual agreements and shall be used throughout the design. All joints and fastenings shall be devised; constructed and documented so that the component part shall be accurately positioned and retained to fulfil their required function. In general, screw threads shall be standard metric threads. The use of other thread forms will only be permitted when prior approval has been obtained from the Owner.
- 1.5 Whenever possible, all similar part of the works shall be made to gauge and shall also be made interchangeable with similar parts. All spare parts shall be interchangeable with, and shall be made of the same material and workmanship as the corresponding

parts of the equipment supplied under specification. Where feasible, common component units shall be Employed in different pieces of the equipment in order to minimize spare parts stocking requirements. All equipment of the same type and rating shall be physically and electrically interchangeable.

- 1.6 All material and equipment shall be installed in strict accordance with the manufacturer's recommendation(s). The erection procedure must be approved by the OEM and erection completion shall be certified by OEM for satisfactory completion. The commissioning of all major equipment as recommended by Engineer in-charge.
- 1.7 Only first-class work in accordance with the best modern practice will be accepted. Installation shall be constructed as being the erection of equipment at its permanent location. This, unless otherwise specified, shall include unpacking, cleaning and lifting into position, grouping, levelling, aligning, coupling of or bolting down to previously installed equipment bases/ foundation, performing the alignment check and final adjusting prior to initial operation, testing and commissioning in accordance with the manufacturer's tolerances and instruction and the specification. All factory assembled rotating machinery shall be checked for alignment and adjustments made as necessary to re-establish the manufacturer's limits suitable guards shall be provided for the protection of personnel on all exposed rotating and/or moving machine parts and shall be designed for easy installation and removal for maintenance purpose. The spare equipment(s) shall be installed at designated location and tested for healthiness.
- 1.8 The Supplier shall apply oil and grease of the proper specification to suit the machinery, as is necessary for the installation of the equipment. Lubricants used for installation purpose shall be drained out and the system flushed through where necessary for applying the lubricant required for operation. The Supplier shall apply all operational lubricants to the equipment installed by him.
- 1.9 All oil, grease and other consumable used in the Works/Equipment shall be purchased in India unless the Supplier has any special requirement for the specific application of a type of oil or grease not available in India. In such is the case he shall declare in the proposal, where such oil or grease is available. He shall help Owner in establishing equivalent India make and Indian supplier. The same shall be applicable to other consumable too.
- 1.10 A cast iron or welded steel base plate shall be provided for all rotating equipment which are to be installed on a concrete base unless otherwise agreed to by the Owner. Each base plate shall support the units and its drive assembly, shall be of design with pads for anchoring the units and shall have a raised up all around and shall have threaded in air connections, if so required.
2. PROVISION FOR EXPOSURE TO HOT HUMID CLIMATE  
Outdoor equipment supplied under the specification shall be suitable for service and storage under tropical conditions of high temperature, high humidity, heavy rainfall and

environment favourable to the growth of fungi and mildew. The indoor equipment located in non- air conditioned areas shall also be same type.

## **2.1 SPACE HEATERS**

2.1.1 The heater shall be suitable for continuous operation at 240 V as supply voltage. On-off switch and fuse shall be provided.

2.1.2 One or more adequately rated permanently or thermostatically connected heater shall be supplied to prevent condensation in any compartment. The heaters shall be installed in the lower portion of the compartment and electrical connection shall be made from below the heaters to minimize deterioration of supply wire insulation. The heaters shall be suitable to maintain the compartment temperature to prevent condensation. This shall be demonstrated by tests.

2.1.3 The heaters shall be suitably designed to prevent any contact between the heater wire and the air and shall consist of coiled resistance wire centred in a metal sheath and completely encased in a highly compacted powder of magnesium oxide or other material having equal heat conducting and electrical insulation properties, or they shall consist of resistance wire wound on a ceramic and completely covered with a ceramic material to prevent any contact between the wire and the air. Alternately, they shall consist of a resistance wire mounted into a tubular ceramic body and embedded in vitreous glaze. The surface temperature of the heater shall be restricted wire is wound on a tubular ceramic body and embedded in vitreous glaze. The surface temperature of the heaters shall be restricted to a value which will not shorten the life of the heater sheaths or that of insulated wire or other component in the compartments.

## **2.2 FUNGISTATIC VARNISH**

Besides the space heaters, special moisture and fungus resistant varnish shall be applied to parts which may be subjected or predisposed to the formation of fungi due to the presence or deposit of nutrient substances. The varnish shall not be applied to any surface of part where the treatment will interfere with the operation or performance of the equipment. Such surfaces or parts shall be protected against the application of the varnish.

## **2.3 VENTILATION OPENING**

In order to ensure adequate ventilation, compartments shall have ventilation openings provided with fine wire mesh of brass or galvanized steel to prevent the entry of insects and to reduce to a minimum the entry of dirt and dust. Outdoor compartment openings shall be provided with shutter type blinds.

## **2.4 DEGREE OF PROTECTION**

The enclosures of the control cabinets, junction boxes and marshalling boxes to be installed shall provide degree of protection as detailed here under:

- a) Installed outdoor: IP 55
- b) Installed indoor in air conditioned area: IP31
- c) Installed in covered area: IP 52
- d) Installed indoor in non-air-conditioned area where possibility of entry of water is limited: IP 41

The degree of protection shall be in accordance with IS: 13947(Part-I) or IEC-947 (Part-I). Type test report for degree of protection test, on each type of the box shall be submitted for approval.

The above requirement is indicative only. Requirements as provided in respective technical specification shall prevail.

#### **10. Rating Plates, Name Plates and Labels**

1. Each main and auxiliary item of substation is to be permanently attached to it in a conspicuous position a rating plate of non-corrosive material upon which is to be engraved manufacturer's name, year of manufacture, equipment name, type or serial number together with details of the loading condition under which the item of substation in question has been designed to operate, and such diagram plates as may be required by the Owner. The rating plates of each equipment shall be according to IEC requirement.
2. All such nameplates instruction plates, rating plates shall be bilingual with Hindi inscription first followed by English. Alternatively, two separate plates one with Hindi and the other English Instruction may be provided.

#### **11. Design Improvements**

1. The bidder may note that the equipment offered by him in the bid only shall be acceptable, however, the Purchaser or the Supplier may propose changes in the specification of the equipment or quality thereof and if the parties agreed upon any such changes, the specification shall be modified accordingly.
2. If any such agreed upon change is such that it affects the price and schedule of completion, the parties shall agree in writing as to the extent of any change in the price and/or schedule of the completion before the Manufacturer proceeds with the change. Following such agreement, the provision thereof, shall be deemed to have been amended accordingly.

#### **12. Quality Assurance Programme**

1. To ensure that the equipment and services under the scope of this contract whether manufactured or performed within the Manufacturer's Work or at his SubManufacturer's premises or at the Owner's site or at any other place of work are in accordance with the specification, the Manufacturer shall adopt suitable quality assurance programme to control such activities at all points necessary.

Such programme shall be outlined by the Manufacturer and shall be finally accepted by the Owner after discussions before award of contract. A quality assurance programme of the Manufacturer shall be generally covered the following,

- a) His Organization structure for the management and implementation of the proposed quality assurance programme.
- b) Qualification data for bidder's key personnel.
- c) Documentation control System.
- d) The procedure for purchases of material, parts components and selection of subManufacturer's services including vendor analysis, source, inspection, incoming raw material inspection, verification of material purchases etc.
- e) System for shop manufacturing and, site erection control including process controls and fabrication and assembly control.
- f) Control and non-conforming items and system for corrective actions.
- g) Inspection and test procedure both for manufacture and field activities.
- h) Control of calibration and testing of measuring instruments and field activities.
- i) System for indication and appraisal of inspection status.
- j) System for quality audits.
- k) System for authorising release of manufactured product to the Purchaser.
- l) System for maintenance of records.
- m) System for handling storage and delivery. and
- n) A quality plan detailing out the specific quality control measures and procedures adopted for controlling the quality characteristics relevant to each item of equipment furnished and/or services ordered.

The Owner or his duly authorised representative reserves the right to carry out quality audit and quality surveillance of the system and procedure of the Manufacturer/his vendor's quality management and control activities.

## **2. QUALITY ASSURANCE DOCUMENTS**

The Manufacturer shall be required to submit the following quality Assurance Documents within three weeks after despatch of the equipment.

All Non-destructive Examination procedures, stress relief and weld repair procedure actually used during fabrication and report including radiography interpretation reports.

Welder identification list, listing welder's and welding operator qualification procedure and welding identification symbols.

Welder and Welding operator qualification certificate.

Raw material test reports on components as specified by the specification and for agreed to in the quality plan.

Stress relief time temperature chart/oil impregnation tile temperature chart.

Factory test results for testing required as per applicable codes/ mutually agreed quality plan/standards referred in the technical specification.

The quality plan with verification of various customer inspection points(CAP) as mutually agreed and methods used to verify the inspection and testing points in the quality plan were performed satisfactory.

### **13. Inspection, Testing and Inspection Certificate**

1. The Owner/ his duly authorised representative and/or outside inspection agency acting on behalf of the Owner shall have at all reasonable times free access to the Manufacturer's premises or Works and shall have the power at all reasonable times to inspect and examine the material and the Workmanship of the Works during its manufacture or erection and if part of the works during its manufacturing or erection and if the part of works being manufactured or assembled at other premises or works, the Manufacturer shall obtain for the Engineer and for his duly authorised representative permission to inspect as if the work were manufactured or assembled on the Manufacturer own premises or works, Inspection may be made at any stage of manufacture, despatch or at site at the option of the Owner and equipment if found unsatisfactory due to bad workmanship or quality, material is liable to be rejected.
2. All equipment being supplied shall conform to type tests and shall be subject to routine tests in accordance with relevant standards.
3. The Manufacturer shall give the Owner/Inspector thirty (30) days written notice of any material being ready for testing along with work test certificate. Such tests shall be to the Manufacturer's account. The Owner unless witnessing of the tests is virtually waived, will attend such tests with thirty (30) days of the date of which the equipment is notified as being ready for tests/inspection, the Manufacturer must ensure TPI for all inspections in line with tender documents.
4. The Owner or Inspector shall, within fifteen (15) days from the date of inspection as defined here in give notice in writing to the Manufacturer, of any objection to any drawings and all any equipment and workmanship which in his opinion is not in accordance with the contract. The Manufacturer shall give due consideration to such objections and shall either made the modifications that may be necessary to meet the said objections or shall confirm in writing to the Engineer/Inspector giving reasons therein, that no modifications are necessary to comply with the Contract.
5. When the, factory tests have been completed at the Manufacturer's or Sub-Manufacturer's Works the Owner/Inspector shall issue a certificate to this effect within fifteen (15) days after completion of tests. The completion of these tests or the issue of the certificate shall not bind the Owner to accept the equipment should, it, on further tests after erection be found not to comply with the Contract. The equipment shall be dispatched to site only after approval of test reports and issuance of dispatch clearances

in approved by the Owner.

6. In all cases where the Manufacturer provides for tests whether at the premises or at the works of the Manufacturer or of any Sub-Manufacturer. The Manufacturer except where otherwise specified shall provide free of charge such items as labour, material electrically, field water, stores, apparatus and instruments as may be reasonably demanded by the Owner/Inspector or his authorized representative to carry out effectively such tests of the equipment in accordance with the Manufacturer and shall give facilities to the Owner/inspector or to his authorised representative to accomplish testing.
7. The inspection by Owner and issue of Inspection Certificate thereon shall in no way limit the liabilities and responsibilities of the Manufacturer in respect of the agreed quality assurance programme forming a part of the Manufacturers.
8. The Owner will have the right of having at his own expenses any other test(s) of Reasonable nature carried out at Manufacturer premises or at site of in any other place in addition of aforesaid type and routine tests, to satisfy that the materials comply with the specification.
9. The Owner reserves the right for getting any field tests conducted on the completely assembled equipment at site.

#### **14. Tests**

##### **1. CHARGING**

On completion of erection of the equipment and before charging, each item of the equipment shall be thoroughly cleaned and then inspected jointly by the Owner and the Manufacturer for correctness and completeness of installation and acceptability for charging, leading to initial pre-commissioning tests at site. The list of pre-commissioning tests to be performed are given in section-7 and shall be included in the Manufacturer's quality assurance programme.

##### **2. COMMISSIONING TESTS**

- 2.1 The available instrumentation and control equipment will be used during such tests shall calibrated. However un-measurable parameters shall be taken into account in a reasonable manner by the Owner for the requirement of these tests. The tests will be conducted at the specified load points and as near the specified cycle condition as practicable. The Owner will apply proper corrections in calculation, to take into account conditions which do not correspond to the specified condition.
- 2.2 Any special equipment, tools and tackles required for the successful completion of the Commissioning Tests shall be provided by the Manufacturer, free of cost.
- 2.3 The specified tests to be conducted on equipment have been brought out in the respective chapters of the technical specification.
- 2.4 The Manufacturer shall be responsible for obtaining statutory clearances from the concerned authorities for commissioning the equipment and the switchyard. However, necessary fee shall be paid by Owner.

**15. Packing and Shipping**

All the equipment shall be suitably protected, coated, covered or boxed and crated to prevent damage or deterioration during transit, handling and storage at site till the time of erection. While packing all the materials, the limitation from the point of view of availability of Railway wagon sizes in India should be taken account. The Manufacturer shall be responsible for any loss or damage during transportation, handling and storage due to improper packing. Owner takes no responsibility of the wagons.

**16. Protection**

All coated surfaces shall be protected against abrasion, impact, discoloration and any other damages. All exposed threaded portions shall be suitably protected with either a metallic or a non-metallic protecting device. All ends of all valves and pilings and conduit equipment connections shall be properly sealed with suitable devices to protect them from damage. The parts which are likely to get rusted, due to exposure to weather should also be properly treated and protected in a suitable manner.

**17. Painting and Finishing of Metal Surfaces****1. GENERAL**

All metal surfaces shall be subjected to treatment for anti-corrosion protection. All ferrous surfaces for external use shall be hot-dip galvanized after fabrication. High tensile steel nuts and bolts and spring washers shall be electro-galvanized to service condition. All steel conductors including those used for earthing/grounding (above ground level) shall also be galvanized according to IS: 2629.

**2. HOT DIP GALVANIZING**

2.1 The minimum weight of the zinc coating shall be 610g/sq.m and minimum thickness of coating shall be 85 microns for all items thicker than 6mm. For items lower than 6mm thickness requirement of coating thickness shall be as per relevant ASTM.

2.2 The galvanized surfaces shall consist of a continuous and uniform thick coating of zinc, firmly adhering to the surface of steel; The finished surfaces shall be clean and smooth and shall be free from defects like colour patches, spots, unevenness of coating, plate which is loosely attached to the steel globules, spiky deposits, blistered surface, flaking or peeling off, etc. The presence of any of these defects noticed on visual or microscopic inspection shall render the material liable to rejection.

2.3 After galvanizing, no drilling or welding shall be performed on the galvanized parts of the equipment excepting that nuts may be threaded after galvanizing. Sodium dichromate treatment shall be provided to avoid formation of white rust after hot dip galvanization.

2.4 The galvanized steel shall be subjected to six one minute dips in copper sulphate solution as per IS-2633.

2.5 Sharp edges with radii less than 2.5mm shall be able to withstand four immersions of the standard price test. All other coating shall withstand six immersions. The following galvanizing tests should essentially be performed as per relevant Indian Standards.

- Coating
- Uniformity of zinc
- Adhesion test
- Mass of Zinc

2.6 Galvanized material must be transported properly to ensure that galvanized surfaces are not damaged during transit. Application of zinc rich paint at site shall not be allowed.

### **3. PAINTING**

3.1 All sheet steel work shall be digressed, pickled, phosphated in accordance with the IS-6005 "code of practice for phosphating iron and sheet". All surfaces which will not be easily accessible after shop assembly shall beforehand to be treated and protected for the life of the equipment. The surface which are to be finished painted after installation, shall be shop painted with at least two coats of primer. Oil, grease, dirt and swart shall be thoroughly removed by emulsion cleaning. Rust and scale shall be removed by pickling with dilute acid followed by washing with running water, rinsing with slightly alkaline hot water and drying.

3.2 After phosphating, thorough rinsing shall be carried out with clean water followed by final rinsing with dilute dichromate solution and over drying. The phosphate coating shall be sealed with application of two coats may be "flash dried" while the second coat shall be stoved.

3.3 After application of the primer, two coats of finishing synthetic enamel paint shall be applied, each coat followed by stoving. The second finishing coat shall be applied after inspection of first coat of painting.

3.4 The exterior colour of the paint shall be as per shade No.:631 of IS-5 and inside shall be glossy white. Each coat of primer and finishing paint shall be of slightly different shade to enable inspection of the painting. A small quantity of finishing paint shall be supplied for minor touching up required at site after installation of the equipment.

3.5 In case the bidder proposes to follow his own standard surface finish and protection procedures or any other established painting procedures, like electrostatic painting etc. the procedure shall be submitted along with the bids for Owner's review & approval.

### **18. Handling, Storing and Installation**

1. In accordance with the specific installation instructions as shown on manufacturer's drawings or as directed by the Owner or his representative, the Manufacturer shall unload, store, erect, install, wire test and place into commercial use all the electrical equipment

included in the contract. Equipment shall be installed in a neat, workmanlike manner so that it is level, plumb, square and properly aligned and oriented. Commercial use of switchyard equipment means completion of all site tests specified and energization at rated voltage.

2. Manufacturer may engage manufacturer's engineer to supervise the unloading, transportation to site, storing and erection. The Manufacturer shall engage the manufacturer's Engineer's for testing and commissioning of the various equipment being procured by them separately. Manufacturer shall unload, transport, store, erect, test and commission the equipment as per instructions of the manufacturer's supervisory Engineer(s)/ as per Manufacturer's approved process and shall extend full cooperation to them.
3. In case of any doubt or misunderstanding as to the correct interpretation of manufacture's drawing or instruction, necessary clarifications shall be obtained from the Owner/ Manufacturer. Manufacturer shall be held responsible for any damage to the equipment consequent to not following manufacturer's drawing/instructions correctly.
4. Where assemblies are supplied in more than one section, Manufacturer shall make all necessary mechanical and electrical connections between section including the connection between buses. Manufacturer shall also do necessary adjustments/alignments necessary for proper operation of circuit breakers, isolators and their operating mechanisms. All components shall be protected during testing and commissioning. Any equipment damaged due to negligence or carelessness or otherwise shall be replaced by the Manufacturer at his own expense.
5. Supplier shall be responsible for examining all the shipment and notify the Owner immediately of any damage, shortage, discrepancy etc. for the purpose of Owner's information only. The supplier shall submit to the Owner every week a report detailing all the receipts for any shortages or damages in transit, handling and/or in storage and erection of the equipment at Site. Any demurrage, wharf age and other such charges claimed by the transporters, railways etc. shall be to the account of the Supplier.
6. The Manufacturer shall be fully responsible for the equipment material unit the same is handed over to the Owner in an operating condition after commissioning. Manufacturer shall be responsible for the maintenance of the equipment material while in storage as well as after erection unit taken over by Owner, as well as protection of the same against theft, element of nature, corrosion, damages etc.
7. Where material/equipment is unloaded by Owner before the Manufacturer arrives at site or even when he is at site. Owner by right can hand over the same to Manufacturer and there upon it will be the responsibility of Manufacturer to store the material in an orderly and proper manner.
8. The Supplier shall be responsible for making suitable indoor storage facilities, to store all equipment which require indoor storage.
9. The words 'erection' and 'installation' used in the specification are synonymous.

10. Exposed live parts shall be placed high enough above ground to meet the requirements of electrical and other statutory safety codes.
11. The minimum phase to earth, phase to phase and section clearance for the various 132 kV, 66 kV and 33 kV sections of the switchyard are given below,

| Voltage Grade          | 220kV | 132kV | 33kV |
|------------------------|-------|-------|------|
| Phase to earth (mm)    | 2100  | 1300  | 320  |
| Phase to Phase (mm)    | 2100  | 1600  | 350  |
| Section clearance (mm) | 5000  | 4000  | 2800 |

The design and workmanship shall be in accordance with the best engineering practices to ensure satisfactory performance throughout the service life.

#### **19. Protective Guard**

Suitable guards shall be provided for protection of personnel on all exposed rotating and/or moving machine parts. All such guards with necessary spares and accessories shall be designed for easy installation and removal for maintenance purpose.

#### **20. Design Co-ordination**

1. The Manufacturer shall be responsible for the selection and design of appropriate equipment to provide the best co-ordinate performance of the entire system. The basic design requirements are detailed out in this Specification. The design of various components, sub-assemblies and assemblies shall be so done so that it facilitates easy field assembly and maintenance.
2. The Manufacturer has to coordinate designs and termination with the agencies (If any) who are LSTK vendors/ Manufacturer for the Owner if applicable. The names of agencies shall be intimated to the successful bidders.

#### **21. Design Co-Ordination Meeting**

The Manufacturer will be called upon to attend design co-ordination meeting with the Engineer, other Manufacturer's and the LSTK vendors of Owner (If any) during the period of Contract. The Manufacturer shall attend such meeting at his own cost as and when required and fully cooperate with such person and agencies involved during those discussions.

#### **22. Tools and Tackles**

The Manufacturer shall supply with the equipment one complete set of all special tools and tackles for the erection, assembly, dis-assembly and maintenance of the equipment. However, these tools and tackles shall be separately, packed and brought on to Site.

#### **23. Equipment Bases**

A cast iron or welded steel base plate shall be provided for all rotating equipment which is to be installed on a concrete base unless otherwise agreed to by the Owner. Each base plate shall support the unit and its drive assembly, shall be of a neat design with pads for anchoring the units, shall have a raised lip all around, and shall have threaded drain connections.

**24. Control Cabinets, Junction Boxes, Terminal Boxes & Marshalling Boxes for Outdoor Equipment**

1. All type of boxes, cabinets etc. shall generally conform to & be tested in accordance with IS5039/IS-8623, IEC-439, as applicable, and the clauses given below.
2. Control cabinet, junction boxes, marshalling boxes & terminal boxes shall be made of sheet steel or aluminium and shall be dust, water and vermin proof. Sheet used shall be least 2.0 mm cold rolled or 2.5 mm hot rolled. The box shall be properly braced to prevent wobbling. There shall be sufficient reinforcement to provide level surfaces, resistance to vibrations and rigidity during transportation and installation. In case of aluminium enclosed box the thickness of aluminium shall be such that it provides adequate rigidity and long life as comparable with sheet of specified thickness.
3. The enclosures of the control cabinets, junction boxes, terminal boxes & marshalling boxes shall provide a degree of protection of not less than IP 55 as per IS: 2147. The bidder shall offer type tested (IP:55) Marshalling kiosk and type test report for degree of protection test each type of box shall be furnished for arrival. After protection degree test of marshalling kiosk, 2.0 kVrms for 1 (one) minute, insulation resistance and functional test should have been conducted. In case these tests have not been carried out during IP55 test, then the Manufacturer shall carry out the IP-55 test along with these tests, at his cost.
4. Cabinet/boxes shall be free standing floor mounting type, wall mounting type or pedestal mounting type as per requirements.
5. All door, removable covers and plates shall be gasketed all around with suitably profiled EPDM gaskets. The gasket shall be tested in the presence of Owners representative. The quality of gasket shall be such that it does not get damaged/ cracked during the years of the equipment or its major overhaul whichever is earlier. All gasketed surfaces shall be smooth straight and reinforced of necessary to minimize distortion and to make a tight seal. Ventilating Louvers, if provided, shall have screen and filters. The screen shall be fine wire mesh made of brass or GI wires.
6. All boxes/cabinets shall be designed for the entry of cables from bottom by means of weather proof and dust-proof connection. Boxes and cabinet shall be designed with generous clearances to avoid interference between the wiring entering from below and any terminal blocks or accessories mounted within the base of the marshalling kiosk/box shall be provided for this purpose along with the proper blanking plates. Necessary number of cable glands shall be supplied and fitted on this gland plate. The gland shall project at least 25mm above gland plate to prevent entry of moisture in cable crutch. Gland plate shall have provision for some future glands to be provided later, if required. The Nickel plated glands shall be dust proof, screw on & double compression type and made of brass. The gland shall have provision for securing armour of the cable separately and shall be provided with earthing tag. The glands shall conform to BS:6121.
7. A 240V, single phase, 50Hz, 15amp AC plug and socket shall be provided the cabinet with

ON-OFF switch for connection of hand lamps. Plug and socket shall be of industrial grade.

8. For illumination of control cabinet, a 7 Watt LED shall be provided.
9. All control switches shall be of rotary switch type and Toggle/piano switches shall not be provided.
10. EARTHING

Positive earthing of the cabinet shall be ensured by providing two separate earthing pads. The earth wire shall be terminated on to the earthing pad and secured by the use of star of self-etching washer. Earthing of hinged door shall be done by using a separate earth wire.

11. TESTS

The marshalling kiosks shall be subject to routine tests as per 18:5039. The following routine tests shall also be conducted:

- Check for wiring
- Visual and dimension check

Marshalling kiosks shall be provided with danger plate and a diagram showing the numbering/connection/ferruling by pasting the same on the inside of the door.

25. Auxiliary Switches

The auxiliary switch shall confirm to the following type tests:

- a) Electrical endurance test -A minimum of 2000 operation for 2A DC with a time constant examination of mV drop/visual defects/temperature rise test.
- b) Mechanical endurance test. A minimum of operations as specified in the relevant IS with a subsequent checking of contact pressure test visual examination. Heat run test on contacts.

26. Terminal Blocks and Wiring

1. Control and instrument leads from the switchboards or from other equipment will be brought to terminal boxes or control cabinets in conduits. All inter-phase and external connections to equipment or to control cubicles will be made through terminal blocks.
2. Terminal blocks shall be 1100 v grade and have continuous rating to carry the maximum expected current on the terminals. Those shall be of moulded piece complete with insulated barriers stud type terminals, washers, nuts and lock nuts. Screw clamp, overall insulated, insertion type, rail mounted terminals can be used in place of stud type terminals. But preferably the terminal blocks shall be non-disconnecting stud type equivalent to Elmex type CATM4, Phoenix cage clamp type of Wedge or equivalent. The insulating material of terminal block shall be nylon 6.6 which shall be free of halogens, fluorocarbons etc.
3. Terminal block for current transformer and voltage transformer secondary leads shall be provided with test links and isolating facilities. The current transformer secondary leads shall also be provided with short circuiting and earthing facilities.
4. The terminal shall be that maximum contact area is achieved when a cable is terminated.

The terminal shall have a locking characteristic to prevent cable from escaping from the terminal clamp unless it is done intentionally.

5. The conducting part in contact with cable shall preferably be tinned or silver plated however Nickel plated copper or zinc plated steel shall also be acceptable.
6. The terminal blocks shall be of extensible design.
7. The terminal blocks shall have locking arrangement to prevent its escape from the mounting rails.
8. The terminal blocks shall be fully enclosed with removable covers of transparent, non-deteriorating type plastic material. Insulating barriers shall be provided between the terminal blocks. These barriers shall not hinder the operator from carrying out the wiring without removing the barriers.
9. Unless otherwise specified terminal blocks shall be suitable for connecting the following conductors on each side.

|    |                                  |                                      |
|----|----------------------------------|--------------------------------------|
| a) | All circuits except CT circuits  | Minimum of 2.5 sq.mm copper flexible |
| b) | All CT circuits copper flexible. | Minimum of 4 sq.mm.                  |

10. The arrangements shall be in such a manner so that it is possible to safely connect or disconnect terminals on live circuits and replace fuse links when the cabinet is live.
11. At least 20 % spare terminals shall be provided on each panel/cubicle/box and these spare terminals shall be uniformly distributed on all terminals rows.
12. There shall be a minimum clearance of 250 mm between the First bottom row of terminal block and the associated cable gland plate. Also the clearance between two rows of terminal blocks shall be a minimum of 150 mm.  
The Supplier shall furnish all wire, conduits and terminals for the necessary interphase electrical connection (where applicable) as well as between phases and common terminal boxes or control cabinets. The wiring required in these items shall be run in metallic ducts or shielded cables in order to avoid surge overvoltage either transferred through the equipment or due to transients induced from the EHV circuits.
13. All input and output terminals of each control cubicle shall be tested for surge withstand capability and transverse modes. The supplier shall also provide all necessary to achieve an impulse withstand level at the cable interfaces of equipment.

## 27. Lamps and Sockets

### 1. LAMPS

All indication lamps shall also be LED based. Socket base shall be as per IS-1258, except in the case of signal lamps.

### 2. SOCKETS

All sockets (convenience outlets) shall be suitable to accept both 5 A & 15 A pin round Standard Indian plugs. They shall be switched sockets with shutters.

### 3. HAND LAMP

A 240 Volts, single phase, 50 Hz AC plug point shall be provided in the interior of each cubicle with ON-OFF Switch for connection of hand lamps.

**4. INTERIOR LIGHTING**

Each panel shall be provided with a LED lighting fixture of Standard Indian type rates for 240 Volts, single phase, 50 Hz supply for the interior illumination of the panel during maintenance. The Fitting shall be controlled by the respective panel door switch.

**5. SWITCHES AND FUSES**

5.1 Each control panel shall be provided with necessary arrangements for receiving, distributing, isolating and fusing of DC and AC supplies for various control, signaling, lighting and space heater circuits. The incoming and sub-circuits shall be separately provided with switch fuse units. Selection of the main and Sub-circuit fuse rating shall be such as to ensure selective clearance of sub-circuit faults. Potential circuits for relaying and metering shall be protected by fuses.

5.2 All fuses be of HRC cartridge type conforming to IS:9228 mounted on plug-in type fuse bases.

5.3 Miniature circuit breakers with thermal protection and alarm contacts will also be accepted. All accessible live connection to fuse bases shall be adequately shrouded. Fuses shall have operation indicators for indicating blown fuse condition. Fuses carrier base shall have imprints of the fuse rating and voltage.

**28. Rating Plates, Name Plates and Labels**

Each main and auxiliary item of equipment is to have permanently attached to it in a conspicuous position a rating plate of non-corrosive material upon which is to be engraved manufacturer's name, year of manufacture, equipment, type or serial number together with details of loading conditions under which the item of equipment in question has been designed to operate and such diagram plates as may be required by the Owner. The rating plate shall conform to IEC requirement.

All such name plates, instruction plates rating plates etc. shall be in bilingual with Hindi inscription first followed by English. Alternatively, two separate plates one with Hindi & the other with English inscription may be provided.

**Annexure-A:****List of Standards and Specifications/ General Standards/ Indian Electricity Rules**

|                   |                                                                                                             |
|-------------------|-------------------------------------------------------------------------------------------------------------|
| IS-5:             | Colours for Ready Mixed Paints and Enamels IS-335 Insulating Oil for Transformers and switchgear            |
| IS-375:           | Marketing and Arrangement for Bus-bars, Main Connection & Auxiliary Winding                                 |
| IS-617:           | Aluminium and Aluminium alloy & Ingots and Castings for General Engineering Purposes                        |
| IS-1448:          | Methods of Test for Petroleum and its Products.                                                             |
| IS-2071:          | Measuring Devices                                                                                           |
| IS-2147:          | Degree of Protection Provided by Enclosures of for Low voltage switch gear and control Gear                 |
| IS-2165:          | Phase-to-Phase Insulation Co-ordination, Principles and Rules                                               |
| IS-2362:          | Determination of Water by the Karl fisher Method                                                            |
| IS-3043:          | Codes of practice for earthing                                                                              |
| IS-3202:          | Code of Practice for climate proofing of electrical equipment                                               |
| IS-3637:          | Gas Operated Relays                                                                                         |
| IS-6103:          | Methods of Test for specific resistance (Resistivity) of Electrical Insulating Liquids                      |
| IS-6104:          | Method of Test for Interfacial Tension of Oil against Water by the Ring Method.                             |
| IS-6262:          | Method for Determination of Electric strength of insulating liquids.                                        |
| IS-6792:          | Method for Radio Interference Tests on High Voltage Insulators                                              |
| IEC-214:          | On-Load Tap-Changers                                                                                        |
| IEC-289:          | Reactors                                                                                                    |
| IEC-354:          | Loading Guide for Oil Immersed power transformers.                                                          |
| IEC-551:          | Determination of Transformer and reactor Sound levels                                                       |
| ANSI-C57, 12, 80: | General requirements for Distribution, Power and Regulating Transformers.                                   |
| ANSI-C57, 12, 90: | Test Code for Distribution, Power and Regulation Transformers.                                              |
| ANSI-C57, 16:     | Terminology & Test Code for current limiting Reactors.                                                      |
| ANSI-C57, 21:     | Requirements Terminology and Test Code for Shunt Reactors Rates over 500 KVA.                               |
| ANSI-C57, 92:     | Guide for loading Oil-Immersed Power Transformer up to and including 100 MVA with 55oC or 65oC Winding Rise |
| ANSI-CG, IEEE-4:  | Standard Techniques for high Voltage Testing                                                                |
| NEMA-TR-1:        | Transformers, Regulators and Reactors                                                                       |
| IS-4379:          | Identification of the Contents of Industrial Gas Cylinders                                                  |

**1. Surge Arresters**

|           |                                                                                                             |
|-----------|-------------------------------------------------------------------------------------------------------------|
| IS-3070:  | Lightning arrestors for alternating current systems: Metal (part-3) oxide lightning arrestors without gaps. |
| IEC 99-4: | Metal oxide surge arresters without gaps                                                                    |

## **2. Cubicles and Panels & Other related Equipment**

- IS:722: AC Electricity Meters (P1 to P9)  
IS 1248 Direct acting indicating analogue electrical measuring instruments their accessories.  
IS722, IS-1248: (PO-3) Electrical relays for power system protection.  
IS-3231, 3231, IEC-68.2.2: Basic environmental testing procedures Part 2: Test B: Dry heat  
IEC-529: Degree of Protection provided by enclosures  
IEC-158: Low Voltage control gear, Manufacturers  
IEC-439: Low voltage switchgear and control gear assemblies  
ANSI-C37.20: Switchgear assemblies, including metal enclosed bus.  
ANSI-C37.50: Test Procedures for low voltage alternating current power circuit breakers  
ANSI-C39: Electric Measuring instrument.  
ANSI-C83: Components for electric equipment  
IS:8623: Specification for sugar NEMA-AB-Moulded Case circuit and systems

## **3. Material and Workmanship Standards**

- IS-1363: Hexagon head bolts, screws and nuts of product grade C.  
IS-1364: Hexagon head bolts, screws and nuts of products grades A and B  
IS-3138: Hexagonal Bolts and nuts (M42 to M150)  
IS-898: Fasteners: Bolts, screws and studs

## **4. Wire and Cables**

- IS-694: PVC insulated cables for working voltages upto and including 1100Volts.  
IS-1255: Code of practice for installation and maintenance of power cables upto and including 33 kV rating.  
IS-1554: PVC insulated (heavy duty) electric cables (part 1) for working voltage upto and including 1100 V Part (2) for working voltage from 3.3 upto including 11 kV.  
IS-1753: Aluminium conductors for insulated cables  
IS-2982: Copper conductors in insulated cables and cords.  
IS-3961: Recommended current rating for cables.  
IS-3975: Mild steel wires, formed wires and tapes for armouring of cables  
IS-5831: PVC insulated and sheath of electric cables  
IS-6380: Elastomeric insulating and sheath of electric cables.  
IS-7098: Cross linked polyethylene insulated PVC sheathed cables for working voltage up to and including 1100 volts. Part (2) Cross-linked polyethylene insulated PVC sheathed cables for working voltage from 3.3 kV up to and including 33 kV.  
IS-8130: Conductors for insulated electrical cables and flexible cords.  
IS-10418: Specification for drums for electrical cables. IEC-96 Radio Frequency cables  
IEC-183: Guide to the selection of High Voltage Cables.  
IEC-189: Low frequency cables and wires with PVC insulation and PVC Sheath  
IEC-227: Polyvinyl Chloride insulated cables of rated voltages up to and including 450/750 V.  
IEC228L Conductors of insulated cables.  
IEC-230: Impulse tests on cables and their accessories.  
IEC-287: Calculation of the continuous current rating of cables (100% load factor).

- IEC-304: Standard colours for insulation for low frequency cables and wires.
- IEC-331: Fire resisting characteristics of Electric cables.
- IEC-332: Tests on electric cables under fire conditions
- IEC-502: Extruded solid dielectric insulated power cable for rates voltages from 1 kV up to 30 kV.
- IEC-754: Tests on gases evolved during combustion of electric cables.
- NEMA-WC1: Asbestos and asbestos-varnished cloth and asbestos thermoplastic insulated wire and cable
- NEMA-WC2: Steel armour and associated covering for impregnated paper insulated cables
- NEMA-WC3: Rubber insulated wire and cable for transmission and distribution of electrical energy.
- NEMA-WC5: Thermoplastic insulated wire and cable for the transmission and distribution of electric energy.
- NEMA-WC7: Cross linked thermo setting polyethylene insulated wire and cable for the transmission and distribution of electrical energy.
- NEMA-WC8: Ethylene-propylene-rubber insulated wire and cable for the transmission and distribution of electrical energy.
- NEMA-W67: Cross linked thermo setting polyethylene
- IS-659: Safety code for air conditioning
- IS-1391: Room air conditioners.
- IS-6272: Industrial cooling fans.

## **5. Galvanizing**

- IS-209: Zinc Ingot.
- IS-2629: Recommended practice for Hot-Dip galvanizing on iron and steel.
- IS-2629: Methods for testing uniformity of coating of zinc coating articles.
- ASTM-a-123: Specification for zinc (Hot galvanizing) coatings on products fabricated from rolled, pressed and forged steel shapes, plates, bars and strips.
- ASTM-A-153: Specification for Zinc coating (Hot Dip) on iron and steel hardware
- ASTM-A-239: Test method for locating the thinnest. Spot in a Zinc (galvanised) coating on iron and steel articles by the preece test (Copper sulfated dip).

**SECTION-4**  
**GUARANTEED TECHNICAL PARTICULARS**

**A. COUPLING DEVICES**

1. Name of Manufacturer and Country
2. Type, Model and Catalogue Number
3. Whether suitable for mounting Outdoor in Switchyard & Type of mounting
4. Maximum temperature limit for satisfactory operation of coupling device mounted outdoor
5. Net weight
6. Nominal Primary Side Impedance
7. Nominal secondary Side Impedance
8. Composite loss within Passband
9. Return loss within Passband
10. Available Bandwidth (with 4400/6600/ 8800 pF CVTs)
11. Nominal Peak Envelope Power (with Distortion and Intermodulation Products 80 dB Down)
12. Maximum number of PLC terminals that can be connected in parallel:
  - (a) 20 W (P.E.P.) PLC terminals
  - (b) 40 W (P.E.P.) PLC terminals
  - (c) 80 W (P.E.P.) PLC terminals

13. Power Frequency Impedance between primary terminal and Earth Terminals of Coupling Device.
14. 1 Minute Power Frequency Insulation level between Primary and Secondary Terminals of Coupling Device
15. Impulse (1.2/50 micro-sec.) Withstand Level between Primary and Secondary Terminals of Coupling Device
16. Power Frequency Current Carrying Capacity of Drain Coil (or Primary Winding of Matching Transformer).
  - (a) Continuous current
  - (b) Short time current for 0.2 sec.
  - (c) Inductance of drain coil with Tolerances (at 50 Hz)
17. Surge Arrester in Primary Side of Coupling Device:
  - (a) Type model & catalogue number
  - (b) Power frequency sparkover voltage
  - (c) Type of construction
  - (d) Maximum permissible arrestor Discharge current with 8/20 micro Sec. impulse discharge
  - (e) Maximum permissible short time Current (2.2 micro sec.)
  - (f) Power frequency discharge current For 0.2 sec.
  - (g) Impulse spark over voltage 1.2/50 Micro sec.
  - (h) Rated voltage
  - (i) Whether Site tunable

18. Surge arrester in Secondary Side of Coupling Device
  - (a) Type model & catalogue number
  - (b) Power frequency spark over voltage
  - (c) Impulse spark over voltage (1.2/50 Micro sec.
19. Details of interlock provided with cover enclosed -
20. Overall dimensions
21. No of H.F. terminals provided for carrier equipment. connection

**B. HIGH FREQUENCY CABLE**

1. Name of Manufacturer and Country
2. Type, Model and Catalogue No.
3. Applicable standards
4. Characteristic Impedance
5. Rated Capacitance
6. Service Voltage
7. Attenuation per km. of cable at various Carrier Frequencies in the Range of 50 to 500 KHz. (Typically at 50,100,200,300, 400,500 KHz)
8. Withstand Test Voltage (RMS) between conductor and Sheath
9. Details and particulars of Insulation
10. Loop Resistance per Km (Typical at 20°C)
11. Details of Armouring
12. Number and Diameter of Stranded Conductor

13. Overall Diameter of Cable
14. Net weight per Km.
15. Minimum bending radius
16. Earthing detail of H. F. Cable
17. Packing length per drum
18. Construction drawing, type test & performance reports enclosed or not

**C. POWER LINE CARRIER TERMINAL FOR SPEECH & DATA TRANSMISSION**

1. Name of Manufacturer and Country
2. Type, Model and Catalogue No.
3. Type of Modulation
4. Mode of transmission
5. Carrier Frequency Range
6. Nominal Carrier Frequency Band in either direction of transmission
7. Return loss within the Nominal Carrier Frequency Band
8. Effectively Transmitted V.F Band
9. Return Loss within the Effectively Transmitted Voice Frequency Band.
10. H. F. Oscillator Details
11. I. F. Oscillator Details
12. Frequency Difference between the V.F. Input and V.F. Output of a pair of terminals connected back to back for permissible Ambient Temperature and supply voltage variations.
13. Maximum H. F. Amplifier output with Single/Multiple tone keying (Peak Envelope Power).
14. Nominal carrier frequency Power (Peak

Envelop Power) at output terminals.

15. H. F. Impedance at output of carrier terminals.
16. Stability of the carrier frequency.
17. Improvement in S/N due to compander
18. Whether carrier is suppressed or reduced during transmission of signal
19. Whether frequency locking between Tx/Rx provided.
20. Automatic gain control range and regulation
21. Level of spurious emission at
  - (a) Edge of nominal Carrier Frequency Band
  - (b) 4.0 KHz away from nominal carrier Frequency band.
  - (c) 8.0 KHz away from nominal carrier Frequency band.
22. Relative level at V. F. 4 wire terminating points:
  - (a) Send leg
  - (b) Receive leg
23. Permissible limits for level variation with frequency relative to 800 Hz in a speech channel (without companders) transmitted over a pair of terminals connected back to back
24. Level of telephone signalling channel:
  - a. Input level
  - b. Output level
25. Near and far end cross talk due to telephone signalling channel in a pair of PLC Terminals (without companders) connected back to back.

26. Pulse distortion of telephone signalling channel when operated at a signalling speed of 10 pps and with a mark to space ratio of 40/60 in PLC terminals connected back to back.
27. Psophometric Noise contribution of a pair of PLC terminals connected back to back
28. Group delay distortion in the frequency band relevant to the transmission of protection signals.
29. Performance Under Noise condition:
  - a. Noise generated within terminal
  - b. Additional noise introduced when terminals are connected back to back at repeater station
  - c. Noise Bandwidth.
30. Power supply requirements:
  - (a) Voltage
  - (b) Permissible voltage variation
  - (c) Maximum current
  - (d) Quiescent Current
31. Installation details
32. Insulation level
33. Meters provided on Test Panel, their range and purpose.
34. Is the equipment suitable to work in Dust laden atmosphere?
35. Whether interior lamps with door switch is provided in cabinets
36. Over all dimensions (Cabinet)
  - (a) Length mm
  - (b) Width mm
  - (c) Height mm

- 37. Weight
- 38. Earthing detail of PLC Cabinet
- 39. Whether Tx/Rx loop-back facility is available for testing locally
- 40. Whether site tunable

**D. POWER LINE CARRIER TERMINAL FOR NETWORK PROTECTION**

- 1. Name of Manufacturer and country
- 2. Type, Model and Catalogue No.
- 3. Type of Modulation
- 4. Mode of transmission
- 5. Carrier Frequency Range
- 6. Nominal Carrier Frequency Band in either direction of transmission
- 7. Return loss within the Nominal Carrier Frequency Band
- 8. Effectively Transmitted V.F Band
- 9. Return Loss within the Effectively Transmitted Voice Frequency Band.
- 10. H. F. Oscillator Details
- 11. I. F. Oscillator Details
- 12. Frequency Difference between the V.F. Input and V.F. Output of a pair of terminals connected back to back for permissible Ambient Temperature and supply voltage variations.
- 13. Maximum H. F. Amplifier output with Single/Multiple tone keying (Peak Envelope Power).
- 14. Nominal carrier frequency Power (Peak Envelop Power) at output terminals.
- 15. H. F. Impedance at output of carrier terminals.

16. Stability of the carrier frequency.
17. Improvement in S/N due to compander
18. Whether carrier is suppressed or reduced during transmission of signal
19. Whether frequency locking between Tx/Rx provided
20. Level of spurious emission at
  - (a) Edge of nominal Carrier Frequency Band
  - (b) 4.0 KHz away from nominal carrier Frequency band
  - (c) 8.0 KHz away from nominal carrier frequency band.
21. Whether frequency locking between Tx/Rx provided
22. Relative level at V. F. 4 wire terminating points:
  - (a) Send leg
  - (b) Receive leg
23. Permissible limits for level variation with frequency relative to 800 Hz in a speech channel (without companders) transmitted over a pair of terminals connected back to back
24. Variation in overall loss of speech circuit with a pair to PLC terminals connected back (without Companders & limiters) when voice frequency input level changes from 10 to 0 dBm
25. Psophometric Noise contribution of a pair of PLC terminals connected back to back
26. Noise frequency Band width
27. Group delay distortion in the frequency band relevant to the transmission of protection signals.

28. Signal Delay with Two PLC Terminals connected back to back
29. Power supply requirements:
  - (a) Voltage
  - (b) Permissible voltage variation
  - (c) Maximum current
30. Installation details
31. Meters provided on Test Panel, their range and purpose.
32. Is the equipment suitable to work in Dust laden atmosphere without air conditioning?
33. Whether interior lamps with door switch is provided in cabinets
34. Over all dimensions
  - (a) Length           mm
  - (b) Width           mm
  - (c) Height           mm
35. Weight
36. Insulation level
37. Cabinet earthing details
38. Whether indication is available in sending end panel for receipt/execution of trip signal/command at remote end.
39. Whether Tx/Rx loop-back facility is available for testing locally
40. Whether site tunable

**E. VF TRANSMISSION TERMINAL FOR NETWORK PROTECTION SIGNALS (PROTECTION COUPLER)**

1. Name of Manufacturer and Country
2. Type, Model and Catalogue Number
3. Whether equipment works on frequency shift

principle of coded signal principle

4. Whether Equipment is suitable for Independently Protecting Two Circuits
5. Frequencies used in the equipment for transmission of signal for coded Signal transmission
  - (a) Guard frequency
  - (b) Working frequency (Trip System - I)
  - (c) Working frequency (Trip System - II)
  - (d) Working frequency (Trip System I&II)
6. Criteria used for command Transmission
7. Whether equipment is protected against Tripping by Spurious Signals.
8. Transmission time corresponding to telegraph speed for transmission on PLCC channel of coded signal
  - (a) 600 Bds.
  - (b) 400 Bds.
  - (c) 200 Bds.
9. Whether in the presence of spurious signals as well as Protection Signals simultaneously, the equipment will initiate a Trip Command.
10. Mode of Transmission of guard signal
11. Whether equipment is suitable for Direct Circuit Breaker tripping.
12. Maximum number of Noises Impulses pps in Presence of which the equipment will satisfactorily perform its duty.
13. Signal Delay with Two Terminals connected back to back
14. Whether the Command Signal is acknowledged at receiving end and in the event of non-receipt of the correct signal, the

- command is repeated or not by the transmitter?
15. Whether it is possible to alter the priority of commands of various codes at site.
  16. What are the performance based results under severe line noise conditions for
    - (a) False trip probability
    - (b) Fail to trip probability
  17. Transmitter Input Requirements (Contact Ratings)
    - (a) Voltage
    - (b) Current
    - (c) Power
    - (d) No. of Contacts
  18. Receiver Output (Contact Rating)
    - (a) Voltage
    - (b) Current
    - (c) Power
    - (d) No. of Contracts
  19. Additional facilities provided in Receiver output
  20. Supervisory and Alarm Contact Facilities
    - (a) Current
    - (b) Voltage
    - (c) No. of contacts
  21. Installation
  22. Power Supply
    - (a) Voltage
    - (b) Current
    - (c) Power
  23. Type and number of counters for recording the number of Trip Commands sent and number of Trip Commands received
  24. Whether loop test is possible

25. Insulation Level
26. Whether the equipment is suitable for transmitting and receiving more than two independent commands (please give full details)

**F. EPAX**

- 1 Name of manufacturer
- 2 Type of Model
- 3 Number of subscriber lines
  - (a) Wired for
  - (b) Equipped for
- 4 Number of trunk lines provided
  - (a) Wired for
  - (b) Equipped for
- 5 Whether the facility to bar subscriber's access to the carrier lines is provided during maintenance?
- 6 Whether P.G. lockout facility provided along with alarm?
- 7 Whether alarm type fuse provided for audio and visual indications?
- 8 Whether suitable for satisfactory operation in conjunction with PLCC system
- 9 Signalling Pulse Width
  - (a) Engage Pulse
  - (B) Priority Pulse
  - (C) Digit pulse
  - (D) Inter digit pause
  - (E) Release Pulse
- 10 Operating voltage
- 11 Power requirement
- 12 Overall dimensions (W x D x H)
- 13 Mounting arrangement

- 14 Weight
- 15 Type of switching
- 16 Whether four-wire interfaces are built-in
- 17 In case four-wire interfaces are built-in maximum number of PLC terminals which can be connected to a single EPAX
- 18 Whether self-diagnostics and monitoring features are built-in
- 19 Whether the following facilities are built-in
  - (a) Priority cutting
  - (b) Conference
  - (c) Alternate routing
  - (d) Call transfer
- 20 Maximum loop resistance permissible
  - (a) For trunk line
  - (b) subscriber lines
- 21 Whether suitable to work in conjunction with electromechanical PAX
- 22 Whether suitable to work with DOT leased lines as per specification